RTEMS POSIX API User's Guide

Edition 4.6.1, for RTEMS 4.6.1

30 August 2003

On-Line Applications Research Corporation

On-Line Applications Research Corporation
TEXinfo 2002-11-25.11

COPYRIGHT © 1988 - 2003.
On-Line Applications Research Corporation (OAR).

The authors have used their best efforts in preparing this material. These efforts include the development, research, and testing of the theories and programs to determine their effectiveness. No warranty of any kind, expressed or implied, with regard to the software or the material contained in this document is provided. No liability arising out of the application or use of any product described in this document is assumed. The authors reserve the right to revise this material and to make changes from time to time in the content hereof without obligation to notify anyone of such revision or changes.

The RTEMS Project is hosted at `http://www.rtems.com`. Any inquiries concerning RTEMS, its related support components, its documentation, or any custom services for RTEMS should be directed to the contacts listed on that site. A current list of RTEMS Support Providers is at `http://www.rtems.com/support.html`.

Table of Contents

Preface 1

1 Process Creation and Execution Manager . . . 3

1.1 Introduction 3
1.2 Background 3
1.3 Operations 3
1.4 Directives 3
1.4.1 fork - Create a Process 4
1.4.2 execl - Execute a File 5
1.4.3 execv - Execute a File 6
1.4.4 execle - Execute a File 7
1.4.5 execve - Execute a File 8
1.4.6 execlp - Execute a File 9
1.4.7 execvp - Execute a File 10
1.4.8 pthread_atfork - Register Fork Handlers 11
1.4.9 wait - Wait for Process Termination 12
1.4.10 waitpid - Wait for Process Termination 13
1.4.11 _exit - Terminate a Process 14

2 Signal Manager 15

2.1 Introduction 15
2.2 Background 15
2.2.1 Signals 15
2.2.2 Signal Delivery 16
2.3 Operations 16
2.3.1 Signal Set Management 16
2.3.2 Blocking Until Signal Generation 16
2.3.3 Sending a Signal 17
2.4 Directives 17
2.4.1 sigaddset - Add a Signal to a Signal Set 18
2.4.2 sigdelset - Delete a Signal from a Signal Set 19
2.4.3 sigfillset - Fill a Signal Set 20
2.4.4 sigismember - Is Signal a Member of a Signal Set 21
2.4.5 sigemptyset - Empty a Signal Set 22
2.4.6 sigaction - Examine and Change Signal Action . . . 23
2.4.7 pthread_kill - Send a Signal to a Thread 24
2.4.8 sigprocmask - Examine and Change Process Blocked Signals 25
2.4.9 pthread_sigmask - Examine and Change Thread Blocked Signals 26
2.4.10 kill - Send a Signal to a Process 27

2.4.11 sigpending - Examine Pending Signals 28
2.4.12 sigsuspend - Wait for a Signal 29
2.4.13 pause - Suspend Process Execution 30
2.4.14 sigwait - Synchronously Accept a Signal 31
2.4.15 sigwaitinfo - Synchronously Accept a Signal 32
2.4.16 sigtimedwait - Synchronously Accept a Signal with Timeout 33
2.4.17 sigqueue - Queue a Signal to a Process 34
2.4.18 alarm - Schedule Alarm 35

3 Process Environment Manager 37

3.1 Introduction 37
3.2 Background 37
3.2.1 Users and Groups 37
3.2.2 User and Group Names 38
3.2.3 Environment Variables 38
3.3 Operations 38
3.3.1 Accessing User and Group Ids 38
3.3.2 Accessing Environment Variables 38
3.4 Directives 39
3.4.1 getpid - Get Process ID 40
3.4.2 getppid - Get Parent Process ID 41
3.4.3 getuid - Get User ID 42
3.4.4 geteuid - Get Effective User ID 43
3.4.5 getgid - Get Real Group ID 44
3.4.6 getegid - Get Effective Group ID 45
3.4.7 setuid - Set User ID 46
3.4.8 setgid - Set Group ID 47
3.4.9 getgroups - Get Supplementary Group IDs 48
3.4.10 getlogin - Get User Name 49
3.4.11 getlogin_r - Reentrant Get User Name 50
3.4.12 getpgrp - Get Process Group ID 51
3.4.13 setsid - Create Session and Set Process Group ID 52
3.4.14 setpgid - Set Process Group ID for Job Control .. 53
3.4.15 uname - Get System Name 54
3.4.16 times - Get process times 55
3.4.17 getenv - Get Environment Variables 56
3.4.18 setenv - Set Environment Variables 57
3.4.19 ctermid - Generate Terminal Pathname 58
3.4.20 ttyname - Determine Terminal Device Name 59
3.4.21 ttyname_r - Reentrant Determine Terminal Device Name 60
3.4.22 isatty - Determine if File Descriptor is Terminal 61
3.4.23 sysconf - Get Configurable System Variables 62

4 Files and Directories Manager 63

4.1 Introduction 63
4.2 Background 64
4.2.1 Path Name Evaluation 64
4.3 Operations 64
4.4 Directives 64
4.4.1 opendir - Open a Directory 65
4.4.2 readdir - Reads a directory 66
4.4.3 rewinddir - Resets the readdir() pointer 67
4.4.4 scandir - Scan a directory for matching entries . . . 68
4.4.5 telldir - Return current location in directory stream 69
4.4.6 closedir - Ends directory read operation 70
4.4.7 chdir - Changes the current working directory 71
4.4.8 fchdir - Changes the current working directory . . . 72
4.4.9 getcwd - Gets current working directory 73
4.4.10 open - Opens a file 74
4.4.11 creat - Create a new file or rewrite an existing one 76
4.4.12 umask - Sets a file creation mask. 78
4.4.13 link - Creates a link to a file 79
4.4.14 symlink - Creates a symbolic link to a file 80
4.4.15 readlink - Obtain the name of a symbolic link destination 81
4.4.16 mkdir - Makes a directory 82
4.4.17 mkfifo - Makes a FIFO special file 83
4.4.18 unlink - Removes a directory entry 84
4.4.19 rmdir - Delete a directory 85
4.4.20 rename - Renames a file 87
4.4.21 stat - Gets information about a file 89
4.4.22 fstat - Gets file status 90
4.4.23 lstat - Gets file status 91
4.4.24 access - Check permissions for a file 92
4.4.25 chmod - Changes file mode. 93
4.4.26 fchmod - Changes permissions of a file 94
4.4.27 getdents - Get directory entries 95
4.4.28 chown - Changes the owner and/or group of a file. 96
4.4.29 utime - Change access and/or modification times of an inode 97
4.4.30 ftruncate - truncate a file to a specified length . . 98
4.4.31 truncate - truncate a file to a specified length . . . 99
4.4.32 pathconf - Gets configuration values for files . . . 100
4.4.33 fpathconf - Gets configuration values for files . . 102
4.4.34 mknod - create a directory 104

5 Input and Output Primitives Manager 107

5.1 Introduction 107
5.2 Background 107
5.3 Operations 107
5.4 Directives 108
5.4.1 pipe - Create an Inter-Process Channel 109
5.4.2 dup - Duplicates an open file descriptor 110
5.4.3 dup2 - Duplicates an open file descriptor 111
5.4.4 close - Closes a file. 112
5.4.5 read - Reads from a file. 113
5.4.6 write - Writes to a file 115
5.4.7 fcntl - Manipulates an open file descriptor 116
5.4.8 lseek - Reposition read/write file offset 118
5.4.9 fsync - Synchronize file complete in-core state with that on disk 119
5.4.10 fdatasync - Synchronize file in-core data with that on disk. 120
5.4.11 mount - Mount a file system 121
5.4.12 unmount - Unmount file systems 122
5.4.13 aio_read - Asynchronous Read 123
5.4.14 aio_write - Asynchronous Write 124
5.4.15 lio_listio - List Directed I/O 125
5.4.16 aio_error - Retrieve Error Status of Asynchronous I/O Operation 126
5.4.17 aio_return - Retrieve Return Status Asynchronous I/O Operation 127
5.4.18 aio_cancel - Cancel Asynchronous I/O Request 128
5.4.19 aio_suspend - Wait for Asynchronous I/O Request 129
5.4.20 aio_fsync - Asynchronous File Synchronization 130

6 Device- and Class- Specific Functions Manager 131

6.1 Introduction 131
6.2 Background 131
6.3 Operations 131
6.4 Directives 131
6.4.1 cfgetispeed - Reads terminal input baud rate 132
6.4.2 cfgetospeed - Reads terminal output baud rate .. 133
6.4.3 cfsetispeed - Sets terminal input baud rate 134
6.4.4 cfsetospeed - Sets terminal output baud rate 135
6.4.5 tcgetattr - Gets terminal attributes 136
6.4.6 tcsetattr - Set terminal attributes 137
6.4.7 tcsendbreak - Sends a break to a terminal 138
6.4.8 tcdrain - Waits for all output to be transmitted to the terminal. 139

6.4.9 tcflush - Discards terminal data 140
6.4.10 tcflow - Suspends/restarts terminal output. 141
6.4.11 tcgetpgrp - Gets foreground process group ID . . 142
6.4.12 tcsetpgrp - Sets foreground process group ID . . 143

7 Language-Specific Services for the C Programming Language Manager 145

7.1 Introduction 145
7.2 Background 145
7.3 Operations 145
7.4 Directives 146
7.4.1 setlocale - Set the Current Locale 147
7.4.2 fileno - Obtain File Descriptor Number for this File 148
7.4.3 fdopen - Associate Stream with File Descriptor . . 149
7.4.4 flockfile - Acquire Ownership of File Stream 150
7.4.5 ftrylockfile - Poll to Acquire Ownership of File Stream 151
7.4.6 funlockfile - Release Ownership of File Stream . . 152
7.4.7 getc_unlocked - Get Character without Locking . . 153
7.4.8 getchar_unlocked - Get Character from stdin without Locking 154
7.4.9 putc_unlocked - Put Character without Locking 155
7.4.10 putchar_unlocked - Put Character to stdin without Locking 156
7.4.11 setjmp - Save Context for Non-Local Goto 157
7.4.12 longjmp - Non-Local Jump to a Saved Context 158
7.4.13 sigsetjmp - Save Context with Signal Status for Non-Local Goto 159
7.4.14 siglongjmp - Non-Local Jump with Signal Status to a Saved Context 160
7.4.15 tzset - Initialize Time Conversion Information . . 161
7.4.16 strtok_r - Reentrant Extract Token from String 162
7.4.17 asctime_r - Reentrant struct tm to ASCII Time Conversion 163
7.4.18 ctime_r - Reentrant time_t to ASCII Time Conversion 164
7.4.19 gmtime_r - Reentrant UTC Time Conversion . . 165
7.4.20 localtime_r - Reentrant Local Time Conversion 166
7.4.21 rand_r - Reentrant Random Number Generation 167

8 System Databases Manager 169

8.1 Introduction 169
8.2 Background 169
8.3 Operations 169
8.4 Directives 169
8.4.1 getgrgid - Get Group File Entry for ID 170
8.4.2 getgrgid_r - Reentrant Get Group File Entry 171
8.4.3 getgrnam - Get Group File Entry for Name 172
8.4.4 getgrnam_r - Reentrant Get Group File Entry for Name 173
8.4.5 getpwuid - Get Password File Entry for UID 174
8.4.6 getpwuid_r - Reentrant Get Password File Entry for UID 175
8.4.7 getpwnam - Password File Entry for Name 176
8.4.8 getpwnam_r - Reentrant Get Password File Entry for Name 177

9 Semaphore Manager 179

9.1 Introduction 179
9.2 Background 179
9.2.1 Theory 179
9.2.2 "sem_t" Structure 179
9.2.3 Building a Semaphore Attribute Set 179
9.3 Operations 180
9.3.1 Using as a Binary Semaphore 180
9.4 Directives 180
9.4.1 sem_init - Initialize an unnamed semaphore 181
9.4.2 sem_destroy - Destroy an unnamed semaphore 182
9.4.3 sem_open - Open a named semaphore 183
9.4.4 sem_close - Close a named semaphore 185
9.4.5 sem_unlink - Unlink a semaphore 186
9.4.6 sem_wait - Wait on a Semaphore 187
9.4.7 sem_trywait - Non-blocking Wait on a Semaphore 188
9.4.8 sem_timedwait - Wait on a Semaphore for a Specified Time 189
9.4.9 sem_post - Unlock a Semaphore 190
9.4.10 sem_getvalue - Get the value of a semaphore 191

10 Mutex Manager 193

10.1 Introduction 193
10.2 Background 193
10.2.1 Mutex Attributes 193
10.2.2 PTHREAD_MUTEX_INITIALIZER 194
10.3 Operations 194
10.4 Services 194
10.4.1 pthread_mutexattr_init - Initialize a Mutex Attribute Set 195
10.4.2 pthread_mutexattr_destroy - Destroy a Mutex Attribute Set 196
10.4.3 pthread_mutexattr_setprotocol - Set the Blocking Protocol 197
10.4.4 pthread_mutexattr_getprotocol - Get the Blocking Protocol 198
10.4.5 pthread_mutexattr_setprioceiling - Set the Priority Ceiling 199
10.4.6 pthread_mutexattr_getprioceiling - Get the Priority Ceiling 200
10.4.7 pthread_mutexattr_setpshared - Set the Visibility 201
10.4.8 pthread_mutexattr_getpshared - Get the Visibility 202
10.4.9 pthread_mutex_init - Initialize a Mutex 203
10.4.10 pthread_mutex_destroy - Destroy a Mutex 204
10.4.11 pthread_mutex_lock - Lock a Mutex 205
10.4.12 pthread_mutex_trylock - Poll to Lock a Mutex 206
10.4.13 pthread_mutex_timedlock - Lock a Mutex with Timeout 207
10.4.14 pthread_mutex_unlock - Unlock a Mutex 208
10.4.15 pthread_mutex_setprioceiling - Dynamically Set the Priority Ceiling 209
10.4.16 pthread_mutex_getprioceiling - Get the Current Priority Ceiling 210

11 Condition Variable Manager 211

11.1 Introduction 211
11.2 Background 211
11.3 Operations 211
11.4 Directives 211
11.4.1 pthread_condattr_init - Initialize a Condition Variable Attribute Set 212
11.4.2 pthread_condattr_destroy - Destroy a Condition Variable Attribute Set 213
11.4.3 pthread_condattr_setpshared - Set Process Shared Attribute 214

11.4.4 pthread_condattr_getpshared - Get Process Shared Attribute 215
11.4.5 pthread_cond_init - Initialize a Condition Variable 216
11.4.6 pthread_cond_destroy - Destroy a Condition Variable 217
11.4.7 pthread_cond_signal - Signal a Condition Variable 218
11.4.8 pthread_cond_broadcast - Broadcast a Condition Variable 219
11.4.9 pthread_cond_wait - Wait on a Condition Variable 220
11.4.10 pthread_cond_timedwait - Wait with Timeout a Condition Variable 221

12 Memory Management Manager 223

12.1 Introduction 223
12.2 Background 223
12.3 Operations 223
12.4 Directives 223
12.4.1 mlockall - Lock the Address Space of a Process 224
12.4.2 munlockall - Unlock the Address Space of a Process 225
12.4.3 mlock - Lock a Range of the Process Address Space 226
12.4.4 munlock - Unlock a Range of the Process Address Space 227
12.4.5 mmap - Map Process Addresses to a Memory Object 228
12.4.6 munmap - Unmap Previously Mapped Addresses 229
12.4.7 mprotect - Change Memory Protection 230
12.4.8 msync - Memory Object Synchronization 231
12.4.9 shm_open - Open a Shared Memory Object 232
12.4.10 shm_unlink - Remove a Shared Memory Object 233

13 Scheduler Manager 235
13.1 Introduction 235
13.2 Background 235
13.2.1 Priority 235
13.2.2 Scheduling Policies 235
13.3 Operations 236
13.4 Directives 236
13.4.1 sched_get_priority_min - Get Minimum Priority Value 237
13.4.2 sched_get_priority_max - Get Maximum Priority Value 238
13.4.3 sched_rr_get_interval - Get Timeslicing Quantum 239
13.4.4 sched_yield - Yield the Processor 240

14 Clock Manager 241
14.1 Introduction 241
14.2 Background 241
14.3 Operations 241
14.4 Directives 241
14.4.1 clock_gettime -Obtain Time of Day 241
14.4.2 clock_settime - Set Time of Day 243
14.4.3 clock_getres - Get Clock Resolution 244
14.4.4 sleep - Delay Process Execution 245
14.4.5 nanosleep - Delay with High Resolution 246
14.4.6 gettimeofday - Get the Time of Day 247
14.4.7 time - Get time in seconds 248

15 Timer Manager 249
15.1 Introduction 249
15.2 Background 249
15.3 Operations 249
15.4 System Calls 249
15.4.1 timer_create - Create a Per-Process Timer 250
15.4.2 timer_delete - Delete a Per-Process Timer 251
15.4.3 timer_settime - Set Next Timer Expiration 252
15.4.4 timer_gettime - Get Time Remaining on Timer 253
15.4.5 timer_getoverrun - Get Timer Overrun Count 254

16 Message Passing Manager 255

16.1 Introduction 255
16.2 Background 255
16.2.1 Theory 255
16.2.2 Messages 255
16.2.3 Message Queues 255
16.2.4 Building a Message Queue Attribute Set 256
16.2.5 Notification of a Message on the Queue 256
16.2.6 POSIX Interpretation Issues 257
16.3 Operations 257
16.3.1 Opening or Creating a Message Queue 257
16.3.2 Closing a Message Queue 257
16.3.3 Removing a Message Queue 257
16.3.4 Sending a Message to a Message Queue 258
16.3.5 Receiving a Message from a Message Queue ... 258
16.3.6 Notification of Receipt of a Message on an Empty Queue 258
16.3.7 Setting the Attributes of a Message Queue 259
16.3.8 Getting the Attributes of a Message Queue 259
16.4 Directives 259
16.4.1 mq_open - Open a Message Queue 260
16.4.2 mq_close - Close a Message Queue 262
16.4.3 mq_unlink - Remove a Message Queue 263
16.4.4 mq_send - Send a Message to a Message Queue 264
16.4.5 mq_receive - Receive a Message from a Message Queue 265
16.4.6 mq_notify - Notify Process that a Message is Available 266
16.4.7 mq_setattr - Set Message Queue Attributes 268
16.4.8 mq_getattr - Get Message Queue Attributes ... 269

17 Thread Manager 271

17.1 Introduction 271
17.2 Background 272
17.2.1 Thread Attributes 272
17.3 Operations 272
17.4 Services 272
17.4.1 pthread_attr_init - Initialize a Thread Attribute Set 273
17.4.2 pthread_attr_destroy - Destroy a Thread Attribute Set 274
17.4.3 pthread_attr_setdetachstate - Set Detach State 275
17.4.4 pthread_attr_getdetachstate - Get Detach State 276
17.4.5 pthread_attr_setstacksize - Set Thread Stack Size 277

17.4.6 pthread_attr_getstacksize - Get Thread Stack Size 278
17.4.7 pthread_attr_setstackaddr - Set Thread Stack Address 279
17.4.8 pthread_attr_getstackaddr - Get Thread Stack Address 280
17.4.9 pthread_attr_setscope - Set Thread Scheduling Scope 281
17.4.10 pthread_attr_getscope - Get Thread Scheduling Scope 282
17.4.11 pthread_attr_setinheritsched - Set Inherit Scheduler Flag 283
17.4.12 pthread_attr_getinheritsched - Get Inherit Scheduler Flag 284
17.4.13 pthread_attr_setschedpolicy - Set Scheduling Policy 285
17.4.14 pthread_attr_getschedpolicy - Get Scheduling Policy 286
17.4.15 pthread_attr_setschedparam - Set Scheduling Parameters 287
17.4.16 pthread_attr_getschedparam - Get Scheduling Parameters 288
17.4.17 pthread_create - Create a Thread 289
17.4.18 pthread_exit - Terminate the Current Thread 291
17.4.19 pthread_detach - Detach a Thread 292
17.4.20 pthread_join - Wait for Thread Termination 293
17.4.21 pthread_self - Get Thread ID 294
17.4.22 pthread_equal - Compare Thread IDs 295
17.4.23 pthread_once - Dynamic Package Initialization 296
17.4.24 pthread_setschedparam - Set Thread Scheduling Parameters 297
17.4.25 pthread_getschedparam - Get Thread Scheduling Parameters 298

18 Key Manager 299

18.1 Introduction 299
18.2 Background 299
18.3 Operations 299
18.4 Directives 299
18.4.1 pthread_key_create - Create Thread Specific Data Key 300
18.4.2 pthread_key_delete - Delete Thread Specific Data Key 301
18.4.3 pthread_setspecific - Set Thread Specific Key Value 302

18.4.4 pthread_getspecific - Get Thread Specific Key Value 303

19 Thread Cancellation Manager 305

19.1 Introduction 305
19.2 Background 305
19.3 Operations 305
19.4 Directives 305
19.4.1 pthread_cancel - Cancel Execution of a Thread 306
19.4.2 pthread_setcancelstate - Set Cancelability State 307
19.4.3 pthread_setcanceltype - Set Cancelability Type 308
19.4.4 pthread_testcancel - Create Cancellation Point 309
19.4.5 pthread_cleanup_push - Establish Cancellation Handler 310
19.4.6 pthread_cleanup_pop - Remove Cancellation Handler 311

20 Services Provided by C Library (libc) 313

20.1 Introduction 313
20.2 Standard Utility Functions (stdlib.h) 313
20.3 Character Type Macros and Functions (ctype.h) 314
20.4 Input and Output (stdio.h) 314
20.5 Strings and Memory (string.h) 315
20.6 Signal Handling (signal.h) 316
20.7 Time Functions (time.h) 316
20.8 Locale (locale.h) 316
20.9 Reentrant Versions of Functions 317
20.10 Miscellaneous Macros and Functions 319
20.11 Variable Argument Lists 319
20.12 Reentrant System Calls 319

21 Services Provided by the Math Library (libm) 321

21.1 Introduction 321
21.2 Standard Math Functions (math.h) 321

22 Status of Implementation 323

Command and Variable Index 325

Concept Index 329

Preface

This is the User's Guide for the POSIX API support provided in RTEMS.

The functionality described in this document is based on the following standards:

- POSIX 1003.1b-1993.
- POSIX 1003.1h/D3.
- Open Group Single UNIX Specification.

Much of the POSIX API standard is actually implemented in the Cygnus Newlib ANSI C Library. Please refer to documentation on Newlib for more information on the functionality it supplies.

This manual is still under construction and improvements are welcomed from users.

1 Process Creation and Execution Manager

1.1 Introduction

The process creation and execution manager provides the functionality associated with the creation and termination of processes.

The directives provided by the process creation and execution manager are:

- `fork` - Create a Process
- `execl` - Execute a File
- `execv` - Execute a File
- `execle` - Execute a File
- `execve` - Execute a File
- `execlp` - Execute a File
- `execvp` - Execute a File
- `pthread_atfork` - Register Fork Handlers
- `wait` - Wait for Process Termination
- `waitpid` - Wait for Process Termination
- `_exit` - Terminate a Process

1.2 Background

POSIX process functionality can not be completely supported by RTEMS. This is because RTEMS provides no memory protection and implements a *single process, multi-threaded execution model*. In this light, RTEMS provides none of the routines that are associated with the creation of new processes. However, since the entire RTEMS application (e.g. executable) is logically a single POSIX process, RTEMS is able to provide implementations of many operations on processes. The rule of thumb is that those routines provide a meaningful result. For example, `getpid()` returns the node number.

1.3 Operations

The only functionality method defined by this manager which is supported by RTEMS is the `_exit` service. The implementation of `_exit` shuts the application down and is equivalent to invoking either `exit` or `rtems_shutdown_executive`.

1.4 Directives

This section details the process creation and execution manager's directives. A subsection is dedicated to each of this manager's directives and describes the calling sequence, related constants, usage, and status codes.

1.4.1 fork - Create a Process

CALLING SEQUENCE:

```
#include <sys/types.h>

int fork( void );
```

STATUS CODES:

ENOSYS This routine is not supported by RTEMS.

DESCRIPTION:

This routine is not supported by RTEMS.

NOTES:

NONE

1.4.2 execl - Execute a File

CALLING SEQUENCE:

```
int execl(
  const char *path,
  const char *arg,
  ...
);
```

STATUS CODES:

ENOSYS This routine is not supported by RTEMS.

DESCRIPTION:

This routine is not supported by RTEMS.

NOTES:

NONE

1.4.3 execv - Execute a File

CALLING SEQUENCE:

```
int execv(
  const char *path,
  char const *argv[],
  ...
);
```

STATUS CODES:

ENOSYS This routine is not supported by RTEMS.

DESCRIPTION:

This routine is not supported by RTEMS.

NOTES:

NONE

1.4.4 execle - Execute a File

CALLING SEQUENCE:

```
int execle(
  const char *path,
  const char *arg,
  ...
);
```

STATUS CODES:

ENOSYS This routine is not supported by RTEMS.

DESCRIPTION:

This routine is not supported by RTEMS.

NOTES:

NONE

1.4.5 execve - Execute a File

CALLING SEQUENCE:

```
int execve(
  const char *path,
  char *const argv[],
  char *const envp[]
);
```

STATUS CODES:

ENOSYS This routine is not supported by RTEMS.

DESCRIPTION:

This routine is not supported by RTEMS.

NOTES:

NONE

1.4.6 execlp - Execute a File

CALLING SEQUENCE:

```
int execlp(
  const char *file,
  const char *arg,
  ...
);
```

STATUS CODES:

ENOSYS This routine is not supported by RTEMS.

DESCRIPTION:

This routine is not supported by RTEMS.

NOTES:

NONE

1.4.7 execvp - Execute a File

CALLING SEQUENCE:

```
int execvp(
  const char *file,
  char *const argv[]
  ...
);
```

STATUS CODES:

ENOSYS This routine is not supported by RTEMS.

DESCRIPTION:

This routine is not supported by RTEMS.

NOTES:

NONE

1.4.8 pthread_atfork - Register Fork Handlers

CALLING SEQUENCE:

```
#include <sys/types.h>

int pthread_atfork(
  void (*prepare)(void),
  void (*parent)(void),
  void (*child)(void)
);
```

STATUS CODES:

ENOSYS This routine is not supported by RTEMS.

DESCRIPTION:

This routine is not supported by RTEMS.

NOTES:

NONE

1.4.9 wait - Wait for Process Termination

CALLING SEQUENCE:

```
#include <sys/types.h>
#include <sys/wait.h>

int wait(
  int *stat_loc
);
```

STATUS CODES:

ENOSYS This routine is not supported by RTEMS.

DESCRIPTION:

This routine is not supported by RTEMS.

NOTES:

NONE

1.4.10 waitpid - Wait for Process Termination

CALLING SEQUENCE:

```
int wait(
  pid_t  pid,
  int   *stat_loc,
  int    options
);
```

STATUS CODES:

ENOSYS This routine is not supported by RTEMS.

DESCRIPTION:

This routine is not supported by RTEMS.

NOTES:

NONE

1.4.11 _exit - Terminate a Process

CALLING SEQUENCE:

```
void _exit(
  int status
);
```

STATUS CODES:

NONE

DESCRIPTION:

The `_exit()` function terminates the calling process.

NOTES:

In RTEMS, a process is equivalent to the entire application on a single processor. Invoking this service terminates the application.

2 Signal Manager

2.1 Introduction

The signal manager provides the functionality associated with the generation, delivery, and management of process-oriented signals.

The directives provided by the signal manager are:

- `sigaddset` - Add a Signal to a Signal Set
- `sigdelset` - Delete a Signal from a Signal Set
- `sigfillset` - Fill a Signal Set
- `sigismember` - Is Signal a Member of a Signal Set
- `sigemptyset` - Empty a Signal Set
- `sigaction` - Examine and Change Signal Action
- `pthread_kill` - Send a Signal to a Thread
- `sigprocmask` - Examine and Change Process Blocked Signals
- `pthread_sigmask` - Examine and Change Thread Blocked Signals
- `kill` - Send a Signal to a Process
- `sigpending` - Examine Pending Signals
- `sigsuspend` - Wait for a Signal
- `pause` - Suspend Process Execution
- `sigwait` - Synchronously Accept a Signal
- `sigwaitinfo` - Synchronously Accept a Signal
- `sigtimedwait` - Synchronously Accept a Signal with Timeout
- `sigqueue` - Queue a Signal to a Process
- `alarm` - Schedule Alarm

2.2 Background

2.2.1 Signals

POSIX signals are an asynchronous event mechanism. Each process and thread has a set of signals associated with it. Individual signals may be enabled (e.g. unmasked) or blocked (e.g. ignored) on both a per-thread and process level. Signals which are enabled have a signal handler associated with them. When the signal is generated and conditions are met, then the signal handler is invoked in the proper process or thread context asynchronous relative to the logical thread of execution.

If a signal has been blocked when it is generated, then it is queued and kept pending until the thread or process unblocks the signal or explicitly checks for it. Traditional, non-real-time POSIX signals do not queue. Thus if a process or thread has blocked a particular signal, then multiple occurrences of that signal are recorded as a single occurrence of that signal.

One can check for the set of outstanding signals that have been blocked. Services are provided to check for outstanding process or thread directed signals.

2.2.2 Signal Delivery

Signals which are directed at a thread are delivered to the specified thread.

Signals which are directed at a process are delivered to a thread which is selected based on the following algorithm:

1. If the action for this signal is currently `SIG_IGN`, then the signal is simply ignored.
2. If the currently executing thread has the signal unblocked, then the signal is delivered to it.
3. If any threads are currently blocked waiting for this signal (`sigwait()`), then the signal is delivered to the highest priority thread waiting for this signal.
4. If any other threads are willing to accept delivery of the signal, then the signal is delivered to the highest priority thread of this set. In the event, multiple threads of the same priority are willing to accept this signal, then priority is given first to ready threads, then to threads blocked on calls which may be interrupted, and finally to threads blocked on non-interruptible calls.
5. In the event the signal still can not be delivered, then it is left pending. The first thread to unblock the signal (`sigprocmask()` or `pthread_sigprocmask()`) or to wait for this signal (`sigwait()`) will be the recipient of the signal.

2.3 Operations

2.3.1 Signal Set Management

Each process and each thread within that process has a set of individual signals and handlers associated with it. Services are provided to construct signal sets for the purposes of building signal sets – type `sigset_t` – that are used to provide arguments to the services that mask, unmask, and check on pending signals.

2.3.2 Blocking Until Signal Generation

A thread may block until receipt of a signal. The "sigwait" and "pause" families of services block until the requested signal is received or if using `sigtimedwait()` until the specified timeout period has elapsed.

2.3.3 Sending a Signal

This is accomplished via one of a number of services that sends a signal to either a process or thread. Signals may be directed at a process by the service `kill()` or at a thread by the service `pthread_kill()`

2.4 Directives

This section details the signal manager's directives. A subsection is dedicated to each of this manager's directives and describes the calling sequence, related constants, usage, and status codes.

2.4.1 sigaddset - Add a Signal to a Signal Set

CALLING SEQUENCE:

```
#include <signal.h>

int sigaddset(
  sigset_t *set,
  int       signo
);
```

STATUS CODES:

EINVAL Invalid argument passed.

DESCRIPTION:

This function adds the `signo` to the specified signal `set`.

NOTES:

NONE

2.4.2 sigdelset - Delete a Signal from a Signal Set

CALLING SEQUENCE:

```
#include <signal.h>

int sigdelset(
  sigset_t *set,
  int       signo
);
```

STATUS CODES:

EINVAL Invalid argument passed.

DESCRIPTION:

This function deletes the `signo` to the specified signal `set`.

NOTES:

NONE

2.4.3 sigfillset - Fill a Signal Set

CALLING SEQUENCE:

```
#include <signal.h>

int sigfillset(
  sigset_t *set
);
```

STATUS CODES:

EINVAL Invalid argument passed.

DESCRIPTION:

This function fills the specified signal `set` such that all signals are set.

NOTES:

NONE

2.4.4 sigismember - Is Signal a Member of a Signal Set

CALLING SEQUENCE:

```
#include <signal.h>

int sigismember(
  const sigset_t *set,
  int             signo
);
```

STATUS CODES:

EINVAL Invalid argument passed.

DESCRIPTION:

This function returns returns 1 if `signo` is a member of `set` and 0 otherwise.

NOTES:

NONE

2.4.5 sigemptyset - Empty a Signal Set

CALLING SEQUENCE:

```
#include <signal.h>

int sigemptyset(
  sigset_t *set
);
```

STATUS CODES:

EINVAL Invalid argument passed.

DESCRIPTION:

This function fills the specified signal `set` such that all signals are cleared.

NOTES:

NONE

2.4.6 sigaction - Examine and Change Signal Action

CALLING SEQUENCE:

```
#include <signal.h>

int sigaction(
  int                     sig,
  const struct sigaction *act,
  struct sigaction       *oact
);
```

STATUS CODES:

EINVAL	Invalid argument passed.
ENOTSUP	Realtime Signals Extension option not supported.

DESCRIPTION:

This function is used to change the action taken by a process on receipt of the specfic signal `sig`. The new action is specified by `act` and the previous action is returned via `oact`.

NOTES:

The signal number cannot be SIGKILL.

2.4.7 pthread_kill - Send a Signal to a Thread

CALLING SEQUENCE:

```
#include <signal.h>

int pthread_kill(
  pthread_t thread,
  int       sig
);
```

STATUS CODES:

ESRCH The thread indicated by the parameter thread is invalid.

EINVAL Invalid argument passed.

DESCRIPTION:

This functions sends the specified signal `sig` to `thread`.

NOTES:

NONE

2.4.8 sigprocmask - Examine and Change Process Blocked Signals

CALLING SEQUENCE:

```
#include <signal.h>

int sigprocmask(
  int             how,
  const sigset_t *set,
  sigset_t       *oset
);
```

STATUS CODES:

EINVAL Invalid argument passed.

DESCRIPTION:

This function is used to alter the set of currently blocked signals on a process wide basis. A blocked signal will not be received by the process. The behavior of this function is dependent on the value of `how` which may be one of the following:

`SIG_BLOCK` The set of blocked signals is set to the union of `set` and those signals currently blocked.

`SIG_UNBLOCK` The signals specific in `set` are removed from the currently blocked set.

`SIG_SETMASK` The set of currently blocked signals is set to `set`.

If `oset` is not `NULL`, then the set of blocked signals prior to this call is returned in `oset`.

NOTES:

It is not an error to unblock a signal which is not blocked.

2.4.9 pthread_sigmask - Examine and Change Thread Blocked Signals

CALLING SEQUENCE:

```
#include <signal.h>

int pthread_sigmask(
  int             how,
  const sigset_t *set,
  sigset_t       *oset
);
```

STATUS CODES:

EINVAL Invalid argument passed.

DESCRIPTION:

This function is used to alter the set of currently blocked signals for the calling thread. A blocked signal will not be received by the process. The behavior of this function is dependent on the value of `how` which may be one of the following:

`SIG_BLOCK` The set of blocked signals is set to the union of `set` and those signals currently blocked.

`SIG_UNBLOCK` The signals specific in `set` are removed from the currently blocked set.

`SIG_SETMASK` The set of currently blocked signals is set to `set`.

If `oset` is not `NULL`, then the set of blocked signals prior to this call is returned in `oset`.

NOTES:

It is not an error to unblock a signal which is not blocked.

2.4.10 kill - Send a Signal to a Process

CALLING SEQUENCE:

```
#include <sys/types.h>
#include <signal.h>

int kill(
  pid_t pid,
  int   sig
);
```

STATUS CODES:

EINVAL	Invalid argument passed.
EPERM	Process does not have permission to send the signal to any receiving process.
ESRCH	The process indicated by the parameter pid is invalid.

DESCRIPTION:

This function sends the signal `sig` to the process `pid`.

NOTES:

NONE

2.4.11 sigpending - Examine Pending Signals

CALLING SEQUENCE:

```
#include <signal.h>

int sigpending(
  const sigset_t *set
);
```

STATUS CODES:

On error, this routine returns -1 and sets `errno` to one of the following:

EFAULT Invalid address for set.

DESCRIPTION:

This function allows the caller to examine the set of currently pending signals. A pending signal is one which has been raised but is currently blocked. The set of pending signals is returned in `set`.

NOTES:

NONE

2.4.12 sigsuspend - Wait for a Signal

CALLING SEQUENCE:

```
#include <signal.h>

int sigsuspend(
  const sigset_t *sigmask
);
```

STATUS CODES:

On error, this routine returns -1 and sets `errno` to one of the following:

EINTR Signal interrupted this function.

DESCRIPTION:

This function temporarily replaces the signal mask for the process with that specified by `sigmask` and blocks the calling thread until the signal is raised.

NOTES:

NONE

2.4.13 pause - Suspend Process Execution

CALLING SEQUENCE:

```
#include <signal.h>

int pause( void );
```

STATUS CODES:

On error, this routine returns -1 and sets `errno` to one of the following:

EINTR Signal interrupted this function.

DESCRIPTION:

This function causes the calling thread to be blocked until an unblocked signal is received.

NOTES:

NONE

2.4.14 sigwait - Synchronously Accept a Signal

CALLING SEQUENCE:

```
#include <signal.h>

int sigwait(
  const sigset_t *set,
  int            *sig
);
```

STATUS CODES:

EINVAL	Invalid argument passed.
EINTR	Signal interrupted this function.

DESCRIPTION:

This function selects a pending signal based on the set specified in `set`, atomically clears it from the set of pending signals, and returns the signal number for that signal in `sig`.

NOTES:

NONE

2.4.15 sigwaitinfo - Synchronously Accept a Signal

CALLING SEQUENCE:

```
#include <signal.h>

int sigwaitinfo(
  const sigset_t *set,
  siginfo_t      *info
);
```

STATUS CODES:

EINTR Signal interrupted this function.

DESCRIPTION:

This function selects a pending signal based on the set specified in `set`, atomically clears it from the set of pending signals, and returns information about that signal in `info`.

NOTES:

NONE

2.4.16 sigtimedwait - Synchronously Accept a Signal with Timeout

CALLING SEQUENCE:

```
#include <signal.h>

int sigtimedwait(
  const sigset_t        *set,
  siginfo_t             *info,
  const struct timespec *timeout
);
```

STATUS CODES:

EAGAIN	Timed out while waiting for the specified signal set.
EINVAL	Nanoseconds field of the timeout argument is invalid.
EINTR	Signal interrupted this function.

DESCRIPTION:

This function selects a pending signal based on the set specified in `set`, atomically clears it from the set of pending signals, and returns information about that signal in `info`. The calling thread will block up to `timeout` waiting for the signal to arrive.

NOTES:

If `timeout` is NULL, then the calling thread will wait forever for the specified signal set.

2.4.17 sigqueue - Queue a Signal to a Process

CALLING SEQUENCE:

```
#include <signal.h>

int sigqueue(
  pid_t              pid,
  int                signo,
  const union sigval value
);
```

STATUS CODES:

EAGAIN	No resources available to queue the signal. The process has already queued SIGQUEUE_MAX signals that are still pending at the receiver or the systemwide resource limit has been exceeded.
EINVAL	The value of the signo argument is an invalid or unsupported signal number.
EPERM	The process does not have the appropriate privilege to send the signal to the receiving process.
ESRCH	The process pid does not exist.

DESCRIPTION:

This function sends the signal specified by `signo` to the process `pid`

NOTES:

NONE

2.4.18 alarm - Schedule Alarm

CALLING SEQUENCE:

```
#include <signal.h>

unsigned int alarm(
  unsigned int seconds
);
```

STATUS CODES:

This call always succeeds.

DESCRIPTION:

If there was a previous `alarm()` request with time remaining, then this routine returns the number of seconds until that outstanding alarm would have fired. If no previous `alarm()` request was outstanding, then zero is returned.

NOTES:

NONE

3 Process Environment Manager

3.1 Introduction

The process environment manager is responsible for providing the functions related to user and group Id management.

The directives provided by the process environment manager are:

- `getpid` - Get Process ID
- `getppid` - Get Parent Process ID
- `getuid` - Get User ID
- `geteuid` - Get Effective User ID
- `getgid` - Get Real Group ID
- `getegid` - Get Effective Group ID
- `setuid` - Set User ID
- `setgid` - Set Group ID
- `getgroups` - Get Supplementary Group IDs
- `getlogin` - Get User Name
- `getlogin_r` - Reentrant Get User Name
- `getpgrp` - Get Process Group ID
- `setsid` - Create Session and Set Process Group ID
- `setpgid` - Set Process Group ID for Job Control
- `uname` - Get System Name
- `times` - Get Process Times
- `getenv` - Get Environment Variables
- `setenv` - Set Environment Variables
- `ctermid` - Generate Terminal Pathname
- `ttyname` - Determine Terminal Device Name
- `ttyname_r` - Reentrant Determine Terminal Device Name
- `isatty` - Determine if File Descriptor is Terminal
- `sysconf` - Get Configurable System Variables

3.2 Background

3.2.1 Users and Groups

RTEMS provides a single process, multi-threaded execution environment. In this light, the notion of user and group is somewhat without meaning. But RTEMS does provide services

to provide a synthetic version of user and group. By default, a single user and group is associated with the application. Thus unless special actions are taken, every thread in the application shares the same user and group Id. The initial rationale for providing user and group Id functionality in RTEMS was for the filesystem infrastructure to implement file permission checks. The effective user/group Id capability has since been used to implement permissions checking by the `ftpd` server.

In addition to the "real" user and group Ids, a process may have an effective user/group Id. This allows a process to function using a more limited permission set for certain operations.

3.2.2 User and Group Names

POSIX considers user and group Ids to be a unique integer that may be associated with a name. This is usually accomplished via a file named `/etc/passwd` for user Id mapping and `/etc/groups` for group Id mapping. Again, although RTEMS is effectively a single process and thus single user system, it provides limited support for user and group names. When configured with an appropriate filesystem, RTEMS will access the appropriate files to map user and group Ids to names.

If these files do not exist, then RTEMS will synthesize a minimal version so this family of services return without error. It is important to remember that a design goal of the RTEMS POSIX services is to provide useable and meaningful results even though a full process model is not available.

3.2.3 Environment Variables

POSIX allows for variables in the run-time environment. These are name/value pairs that make be dynamically set and obtained by programs. In a full POSIX environment with command line shell and multiple processes, environment variables may be set in one process – such as the shell – and inherited by child processes. In RTEMS, there is only one process and thus only one set of environment variables across all processes.

3.3 Operations

3.3.1 Accessing User and Group Ids

The user Id associated with the current thread may be obtain using the `getuid()` service. Similarly, the group Id may be obtained using the `getgid()` service.

3.3.2 Accessing Environment Variables

The value associated with an environment variable may be obtained using the `getenv()` service and set using the `putenv()` service.

3.4 Directives

This section details the process environment manager's directives. A subsection is dedicated to each of this manager's directives and describes the calling sequence, related constants, usage, and status codes.

3.4.1 getpid - Get Process ID

CALLING SEQUENCE:

```
int getpid( void );
```

STATUS CODES:

The process Id is returned.

DESCRIPTION:

This service returns the process Id.

NOTES:

NONE

3.4.2 getppid - Get Parent Process ID

CALLING SEQUENCE:

```
int getppid( void );
```

STATUS CODES:

The parent process Id is returned.

DESCRIPTION:

This service returns the parent process Id.

NOTES:

NONE

3.4.3 getuid - Get User ID

CALLING SEQUENCE:

```
int getuid( void );
```

STATUS CODES:

The effective user Id is returned.

DESCRIPTION:

This service returns the effective user Id.

NOTES:

NONE

3.4.4 geteuid - Get Effective User ID

CALLING SEQUENCE:

```
int geteuid( void );
```

STATUS CODES:

The effective group Id is returned.

DESCRIPTION:

This service returns the effective group Id.

NOTES:

NONE

3.4.5 getgid - Get Real Group ID

CALLING SEQUENCE:

```
int getgid( void );
```

STATUS CODES:

The group Id is returned.

DESCRIPTION:

This service returns the group Id.

NOTES:

NONE

3.4.6 getegid - Get Effective Group ID

CALLING SEQUENCE:

```
int getegid( void );
```

STATUS CODES:

The effective group Id is returned.

DESCRIPTION:

This service returns the effective group Id.

NOTES:

NONE

3.4.7 setuid - Set User ID

CALLING SEQUENCE:

```
int setuid(
  uid_t uid
);
```

STATUS CODES:

This service returns 0.

DESCRIPTION:

This service sets the user Id to `uid`.

NOTES:

NONE

3.4.8 setgid - Set Group ID

CALLING SEQUENCE:

```
int setgid(
  gid_t  gid
);
```

STATUS CODES:

This service returns 0.

DESCRIPTION:

This service sets the group Id to `gid`.

NOTES:

NONE

3.4.9 getgroups - Get Supplementary Group IDs

CALLING SEQUENCE:

```
int getgroups(
  int    gidsetsize,
  gid_t  grouplist[]
);
```

STATUS CODES:

NA

DESCRIPTION:

This service is not implemented as RTEMS has no notion of supplemental groups.

NOTES:

If supported, this routine would only be allowed for the super-user.

3.4.10 getlogin - Get User Name

CALLING SEQUENCE:

```
char *getlogin( void );
```

STATUS CODES:

Returns a pointer to a string containing the name of the current user.

DESCRIPTION:

This routine returns the name of the current user.

NOTES:

This routine is not reentrant and subsequent calls to `getlogin()` will overwrite the same buffer.

3.4.11 getlogin_r - Reentrant Get User Name

CALLING SEQUENCE:

```
int getlogin_r(
  char   *name,
  size_t  namesize
);
```

STATUS CODES:

EINVAL The arguments were invalid.

DESCRIPTION:

This is a reentrant version of the `getlogin()` service. The caller specified their own buffer, `name`, as well as the length of this buffer, `namesize`.

NOTES:

NONE

3.4.12 getpgrp - Get Process Group ID

CALLING SEQUENCE:

```
pid_t getpgrp( void );
```

STATUS CODES:

The procress group Id is returned.

DESCRIPTION:

This service returns the current progress group Id.

NOTES:

This routine is implemented in a somewhat meaningful way for RTEMS but is truly not functional.

3.4.13 setsid - Create Session and Set Process Group ID

CALLING SEQUENCE:

```
pid_t setsid( void );
```

STATUS CODES:

EPERM The application does not have permission to create a process group.

DESCRIPTION:

This routine always returns `EPERM` as RTEMS has no way to create new processes and thus no way to create a new process group.

NOTES:

NONE

3.4.14 setpgid - Set Process Group ID for Job Control

CALLING SEQUENCE:

```
int setpgid(
  pid_t pid,
  pid_t pgid
);
```

STATUS CODES:

ENOSYS The routine is not implemented.

DESCRIPTION:

This service is not implemented for RTEMS as process groups are not supported.

NOTES:

NONE

3.4.15 uname - Get System Name

CALLING SEQUENCE:

```
int uname(
  struct utsname *name
);
```

STATUS CODES:

EPERM The provided structure pointer is invalid.

DESCRIPTION:

This service returns system information to the caller. It does this by filling in the `struct utsname` format structure for the caller.

NOTES:

The information provided includes the operating system (RTEMS in all configurations), the node number, the release as the RTEMS version, and the CPU family and model. The CPU model name will indicate the multilib executive variant being used.

3.4.16 times - Get process times

CALLING SEQUENCE:

```
#include <sys/time.h>

clock_t times(
  struct tms *ptms
);
```

STATUS CODES:

This routine returns the number of clock ticks that have elapsed since the system was initialized (e.g. the application was started).

DESCRIPTION:

`times` stores the current process times in `ptms`. The format of `struct tms` is as defined in `<sys/times.h>`. RTEMS fills in the field `tms_utime` with the number of ticks that the calling thread has executed and the field `tms_stime` with the number of clock ticks since system boot (also returned). All other fields in the `ptms` are left zero.

NOTES:

RTEMS has no way to distinguish between user and system time so this routine returns the most meaningful information possible.

3.4.17 getenv - Get Environment Variables

CALLING SEQUENCE:

```
char *getenv(
  const char *name
);
```

STATUS CODES:

NULL	when no match
pointer to value	when successful

DESCRIPTION:

This service searches the set of environment variables for a string that matches the specified `name`. If found, it returns the associated value.

NOTES:

The environment list consists of name value pairs that are of the form *name = value*.

3.4.18 setenv - Set Environment Variables

CALLING SEQUENCE:

```
int setenv(
  const char *name,
  const char *value,
  int overwrite
);
```

STATUS CODES:

Returns 0 if successful and -1 otherwise.

DESCRIPTION:

This service adds the variable `name` to the environment with `value`. If `name` is not already exist, then it is created. If `name` exists and `overwrite` is zero, then the previous value is not overwritten.

NOTES:

NONE

3.4.19 ctermid - Generate Terminal Pathname

CALLING SEQUENCE:

```
char *ctermid(
  char *s
);
```

STATUS CODES:

Returns a pointer to a string indicating the pathname for the controlling terminal.

DESCRIPTION:

This service returns the name of the terminal device associated with this process. If `s` is NULL, then a pointer to a static buffer is returned. Otherwise, `s` is assumed to have a buffer of sufficient size to contain the name of the controlling terminal.

NOTES:

By default on RTEMS systems, the controlling terminal is `/dev/console`. Again this implementation is of limited meaning, but it provides true and useful results which should be sufficient to ease porting applications from a full POSIX implementation to the reduced profile supported by RTEMS.

3.4.20 ttyname - Determine Terminal Device Name

CALLING SEQUENCE:

```
char *ttyname(
  int fd
);
```

STATUS CODES:

Pointer to a string containing the terminal device name or NULL is returned on any error.

DESCRIPTION:

This service returns a pointer to the pathname of the terminal device that is open on the file descriptor `fd`. If `fd` is not a valid descriptor for a terminal device, then NULL is returned.

NOTES:

This routine uses a static buffer.

3.4.21 ttyname_r - Reentrant Determine Terminal Device Name

CALLING SEQUENCE:

```
int ttyname_r(
  int   fd,
  char *name,
  int   namesize
);
```

STATUS CODES:

This routine returns -1 and sets `errno` as follows:

EBADF If not a valid descriptor for a terminal device.

EINVAL If `name` is NULL or `namesize` are insufficient.

DESCRIPTION:

This service the pathname of the terminal device that is open on the file descriptor `fd`.

NOTES:

NONE

3.4.22 isatty - Determine if File Descriptor is Terminal

CALLING SEQUENCE:

```
int isatty(
  int fd
);
```

STATUS CODES:

Returns 1 if `fd` is a terminal device and 0 otherwise.

DESCRIPTION:

This service returns 1 if `fd` is an open file descriptor connected to a terminal and 0 otherwise.

NOTES:

3.4.23 sysconf - Get Configurable System Variables

CALLING SEQUENCE:

```
long sysconf(
  int name
);
```

STATUS CODES:

The value returned is the actual value of the system resource. If the requested configuration name is a feature flag, then 1 is returned if the available and 0 if it is not. On any other error condition, -1 is returned.

DESCRIPTION:

This service is the mechanism by which an application determines values for system limits or options at runtime.

NOTES:

Much of the information that may be obtained via `sysconf` has equivalent macros in `<unistd.h`. However, those macros reflect conservative limits which may have been altered by application configuration.

4 Files and Directories Manager

4.1 Introduction

The files and directories manager is ...

The directives provided by the files and directories manager are:

- `opendir` - Open a Directory
- `readdir` - Reads a directory
- `rewinddir` - Resets the `readdir()` pointer
- `scandir` - Scan a directory for matching entries
- `telldir` - Return current location in directory stream
- `closedir` - Ends directory read operation
- `getdents` - Get directory entries
- `chdir` - Changes the current working directory
- `fchdir` - Changes the current working directory
- `getcwd` - Gets current working directory
- `open` - Opens a file
- `creat` - Create a new file or rewrite an existing one
- `umask` - Sets a file creation mask
- `link` - Creates a link to a file
- `symlink` - Creates a symbolic link to a file
- `readlink` - Obtain the name of the link destination
- `mkdir` - Makes a directory
- `mkfifo` - Makes a FIFO special file
- `unlink` - Removes a directory entry
- `rmdir` - Delete a directory
- `rename` - Renames a file
- `stat` - Gets information about a file.
- `fstat` - Gets file status
- `lstat` - Gets file status
- `access` - Check permissions for a file.
- `chmod` - Changes file mode
- `fchmod` - Changes permissions of a file
- `chown` - Changes the owner and/ or group of a file
- `utime` - Change access and/or modification times of an inode
- `ftruncate` - Truncate a file to a specified length
- `truncate` - Truncate a file to a specified length

- `pathconf` - Gets configuration values for files
- `fpathconf` - Get configuration values for files
- `mknod` - Create a directory

4.2 Background

4.2.1 Path Name Evaluation

A pathname is a string that consists of no more than `PATH_MAX` bytes, including the terminating null character. A pathname has an optional beginning slash, followed by zero or more filenames separated by slashes. If the pathname refers to a directory, it may also have one or more trailing slashes. Multiple successive slahes are considered to be the same as one slash.

POSIX allows a pathname that begins with precisely two successive slashes to be interpreted in an implementation-defined manner. RTEMS does not currently recognize this as a special condition. Any number of successive slashes is treated the same as a single slash. POSIX requires that an implementation treat more than two leading slashes as a single slash.

4.3 Operations

There is currently no text in this section.

4.4 Directives

This section details the files and directories manager's directives. A subsection is dedicated to each of this manager's directives and describes the calling sequence, related constants, usage, and status codes.

4.4.1 opendir - Open a Directory

CALLING SEQUENCE:

```
#include <sys/types.h>
#include <dirent.h>

int opendir(
  const char *dirname
);
```

STATUS CODES:

EACCES	Search permission was denied on a component of the path prefix of `dirname`, or read permission is denied
EMFILE	Too many file descriptors in use by process
ENFILE	Too many files are currently open in the system.
ENOENT	Directory does not exist, or `name` is an empty string.
ENOMEM	Insufficient memory to complete the operation.
ENOTDIR	`name` is not a directory.

DESCRIPTION:

This routine opens a directory stream corresponding to the directory specified by the `dirname` argument. The directory stream is positioned at the first entry.

NOTES:

The routine is implemented in Cygnus newlib.

4.4.2 readdir - Reads a directory

CALLING SEQUENCE:

```
#include <sys/types.h>
#include <dirent.h>

int readdir(
  DIR *dirp
);
```

STATUS CODES:

EBADF Invalid file descriptor

DESCRIPTION:

The `readdir()` function returns a pointer to a structure `dirent` representing the next directory entry from the directory stream pointed to by `dirp`. On end-of-file, NULL is returned.

The `readdir()` function may (or may not) return entries for . or .. Your program should tolerate reading dot and dot-dot but not require them.

The data pointed to be `readdir()` may be overwritten by another call to `readdir()` for the same directory stream. It will not be overwritten by a call for another directory.

NOTES:

If `ptr` is not a pointer returned by `malloc()`, `calloc()`, or `realloc()` or has been deallocated with `free()` or `realloc()`, the results are not portable and are probably disastrous.

The routine is implemented in Cygnus newlib.

4.4.3 rewinddir - Resets the readdir() pointer

CALLING SEQUENCE:

```
#include <sys/types.h>
#include <dirent.h>

void rewinddir(
  DIR *dirp
);
```

STATUS CODES:

No value is returned.

DESCRIPTION:

The `rewinddir()` function resets the position associated with the directory stream pointed to by `dirp`. It also causes the directory stream to refer to the current state of the directory.

NOTES:

NONE

If `dirp` is not a pointer by `opendir()`, the results are undefined.

The routine is implemented in Cygnus newlib.

4.4.4 scandir - Scan a directory for matching entries

CALLING SEQUENCE:

```
#include <dirent.h>

int scandir(
  const char       *dir,
  struct dirent ***namelist,
  int  (*select)(const struct dirent *),
  int  (*compar)(const struct dirent **, const struct dirent **)
);
```

STATUS CODES:

ENOMEM Insufficient memory to complete the operation.

DESCRIPTION:

The `scandir()` function scans the directory `dir`, calling `select()` on each directory entry. Entries for which `select()` returns non-zero are stored in strings allocated via `malloc()`, sorted using `qsort()` with the comparison function `compar()`, and collected in array `namelist` which is allocated via `malloc()`. If `select` is NULL, all entries are selected.

NOTES:

The routine is implemented in Cygnus newlib.

4.4.5 telldir - Return current location in directory stream

CALLING SEQUENCE:

```
#include <dirent.h>

off_t telldir(
  DIR *dir
);
```

STATUS CODES:

EBADF Invalid directory stream descriptor `dir`.

DESCRIPTION:

The `telldir()` function returns the current location associated with the directory stream `dir`.

NOTES:

The routine is implemented in Cygnus newlib.

4.4.6 closedir - Ends directory read operation

CALLING SEQUENCE:

```
#include <sys/types.h>
#include <dirent.h>

int closedir(
  DIR *dirp
);
```

STATUS CODES:

EBADF Invalid file descriptor

DESCRIPTION:

The directory stream associated with `dirp` is closed. The value in `dirp` may not be usable after a call to `closedir()`.

NOTES:

NONE

The argument to `closedir()` must be a pointer returned by `opendir()`. If it is not, the results are not portable and most likely unpleasant.

The routine is implemented in Cygnus newlib.

4.4.7 chdir - Changes the current working directory

CALLING SEQUENCE:

```
#include <unistd.h>

int chdir(
  const char *path
);
```

STATUS CODES:

On error, this routine returns -1 and sets `errno` to one of the following:

EACCES	Search permission is denied for a directory in a file's path prefix.
ENAMETOOLONG	Length of a filename string exceeds PATH_MAX and _POSIX_NO_TRUNC is in effect.
ENOENT	A file or directory does not exist.
ENOTDIR	A component of the specified pathname was not a directory when directory was expected.

DESCRIPTION:

The `chdir()` function causes the directory named by `path` to become the current working directory; that is, the starting point for searches of pathnames not beginning with a slash.

If `chdir()` detects an error, the current working directory is not changed.

NOTES:

NONE

4.4.8 fchdir - Changes the current working directory

CALLING SEQUENCE:

```
#include <unistd.h>

int fchdir(
  int fd
);
```

STATUS CODES:

On error, this routine returns -1 and sets `errno` to one of the following:

EACCES	Search permission is denied for a directory in a file's path prefix.
ENAMETOOLONG	Length of a filename string exceeds PATH_MAX and _POSIX_NO_TRUNC is in effect.
ENOENT	A file or directory does not exist.
ENOTDIR	A component of the specified pathname was not a directory when directory was expected.

DESCRIPTION:

The `fchdir()` function causes the directory named by `fd` to become the current working directory; that is, the starting point for searches of pathnames not beginning with a slash.

If `fchdir()` detects an error, the current working directory is not changed.

NOTES:

NONE

4.4.9 getcwd - Gets current working directory

CALLING SEQUENCE:

```
#include <unistd.h>

int getcwd( void );
```

STATUS CODES:

EINVAL	Invalid argument
ERANGE	Result is too large
EACCES	Search permission is denied for a directory in a file's path prefix.

DESCRIPTION:

The `getcwd()` function copies the absolute pathname of the current working directory to the character array pointed to by `buf`. The `size` argument is the number of bytes available in `buf`

NOTES:

There is no way to determine the maximum string length that `fetcwd()` may need to return. Applications should tolerate getting `ERANGE` and allocate a larger buffer.

It is possible for `getcwd()` to return EACCES if, say, `login` puts the process into a directory without read access.

The 1988 standard uses `int` instead of `size_t` for the second parameter.

4.4.10 open - Opens a file

CALLING SEQUENCE:

```
#include <sys/types.h>
#include <sys/stat.h>
#include <fcntl.h>

int open(
  const char *path,
  int         oflag,
  mode_t      mode
);
```

STATUS CODES:

EACCES	Search permission is denied for a directory in a file's path prefix.
EEXIST	The named file already exists.
EINTR	Function was interrupted by a signal.
EISDIR	Attempt to open a directory for writing or to rename a file to be a directory.
EMFILE	Too many file descriptors are in use by this process.
ENAMETOOLONG	Length of a filename string exceeds PATH_MAX and _POSIX_NO_TRUNC is in effect.
ENFILE	Too many files are currently open in the system.
ENOENT	A file or directory does not exist.
ENOSPC	No space left on disk.
ENOTDIR	A component of the specified pathname was not a directory when a directory was expected.
ENXIO	No such device. This error may also occur when a device is not ready, for example, a tape drive is off-line.
EROFS	Read-only file system.

DESCRIPTION:

The `open` function establishes a connection between a file and a file descriptor. The file descriptor is a small integer that is used by I/O functions to reference the file. The `path` argument points to the pathname for the file.

The `oflag` argument is the bitwise inclusive OR of the values of symbolic constants. The programmer must specify exactly one of the following three symbols:

O_RDONLY Open for reading only.

O_WRONLY Open for writing only.

O_RDWR Open for reading and writing.

Any combination of the following symbols may also be used.

O_APPEND Set the file offset to the end-of-file prior to each write.

O_CREAT If the file does not exist, allow it to be created. This flag indicates that the `mode` argument is present in the call to `open`.

O_EXCL This flag may be used only if O_CREAT is also set. It causes the call to `open` to fail if the file already exists.

O_NOCTTY If `path` identifies a terminal, this flag prevents that teminal from becoming the controlling terminal for thi9s process. See Chapter 8 for a description of terminal I/O.

O_NONBLOCK Do no wait for the device or file to be ready or available. After the file is open, the `read` and `write` calls return immediately. If the process would be delayed in the read or write opermation, -1 is returned and `errno` is set to `EAGAIN` instead of blocking the caller.

O_TRUNC This flag should be used only on ordinary files opened for writing. It causes the file to be tuncated to zero length..

Upon successful completion, `open` returns a non-negative file descriptor.

NOTES:

NONE

4.4.11 creat - Create a new file or rewrite an existing one

CALLING SEQUENCE:

```
#include <sys/types.h>
#include <sys/stat.h>
#include <fcntl.h>

int creat(
  const char *path,
  mode_t      mode
);
```

STATUS CODES:

EEXIST	`path` already exists and O_CREAT and O_EXCL were used.
EISDIR	`path` refers to a directory and the access requested involved writing
ETXTBSY	`path` refers to an executable image which is currently being executed and write access was requested
EFAULT	`path` points outside your accessible address space
EACCES	The requested access to the file is not allowed, or one of the directories in `path` did not allow search (execute) permission.
ENAMETOOLONG	`path` was too long.
ENOENT	A directory component in `path` does not exist or is a dangling symbolic link.
ENOTDIR	A component used as a directory in `path` is not, in fact, a directory.
EMFILE	The process alreadyh has the maximum number of files open.
ENFILE	The limit on the total number of files open on the system has been reached.
ENOMEM	Insufficient kernel memory was available.
EROFS	`path` refers to a file on a read-only filesystem and write access was requested

DESCRIPTION:

`creat` attempts to create a file and return a file descriptor for use in read, write, etc.

NOTES:

NONE

The routine is implemented in Cygnus newlib.

4.4.12 umask - Sets a file creation mask.

CALLING SEQUENCE:

```
#include <sys/types.h>
#include <sys/stat.h>

mode_t umask(
  mode_t cmask
);
```

STATUS CODES:

DESCRIPTION:

The `umask()` function sets the process file creation mask to `cmask`. The file creation mask is used during `open()`, `creat()`, `mkdir()`, `mkfifo()` calls to turn off permission bits in the `mode` argument. Bit positions that are set in `cmask` are cleared in the mode of the created file.

NOTES:

NONE

The `cmask` argument should have only permission bits set. All other bits should be zero.

In a system which supports multiple processes, the file creation mask is inherited across `fork()` and `exec()` calls. This makes it possible to alter the default permission bits of created files. RTEMS does not support multiple processes so this behavior is not possible.

4.4.13 link - Creates a link to a file

CALLING SEQUENCE:

```
#include <unistd.h>

int link(
  const char *existing,
  const char *new
);
```

STATUS CODES:

EACCES	Search permission is denied for a directory in a file's path prefix
EEXIST	The named file already exists.
EMLINK	The number of links would exceed `LINK_MAX`.
ENAMETOOLONG	Length of a filename string exceeds PATH_MAX and _POSIX_NO_TRUNC is in effect.
ENOENT	A file or directory does not exist.
ENOSPC	No space left on disk.
ENOTDIR	A component of the specified pathname was not a directory when a directory was expected.
EPERM	Operation is not permitted. Process does not have the appropriate priviledges or permissions to perform the requested operations.
EROFS	Read-only file system.
EXDEV	Attempt to link a file to another file system.

DESCRIPTION:

The `link()` function atomically creates a new link for an existing file and increments the link count for the file.

If the `link()` function fails, no directories are modified.

The `existing` argument should not be a directory.

The caller may (or may not) need permission to access the existing file.

NOTES:

NONE

4.4.14 symlink - Creates a symbolic link to a file

CALLING SEQUENCE:

```
#include <unistd.h>

int symlink(
  const char *topath,
  const char *frompath
);
```

STATUS CODES:

EACCES	Search permission is denied for a directory in a file's path prefix
EEXIST	The named file already exists.
ENAMETOOLONG	Length of a filename string exceeds PATH_MAX and _POSIX_NO_TRUNC is in effect.
ENOENT	A file or directory does not exist.
ENOSPC	No space left on disk.
ENOTDIR	A component of the specified pathname was not a directory when a directory was expected.
EPERM	Operation is not permitted. Process does not have the appropriate priviledges or permissions to perform the requested operations.
EROFS	Read-only file system.

DESCRIPTION:

The `symlink()` function creates a symbolic link from the frombath to the topath. The symbolic link will be interpreted at run-time.

If the `symlink()` function fails, no directories are modified.

The caller may (or may not) need permission to access the existing file.

NOTES:

NONE

4.4.15 readlink - Obtain the name of a symbolic link destination

CALLING SEQUENCE:

```
#include <unistd.h>

int readlink(
  const char *path,
  char       *buf,
  size_t      bufsize
);
```

STATUS CODES:

EACCES	Search permission is denied for a directory in a file's path prefix
ENAMETOOLONG	Length of a filename string exceeds PATH_MAX and _POSIX_NO_TRUNC is in effect.
ENOENT	A file or directory does not exist.
ENOTDIR	A component of the prefix pathname was not a directory when a directory was expected.
ELOOP	Too many symbolic links were encountered in the pathname.
EINVAL	The pathname does not refer to a symbolic link
EFAULT	An invalid pointer was passed into the `readlink()` routine.

DESCRIPTION:

The `readlink()` function places the symbolic link destination into `buf` argument and returns the number of characters copied.

If the symbolic link destination is longer than bufsize characters the name will be truncated.

NOTES:

NONE

4.4.16 mkdir - Makes a directory

CALLING SEQUENCE:

```
#include <sys/types.h>
#include <sys/stat.h>

int mkdir(
  const char *path,
  mode_t      mode
);
```

STATUS CODES:

EACCES	Search permission is denied for a directory in a file's path prefix
EEXIST	The name file already exist.
EMLINK	The number of links would exceed LINK_MAX
ENAMETOOLONG	Length of a filename string exceeds PATH_MAX and _POSIX_NO_TRUNC is in effect.
ENOENT	A file or directory does not exist.
ENOSPC	No space left on disk.
ENOTDIR	A component of the specified pathname was not a directory when a directory was expected.
EROFS	Read-only file system.

DESCRIPTION:

The `mkdir()` function creates a new diectory named `path`. The permission bits (modified by the file creation mask) are set from `mode`. The owner and group IDs for the directory are set from the effective user ID and group ID.

The new directory may (or may not) contain entries for.. and .. but is otherwise empty.

NOTES:

NONE

4.4.17 mkfifo - Makes a FIFO special file

CALLING SEQUENCE:

```
#include <sys/types.h>
#include <sys/stat.h>


int mkfifo(
  const char *path,
  mode_t      mode
);
```

STATUS CODES:

EACCES	Search permission is denied for a directory in a file's path prefix
EEXIST	The named file already exists.
ENOENT	A file or directory does not exist.
ENOSPC	No space left on disk.
ENOTDIR	A component of the specified `path` was not a directory when a directory was expected.
EROFS	Read-only file system.

DESCRIPTION:

The `mkfifo()` function creates a new FIFO special file named `path`. The permission bits (modified by the file creation mask) are set from `mode`. The owner and group IDs for the FIFO are set from the efective user ID and group ID.

NOTES:

NONE

4.4.18 unlink - Removes a directory entry

CALLING SEQUENCE:

```
#include <unistd.h>

int unlink(
  const char path
);
```

STATUS CODES:

EACCES	Search permission is denied for a directory in a file's path prefix
EBUSY	The directory is in use.
ENAMETOOLONG	Length of a filename string exceeds PATH_MAX and _POSIX_NO_TRUNC is in effect.
ENOENT	A file or directory does not exist.
ENOTDIR	A component of the specified `path` was not a directory when a directory was expected.
EPERM	Operation is not permitted. Process does not have the appropriate priviledges or permissions to perform the requested operations.
EROFS	Read-only file system.

DESCRIPTION:

The `unlink` function removes the link named by `path` and decrements the link count of the file referenced by the link. When the link count goes to zero and no process has the file open, the space occupied by the file is freed and the file is no longer accessible.

NOTES:

NONE

4.4.19 rmdir - Delete a directory

CALLING SEQUENCE:

```
#include <unistd.h>

int rmdir(
  const char *pathname
);
```

STATUS CODES:

EPERM	The filesystem containing `pathname` does not support the removal of directories.
EFAULT	`pathname` points ouside your accessible address space.
EACCES	Write access to the directory containing `pathname` was not allowed for the process's effective uid, or one of the directories in `pathname` did not allow search (execute) permission.
EPERM	The directory containing `pathname` has the stickybit (S_ISVTX) set and the process's effective uid is neither the uid of the file to be delected nor that of the director containing it.
ENAMETOOLONG	`pathname` was too long.
ENOENT	A dirctory component in `pathname` does not exist or is a dangling symbolic link.
ENOTDIR	`pathname`, or a component used as a directory in `pathname`, is not, in fact, a directory.
ENOTEMPTY	`pathname` contains entries other than . and .. .
EBUSY	`pathname` is the current working directory or root directory of some process
EBUSY	`pathname` is the current directory or root directory of some process.
ENOMEM	Insufficient kernel memory was available
EROGS	`pathname` refers to a file on a read-only filesystem.
ELOOP	`pathname` contains a reference to a circular symbolic link

DESCRIPTION:

`rmdir` deletes a directory, which must be empty

NOTES:

NONE

4.4.20 rename - Renames a file

CALLING SEQUENCE:

```
#include <unistd.h>

int rename(
  const char *old,
  const char *new
);
```

STATUS CODES:

EACCES	Search permission is denied for a directory in a file's path prefix.
EBUSY	The directory is in use.
EEXIST	The named file already exists.
EINVAL	Invalid argument.
EISDIR	Attempt to open a directory for writing or to rename a file to be a directory.
EMLINK	The number of links would exceed LINK_MAX.
ENAMETOOLONG	Length of a filename string exceeds PATH_MAX and _POSIX_NO_TRUNC is in effect.
ENOENT	A file or directory does no exist.
ENOSPC	No space left on disk.
ENOTDIR	A component of the specified pathname was not a directory when a directory was expected.
ENOTEMPTY	Attempt to delete or rename a non-empty directory.
EROFS	Read-only file system
EXDEV	Attempt to link a file to another file system.

DESCRIPTION:

The `rename()` function causes the file known bo `old` to now be known as `new`.

Ordinary files may be renamed to ordinary files, and directories may be renamed to directories; however, files cannot be converted using `rename()`. The `new` pathname may not contain a path prefix of `old`.

NOTES:

If a file already exists by the name `new`, it is removed. The `rename()` function is atomic. If the `rename()` detects an error, no files are removed. This guarantees that the `rename("x", "x")` does not remove `x`.

You may not rename dot or dot-dot.

The routine is implemented in Cygnus newlib using `link()` and `unlink()`.

4.4.21 stat - Gets information about a file

CALLING SEQUENCE:

```
#include <sys/types.h>
#include <sys/stat.h>

int stat(
  const char  *path,
  struct stat *buf
);
```

STATUS CODES:

EACCES	Search permission is denied for a directory in a file's path prefix.
EBADF	Invalid file descriptor.
ENAMETOOLONG	Length of a filename string exceeds PATH_MAX and _POSIX_NO_TRUNC is in effect.
ENOENT	A file or directory does not exist.
ENOTDIR	A component of the specified pathname was not a directory when a directory was expected.

DESCRIPTION:

The `path` argument points to a pathname for a file. Read, write, or execute permission for the file is not required, but all directories listed in `path` must be searchable. The `stat()` function obtains information about the named file and writes it to the area pointed to by `buf`.

NOTES:

NONE

4.4.22 fstat - Gets file status

CALLING SEQUENCE:

```
#include <sys/types.h>
#include <sys/stat.h>

int fstat(
  int          fildes,
  struct stat *buf
);
```

STATUS CODES:

EBADF Invalid file descriptor

DESCRIPTION:

The `fstat()` function obtains information about the file associated with `fildes` and writes it to the area pointed to by the `buf` argument.

NOTES:

If the filesystem object referred to by `fildes` is a link, then the information returned in `buf` refers to the destination of that link. This is in contrast to `lstat()` which does not follow the link.

4.4.23 lstat - Gets file status

CALLING SEQUENCE:

```
#include <sys/types.h>
#include <sys/stat.h>

int lstat(
  int          fildes,
  struct stat *buf
);
```

STATUS CODES:

EBADF Invalid file descriptor

DESCRIPTION:

The `lstat()` function obtains information about the file associated with `fildes` and writes it to the area pointed to by the `buf` argument.

NOTES:

If the filesystem object referred to by `fildes` is a link, then the information returned in `buf` refers to the link itself. This is in contrast to `fstat()` which follows the link.

The `lstat()` routine is defined by BSD 4.3 and SVR4 and not included in POSIX 1003.1b-1996.

4.4.24 access - Check permissions for a file

CALLING SEQUENCE:

```
#include <unistd.h>

int access(
  const char *pathname,
  int         mode
);
```

STATUS CODES:

EACCES	The requested access would be denied, either to the file itself or one of the directories in `pathname`.
EFAULT	`pathname` points outside your accessible address space.
EINVAL	`Mode` was incorrectly specified.
ENAMETOOLONG	`pathname` is too long.
ENOENT	A directory component in `pathname` would have been accessible but does not exist or was a dangling symbolic link.
ENOTDIR	A component used as a directory in `pathname` is not, in fact, a directory.
ENOMEM	Insufficient kernel memory was available.

DESCRIPTION:

`Access` checks whether the process would be allowed to read, write or test for existence of the file (or other file system object) whose name is `pathname`. If `pathname` is a symbolic link permissions of the file referred by this symbolic link are tested.

`Mode` is a mask consisting of one or more of R_OK, W_OK, X_OK and F_OK.

NOTES:

NONE

4.4.25 chmod - Changes file mode.

CALLING SEQUENCE:

```
#include <sys/types.h>
#include <sys/stat.h>

int chmod(
  const char *path,
  mode_t      mode
);
```

STATUS CODES:

EACCES	Search permission is denied for a directory in a file's path prefix
ENAMETOOLONG	Length of a filename string exceeds PATH_MAX and _POSIX_NO_TRUNC is in effect.
ENOENT	A file or directory does not exist.
ENOTDIR	A component of the specified pathname was not a directory when a directory was expected.
EPERM	Operation is not permitted. Process does not have the appropriate priviledges or permissions to perform the requested operations.
EROFS	Read-only file system.

DESCRIPTION:

Set the file permission bits, the set user ID bit, and the set group ID bit for the file named by `path` to `mode`. If the effective user ID does not match the owner of the file and the calling process does not have the appropriate privileges, `chmod()` returns -1 and sets `errno` to `EPERM`.

NOTES:

NONE

4.4.26 fchmod - Changes permissions of a file

CALLING SEQUENCE:

```
#include <sys/types.h>
#include <sys/stat.h>

int fchmod(
  int    fildes,
  mode_t mode
);
```

STATUS CODES:

EACCES	Search permission is denied for a directory in a file's path prefix.
EBADF	The descriptor is not valid.
EFAULT	`path` points outside your accessible address space.
EIO	A low-level I/o error occurred while modifying the inode.
ELOOP	`path` contains a circular reference
ENAMETOOLONG	Length of a filename string exceeds PATH_MAX and _POSIX_NO_TRUNC is in effect.
ENOENT	A file or directory does no exist.
ENOMEM	Insufficient kernel memory was avaliable.
ENOTDIR	A component of the specified pathname was not a directory when a directory was expected.
EPERM	The effective UID does not match the owner of the file, and is not zero
EROFS	Read-only file system

DESCRIPTION:

The mode of the file given by `path` or referenced by `filedes` is changed.

NOTES:

NONE

4.4.27 getdents - Get directory entries

CALLING SEQUENCE:

```
#include <unistd.h>
#include <linux/dirent.h>
#include <linux/unistd.h>

long getdents(
  int   dd_fd,
  char *dd_buf,
  int   dd_len
);
```

STATUS CODES:

A successful call to `getdents` returns th the number of bytes read. On end of directory, 0 is returned. When an error occurs, -1 is returned, and `errno` is set appropriately.

EBADF	Invalid file descriptor `fd`.
EFAULT	Argument points outside the calling process's address space.
EINVAL	Result buffer is too small.
ENOENT	No such directory.
ENOTDIR	File descriptor does not refer to a directory.

DESCRIPTION:

`getdents` reads several `dirent` structures from the directory pointed by `fd` into the memory area pointed to by `dirp`. The parameter `count` is the size of the memory area.

NOTES:

NONE

4.4.28 chown - Changes the owner and/or group of a file.

CALLING SEQUENCE:

```
#include <sys/types.h>
#include <unistd.h>

int chown(
  const char *path,
  uid_t       owner,
  gid_t       group
);
```

STATUS CODES:

EACCES	Search permission is denied for a directory in a file's path prefix
EINVAL	Invalid argument
ENAMETOOLONG	Length of a filename string exceeds PATH_MAX and _POSIX_NO_TRUNC is in effect.
ENOENT	A file or directory does not exist.
ENOTDIR	A component of the specified pathname was not a directory when a directory was expected.
EPERM	Operation is not permitted. Process does not have the appropriate priviledges or permissions to perform the requested operations.
EROFS	Read-only file system.

DESCRIPTION:

The user ID and group ID of the file named by `path` are set to `owner` and `path`, respectively.

For regular files, the set group ID (S_ISGID) and set user ID (S_ISUID) bits are cleared.

Some systems consider it a security violation to allow the owner of a file to be changed, If users are billed for disk space usage, loaning a file to another user could result in incorrect billing. The `chown()` function may be restricted to privileged users for some or all files. The group ID can still be changed to one of the supplementary group IDs.

NOTES:

This function may be restricted for some file. The `pathconf` function can be used to test the `_PC_CHOWN_RESTRICTED` flag.

4.4.29 utime - Change access and/or modification times of an inode

CALLING SEQUENCE:

```
#include <sys/types.h>

int utime(
  const char     *filename,
  struct utimbuf *buf
);
```

STATUS CODES:

EACCES	Permission to write the file is denied
ENOENT	`Filename` does not exist

DESCRIPTION:

`Utime` changes the access and modification times of the inode specified by `filename` to the `actime` and `modtime` fields of `buf` respectively. If `buf` is NULL, then the access and modification times of the file are set to the current time.

NOTES:

NONE

4.4.30 ftruncate - truncate a file to a specified length

CALLING SEQUENCE:

```
#include <unistd.h>

int ftrunctate(
  int    fd,
  size_t length
);
```

STATUS CODES:

ENOTDIR	A component of the path prefix is not a directory.
EINVAL	The pathname contains a character with the high-order bit set.
ENAMETOOLONG	A component of a pathname exceeded 255 characters, or an entire path name exceeded 1023 characters.
ENOENT	The named file does not exist.
EACCES	The named file is not writable by the user.
EACCES	Search permission is denied for a component of the path prefix.
ELOOP	Too many symbolic links were encountered in translating the pathname
EISDIR	The named file is a directory.
EROFS	The named file resides on a read-only file system
ETXTBSY	The file is a pure procedure (shared text) file that is being executed
EIO	An I/O error occurred updating the inode.
EFAULT	`Path` points outside the process's allocated address space.
EBADF	The `fd` is not a valid descriptor.

DESCRIPTION:

`truncate()` causes the file named by `path` or referenced by `fd` to be truncated to at most `length` bytes in size. If the file previously was larger than this size, the extra data is lost. With `ftruncate()`, the file must be open for writing.

NOTES:

NONE

4.4.31 truncate - truncate a file to a specified length

CALLING SEQUENCE:

```
#include <unistd.h>

int trunctate(
  const char *path,
  size_t      length
);
```

STATUS CODES:

ENOTDIR	A component of the path prefix is not a directory.
EINVAL	The pathname contains a character with the high-order bit set.
ENAMETOOLONG	A component of a pathname exceeded 255 characters, or an entire path name exceeded 1023 characters.
ENOENT	The named file does not exist.
EACCES	The named file is not writable by the user.
EACCES	Search permission is denied for a component of the path prefix.
ELOOP	Too many symbolic links were encountered in translating the pathname
EISDIR	The named file is a directory.
EROFS	The named file resides on a read-only file system
ETXTBSY	The file is a pure procedure (shared text) file that is being executed
EIO	An I/O error occurred updating the inode.
EFAULT	`Path` points outside the process's allocated address space.
EBADF	The `fd` is not a valid descriptor.

DESCRIPTION:

`truncate()` causes the file named by `path` or referenced by `fd` to be truncated to at most `length` bytes in size. If the file previously was larger than this size, the extra data is lost. With `ftruncate()`, the file must be open for writing.

NOTES:

NONE

4.4.32 pathconf - Gets configuration values for files

CALLING SEQUENCE:

```
#include <unistd.h>

int pathconf(
  const char *path,
  int         name
);
```

STATUS CODES:

EINVAL	Invalid argument
EACCES	Permission to write the file is denied
ENAMETOOLONG	Length of a filename string exceeds PATH_MAX and _POSIX_NO_TRUNC is in effect.
ENOENT	A file or directory does not exist
ENOTDIR	A component of the specified `path` was not a directory whan a directory was expected.

DESCRIPTION:

`pathconf()` gets a value for the configuration option `name` for the open file descriptor `filedes`.

The possible values for `name` are:

_PC_LINK_MAX	returns the maximum number of links to the file. If `filedes` or `path` refer to a directory, then the value applies to the whole directory. The corresponding macro is `_POSIX_LINK_MAX`.
_PC_MAX_CANON	returns the maximum length of a formatted input line, where `filedes` or `path` must refer to a terminal. The corresponding macro is `_POSIX_MAX_CANON`.
_PC_MAX_INPUT	returns the maximum length of an input line, where `filedes` or `path` must refer to a terminal. The corresponding macro is `_POSIX_MAX_INPUT`.
_PC_NAME_MAX	returns the maximum length of a filename in the directory `path` or `filedes`. The process is allowed to create. The corresponding macro is `_POSIX_NAME_MAX`.
_PC_PATH_MAX	returns the maximum length of a relative pathname when `path` or `filedes` is the current working directory. The corresponding macro is `_POSIX_PATH_MAX`.

_PC_PIPE_BUF returns the size of the pipe buffer, where `filedes` must refer to a pipe or FIFO and `path` must refer to a FIFO. The corresponding macro is `_POSIX_PIPE_BUF`.

_PC_CHOWN_RESTRICTED
returns nonzero if the chown(2) call may not be used on this file. If `filedes` or `path` refer to a directory, then this applies to all files in that directory. The corresponding macro is `_POSIX_CHOWN_RESTRICTED`.

NOTES:

Files with name lengths longer than the value returned for `name` equal `_PC_NAME_MAX` may exist in the given directory.

4.4.33 fpathconf - Gets configuration values for files

CALLING SEQUENCE:

```
#include <unistd.h>

int fpathconf(
  int filedes,
  int name
);
```

STATUS CODES:

EINVAL Invalid argument

EACCES Permission to write the file is denied

ENAMETOOLONG

Length of a filename string exceeds PATH_MAX and _POSIX_NO_TRUNC is in effect.

ENOENT A file or directory does not exist

ENOTDIR A component of the specified `path` was not a directory whan a directory was expected.

DESCRIPTION:

`pathconf()` gets a value for the configuration option `name` for the open file descriptor `filedes`.

The possible values for name are:

_PC_LINK_MAX returns the maximum number of links to the file. If `filedes` or `path` refer to a directory, then the value applies to the whole directory. The corresponding macro is _POSIX_LINK_MAX.

_PC_MAX_CANON returns the maximum length of a formatted input line, where `filedes` or `path` must refer to a terminal. The corresponding macro is `_POSIX_MAX_CANON`.

_PC_MAX_INPUT returns the maximum length of an input line, where `filedes` or `path` must refer to a terminal. The corresponding macro is `_POSIX_MAX_INPUT`.

_PC_NAME_MAX returns the maximum length of a filename in the directory `path` or `filedes`. The process is allowed to create. The corresponding macro is `_POSIX_NAME_MAX`.

_PC_PATH_MAX returns the maximum length of a relative pathname when `path` or `filedes` is the current working directory. The corresponding macro is `_POSIX_PATH_MAX`.

_PC_PIPE_BUF returns the size of the pipe buffer, where `filedes` must refer to a pipe or FIFO and `path` must refer to a FIFO. The corresponding macro is `_POSIX_PIPE_BUF`.

_PC_CHOWN_RESTRICTED
returns nonzero if the `chown()` call may not be used on this file. If `filedes` or `path` refer to a directory, then this applies to all files in that directory. The corresponding macro is `_POSIX_CHOWN_RESTRICTED`.

NOTES:

NONE

4.4.34 mknod - create a directory

CALLING SEQUENCE:

```
#include <unistd.h>
#include <fcntl.h>
#include <sys/types.h>
#include <sys/stat.h>

long mknod(
  const char *pathname,
  mode_t      mode,
  dev_t       dev
);
```

STATUS CODES:

`mknod` returns zero on success, or -1 if an error occurred (in which case, errno is set appropriately).

ENAMETOOLONG `pathname` was too long.

ENOENT A directory component in `pathname` does not exist or is a dangling symbolic link.

ENOTDIR A component used in the directory `pathname` is not, in fact, a directory.

ENOMEM Insufficient kernel memory was available

EROFS `pathname` refers to a file on a read-only filesystem.

ELOOP `pathname` contains a reference to a circular symbolic link, ie a symbolic link whose expansion contains a reference to itself.

ENOSPC The device containing `pathname` has no room for the new node.

DESCRIPTION:

`mknod` attempts to create a filesystem node (file, device special file or named pipe) named `pathname`, specified by `mode` and `dev`.

`mode` specifies both the permissions to use and the type of node to be created.

It should be a combination (using bitwise OR) of one of the file types listed below and the permissions for the new node.

The permissions are modified by the process's `umask` in the usual way: the permissions of the created node are `(mode & ~umask)`.

The file type should be one of `S_IFREG`, `S_IFCHR`, `S_IFBLK` and `S_IFIFO` to specify a normal file (which will be created empty), character special file, block special file or FIFO (named pipe), respectively, or zero, which will create a normal file.

If the file type is `S_IFCHR` or `S_IFBLK` then `dev` specifies the major and minor numbers of the newly created device special file; otherwise it is ignored.

The newly created node will be owned by the effective uid of the process. If the directory containing the node has the set group id bit set, or if the filesystem is mounted with BSD group semantics, the new node will inherit the group ownership from its parent directory; otherwise it will be owned by the effective gid of the process.

NOTES:

NONE

5 Input and Output Primitives Manager

5.1 Introduction

The input and output primitives manager is ...

The directives provided by the input and output primitives manager are:

- `pipe` - Create an Inter-Process Channel
- `dup` - Duplicates an open file descriptor
- `dup2` - Duplicates an open file descriptor
- `close` - Closes a file
- `read` - Reads from a file
- `write` - Writes to a file
- `fcntl` - Manipulates an open file descriptor
- `lseek` - Reposition read/write file offset
- `fsync` - Synchronize file complete in-core state with that on disk
- `fdatasync` - Synchronize file in-core data with that on disk
- `mount` - Mount a file system
- `unmount` - Unmount file systems
- `aio_read` - Asynchronous Read
- `aio_write` - Asynchronous Write
- `lio_listio` - List Directed I/O
- `aio_error` - Retrieve Error Status of Asynchronous I/O Operation
- `aio_return` - Retrieve Return Status Asynchronous I/O Operation
- `aio_cancel` - Cancel Asynchronous I/O Request
- `aio_suspend` - Wait for Asynchronous I/O Request
- `aio_fsync` - Asynchronous File Synchronization

5.2 Background

There is currently no text in this section.

5.3 Operations

There is currently no text in this section.

5.4 Directives

This section details the input and output primitives manager's directives. A subsection is dedicated to each of this manager's directives and describes the calling sequence, related constants, usage, and status codes.

5.4.1 pipe - Create an Inter-Process Channel

CALLING SEQUENCE:

```
int pipe(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

This routine is not currently supported by RTEMS but could be in a future version.

5.4.2 dup - Duplicates an open file descriptor

CALLING SEQUENCE:

```
#include <unistd.h>

int dup(
  int fildes
);
```

STATUS CODES:

EBADF	Invalid file descriptor.
EINTR	Function was interrupted by a signal.
EMFILE	The process already has the maximum number of file descriptors open and tried to open a new one.

DESCRIPTION:

The `dup` function returns the lowest numbered available file descriptor. This new desciptor refers to the same open file as the original descriptor and shares any locks.

NOTES:

NONE

5.4.3 dup2 - Duplicates an open file descriptor

CALLING SEQUENCE:

```
#include <unistd.h>

int dup2(
  int fildes,
  int fildes2
);
```

STATUS CODES:

EBADF	Invalid file descriptor.
EINTR	Function was interrupted by a signal.
EMFILE	The process already has the maximum number of file descriptors open and tried to open a new one.

DESCRIPTION:

`Dup2` creates a copy of the file descriptor `oldfd`.

The old and new descriptors may be used interchangeably. They share locks, file position pointers and flags; for example, if the file position is modified by using `lseek` on one of the descriptors, the position is also changed for the other.

NOTES:

NONE

5.4.4 close - Closes a file.

CALLING SEQUENCE:

```
#include <unistd.h>

int close(
  int fildes
);
```

STATUS CODES:

EBADF	Invalid file descriptor
EINTR	Function was interrupted by a signal.

DESCRIPTION:

The `close()` function deallocates the file descriptor named by `fildes` and makes it available for reuse. All outstanding record locks owned by this process for the file are unlocked.

NOTES:

A signal can interrupt the `close()` function. In that case, `close()` returns -1 with `errno` set to EINTR. The file may or may not be closed.

5.4.5 read - Reads from a file.

CALLING SEQUENCE:

```
#include <unistd.h>

int read(
  int           fildes,
  void         *buf,
  unsigned int  nbyte
);
```

STATUS CODES:

On error, this routine returns -1 and sets `errno` to one of the following:

EAGAIN	The O_NONBLOCK flag is set for a file descriptor and the process would be delayed in the I/O operation.
EBADF	Invalid file descriptor
EINTR	Function was interrupted by a signal.
EIO	Input or output error

DESCRIPTION:

The `read()` function reads `nbyte` bytes from the file associated with `fildes` into the buffer pointed to by `buf`.

The `read()` function returns the number of bytes actually read and placed in the buffer. This will be less than `nbyte` if:

- The number of bytes left in the file is less than `nbyte`.
- The `read()` request was interrupted by a signal.
- The file is a pipe or FIFO or special file with less than `nbytes` immediately available for reading.

When attempting to read from any empty pipe or FIFO:

- If no process has the pipe open for writing, zero is returned to indicate end-of-file.
- If some process has the pipe open for writing and O_NONBLOCK is set, -1 is returned and `errno` is set to EAGAIN.
- If some process has the pipe open for writing and O_NONBLOCK is clear, `read()` waits for some data to be written or the pipe to be closed.

When attempting to read from a file other than a pipe or FIFO and no data is available.

- If O_NONBLOCK is set, -1 is returned and `errno` is set to EAGAIN.
- If O_NONBLOCK is clear, `read()` waits for some data to become available.
- The O_NONBLOCK flag is ignored if data is available.

NOTES:

NONE

5.4.6 write - Writes to a file

CALLING SEQUENCE:

```
#include <unistd.h>

int write(
  int           fildes,
  const void   *buf,
  unsigned int  nbytes
);
```

STATUS CODES:

EAGAIN	The O_NONBLOCK flag is set for a file descriptor and the process would be delayed in the I/O operation.
EBADF	Invalid file descriptor
EFBIG	An attempt was made to write to a file that exceeds the maximum file size
EINTR	The function was interrupted by a signal.
EIO	Input or output error.
ENOSPC	No space left on disk.
EPIPE	Attempt to write to a pope or FIFO with no reader.

DESCRIPTION:

The `write()` function writes `nbyte` from the array pointed to by `buf` into the file associated with `fildes`.

If `nybte` is zero and the file is a regular file, the `write()` function returns zero and has no other effect. If `nbyte` is zero and the file is a special file, te results are not portable.

The `write()` function returns the number of bytes written. This number will be less than `nbytes` if there is an error. It will never be greater than `nbytes`.

NOTES:

NONE

5.4.7 fcntl - Manipulates an open file descriptor

CALLING SEQUENCE:

```
#include <sys/types.h>
#include <fcntl.h>
#include <unistd.h>

int fcntl(
  int fildes,
  int cmd
);
```

STATUS CODES:

EACCESS	Search permission is denied for a direcotry in a file's path prefix.
EAGAIN	The O_NONBLOCK flag is set for a file descriptor and the process would be delayed in the I/O operation.
EBADF	Invalid file descriptor
EDEADLK	An `fcntl` with function F_SETLKW would cause a deadlock.
EINTR	The functioin was interrupted by a signal.
EINVAL	Invalid argument
EMFILE	Too many file descriptor or in use by the process.
ENOLCK	No locks available

DESCRIPTION:

`fcntl()` performs one of various miscellaneous operations on `fd`. The operation in question is determined by `cmd`:

F_DUPFD Makes `arg` be a copy of `fd`, closing `fd` first if necessary.

The same functionality can be more easily achieved by using `dup2()`.

The old and new descriptors may be used interchangeably. They share locks, file position pointers and flags; for example, if the file position is modified by using `lseek()` on one of the descriptors, the position is also changed for the other.

The two descriptors do not share the close-on-exec flag, however. The close-on-exec flag of the copy is off, meaning that it will be closed on exec.

On success, the new descriptor is returned.

F_GETFD Read the close-on-exec flag. If the low-order bit is 0, the file will remain open across exec, otherwise it will be closed.

F_SETFD Set the close-on-exec flag to the value specified by `arg` (only the least significant bit is used).

F_GETFL Read the descriptor's flags (all flags (as set by open()) are returned).

F_SETFL Set the descriptor's flags to the value specified by `arg`. Only `O_APPEND` and `O_NONBLOCK` may be set.

The flags are shared between copies (made with `dup()` etc.) of the same file descriptor.

The flags and their semantics are described in `open()`.

F_GETLK, F_SETLK and F_SETLKW
Manage discretionary file locks. The third argument `arg` is a pointer to a struct flock (that may be overwritten by this call).

F_GETLK Return the flock structure that prevents us from obtaining the lock, or set the `l_type` field of the lock to `F_UNLCK` if there is no obstruction.

F_SETLK The lock is set (when `l_type` is `F_RDLCK` or `F_WRLCK`) or cleared (when it is `F_UNLCK`. If lock is held by someone else, this call returns -1 and sets `errno` to EACCES or EAGAIN.

F_SETLKW Like `F_SETLK`, but instead of returning an error we wait for the lock to be released.

F_GETOWN Get the process ID (or process group) of the owner of a socket.

Process groups are returned as negative values.

F_SETOWN Set the process or process group that owns a socket.

For these commands, ownership means receiving `SIGIO` or `SIGURG` signals.

Process groups are specified using negative values.

NOTES:

The errors returned by `dup2` are different from those returned by `F_DUPFD`.

5.4.8 lseek - Reposition read/write file offset

CALLING SEQUENCE:

```
#include <sys/types.h>
#include <unistd.h>

int lseek(
  int    fildes,
  off_t  offset,
  int    whence
);
```

STATUS CODES:

EBADF	`Fildes` is not an open file descriptor.
ESPIPE	`Fildes` is associated with a pipe, socket or FIFO.
EINVAL	`Whence` is not a proper value.

DESCRIPTION:

The `lseek` function repositions the offset of the file descriptor `fildes` to the argument offset according to the directive whence. The argument `fildes` must be an open file descriptor. `Lseek` repositions the file pointer fildes as follows:

- If `whence` is SEEK_SET, the offset is set to `offset` bytes.
- If `whence` is SEEK_CUR, the offset is set to its current location plus offset bytes.
- If `whence` is SEEK_END, the offset is set to the size of the file plus `offset` bytes.

The `lseek` function allows the file offset to be set beyond the end of the existing end-of-file of the file. If data is later written at this point, subsequent reads of the data in the gap return bytes of zeros (until data is actually written into the gap).

Some devices are incapable of seeking. The value of the pointer associated with such a device is undefined.

NOTES:

NONE

5.4.9 fsync - Synchronize file complete in-core state with that on disk

CALLING SEQUENCE:

```
int fsync(
  int fd
);
```

STATUS CODES:

On success, zero is returned. On error, -1 is returned, and `errno` is set appropriately.

EBADF	`fd` is not a valid descriptor open for writing
EINVAL	`fd` is bound to a special file which does not support support synchronization
EROFS	`fd` is bound to a special file which does not support support synchronization
EIO	An error occurred during synchronization

DESCRIPTION:

`fsync` copies all in-core parts of a file to disk.

NOTES:

NONE

5.4.10 fdatasync - Synchronize file in-core data with that on disk.

CALLING SEQUENCE:

```
int fdatasync(
  int fd
);
```

STATUS CODES:

On success, zero is returned. On error, -1 is returned, and `errno` is set appropriately.

EBADF	`fd` is not a valid file descriptor open for writing.
EINVAL	`fd` is bound to a special file which does not support synchronization.
EIO	An error occurred during synchronization.
EROFS	`fd` is bound to a special file which dows not support synchronization.

DESCRIPTION:

`fdatasync` flushes all data buffers of a file to disk (before the system call returns). It resembles `fsync` but is not required to update the metadata such as access time.

Applications that access databases or log files often write a tiny data fragment (e.g., one line in a log file) and then call `fsync` immediately in order to ensure that the written data is physically stored on the harddisk. Unfortunately, fsync will always initiate two write operations: one for the newly written data and another one in order to update the modification time stored in the inode. If the modification time is not a part of the transaction concept `fdatasync` can be used to avoid unnecessary inode disk write operations.

NOTES:

NONE

5.4.11 mount - Mount a file system

CALLING SEQUENCE:

```
#include <libio.h>

int mount(
  rtems_filesystem_mount_table_entry_t **mt_entry,
  rtems_filesystem_operations_table    *fs_ops,
  rtems_filesystem_options_t            fsoptions,
  char                                 *device,
  char                                 *mount_point
);
```

STATUS CODES:

EXXX

DESCRIPTION:

The `mount` routines mounts the filesystem class which uses the filesystem operations specified by `fs_ops` and `fsoptions`. The filesystem is mounted at the directory `mount_point` and the mode of the mounted filesystem is specified by `fsoptions`. If this filesystem class requires a device, then the name of the device must be specified by `device`.

If this operation succeeds, the mount table entry for the mounted filesystem is returned in `mt_entry`.

NOTES:

NONE

5.4.12 unmount - Unmount file systems

CALLING SEQUENCE:

```
#include <libio.h>

int unmount(
  const char *mount_path
);
```

STATUS CODES:

EXXX

DESCRIPTION:

The `unmount` routine removes the attachment of the filesystem specified by `mount_path`.

NOTES:

NONE

5.4.13 aio_read - Asynchronous Read

CALLING SEQUENCE:

```
int aio_read(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

This routine is not currently supported by RTEMS but could be in a future version.

5.4.14 aio_write - Asynchronous Write

CALLING SEQUENCE:

```
int aio_write(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

This routine is not currently supported by RTEMS but could be in a future version.

5.4.15 lio_listio - List Directed I/O

CALLING SEQUENCE:

```
int lio_listio(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

This routine is not currently supported by RTEMS but could be in a future version.

5.4.16 aio_error - Retrieve Error Status of Asynchronous I/O Operation

CALLING SEQUENCE:

```
int aio_error(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

This routine is not currently supported by RTEMS but could be in a future version.

5.4.17 aio_return - Retrieve Return Status Asynchronous I/O Operation

CALLING SEQUENCE:

```
int aio_return(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

This routine is not currently supported by RTEMS but could be in a future version.

5.4.18 aio_cancel - Cancel Asynchronous I/O Request

CALLING SEQUENCE:

```
int aio_cancel(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

This routine is not currently supported by RTEMS but could be in a future version.

5.4.19 aio_suspend - Wait for Asynchronous I/O Request

CALLING SEQUENCE:

```
int aio_suspend(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

This routine is not currently supported by RTEMS but could be in a future version.

5.4.20 aio_fsync - Asynchronous File Synchronization

CALLING SEQUENCE:

```
int aio_fsync(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

This routine is not currently supported by RTEMS but could be in a future version.

6 Device- and Class- Specific Functions Manager

6.1 Introduction

The device- and class- specific functions manager is ...

The directives provided by the device- and class- specific functions manager are:

- `cfgetispeed` - Reads terminal input baud rate
- `cfgetospeed` - Reads terminal output baud rate
- `cfsetispeed` - Sets terminal input baud rate
- `cfsetospeed` - Set terminal output baud rate
- `tcgetattr` - Gets terminal attributes
- `tcsetattr` - Set terminal attributes
- `tcsendbreak` - Sends a break to a terminal
- `tcdrain` - Waits for all output to be transmitted to the terminal
- `tcflush` - Discards terminal data
- `tcflow` - Suspends/restarts terminal output
- `tcgetpgrp` - Gets foreground process group ID
- `tcsetpgrp` - Sets foreground process group ID

6.2 Background

There is currently no text in this section.

6.3 Operations

There is currently no text in this section.

6.4 Directives

This section details the device- and class- specific functions manager's directives. A subsection is dedicated to each of this manager's directives and describes the calling sequence, related constants, usage, and status codes.

6.4.1 cfgetispeed - Reads terminal input baud rate

CALLING SEQUENCE:

```
#include <termios.h>

int cfgetispeed(
  const struct termios *p
);
```

STATUS CODES:

The `cfgetispeed()` function returns a code for baud rate.

DESCRIPTION:

The `cfsetispeed()` function stores a code for the terminal speed stored in a struct termios. The codes are defined in `<termios.h>` by the macros BO, B50, B75, B110, B134, B150, B200, B300, B600, B1200, B1800, B2400, B4800, B9600, B19200, and B38400.

The `cfsetispeed()` function does not do anything to the hardware. It merely stores a value for use by `tcsetattr()`.

NOTES:

Baud rates are defined by symbols, such as B110, B1200, B2400. The actual number returned for any given speed may change from system to system.

6.4.2 cfgetospeed - Reads terminal output baud rate

CALLING SEQUENCE:

```
#include <termios.h>

int cfgetospeed(
  const struct termios *p
);
```

STATUS CODES:

The `cfgetospeed()` function returns the termios code for the baud rate.

DESCRIPTION:

The `cfgetospeed()` function returns a code for the terminal speed stored in a `struct termios`. The codes are defined in `<termios.h>` by the macros BO, B50, B75, B110, B134, B150, B200, B300, B600, B1200, B1800, B2400, B4800, B9600, B19200, and B38400.

The `cfgetospeed()` function does not do anything to the hardware. It merely returns the value stored by a previous call to `tcgetattr()`.

NOTES:

Baud rates are defined by symbols, such as B110, B1200, B2400. The actual number returned for any given speed may change from system to system.

6.4.3 cfsetispeed - Sets terminal input baud rate

CALLING SEQUENCE:

```
#include <termios.h>

int cfsetispeed(
  struct termios *p,
  speed_t         speed
);
```

STATUS CODES:

The `cfsetispeed()` function returns a zero when successful and returns -1 when an error occurs.

DESCRIPTION:

The `cfsetispeed()` function stores a code for the terminal speed stored in a struct termios. The codes are defined in `<termios.h>` by the macros B0, B50, B75, B110, B134, B150, B200, B300, B600, B1200, B1800, B2400, B4800, B9600, B19200, and B38400.

NOTES:

This function merely stores a value in the `termios` structure. It does not change the terminal speed until a `tcsetattr()` is done. It does not detect impossible terminal speeds.

6.4.4 cfsetospeed - Sets terminal output baud rate

CALLING SEQUENCE:

```
#include <termios.h>

int cfsetospeed(
  struct termios *p,
  speed_t         speed
);
```

STATUS CODES:

The `cfsetospeed()` function returns a zero when successful and returns -1 when an error occurs.

DESCRIPTION:

The `cfsetospeed()` function stores a code for the terminal speed stored in a struct `termios`. The codes are defiined in `<termios.h>` by the macros B0, B50, B75, B110, B134, B150, B200, B300, B600, B1200, B1800, B2400, B4800, B9600, B19200, and B38400.

The `cfsetospeed()` function does not do anything to the hardware. It merely stores a value for use by `tcsetattr()`.

NOTES:

This function merely stores a value in the `termios` structure. It does not change the terminal speed until a `tcsetattr()` is done. It does not detect impossible terminal speeds.

6.4.5 tcgetattr - Gets terminal attributes

CALLING SEQUENCE:

```
#include <termios.h>
#include <unistd.h>

int tcgetattr(
  int             fildes,
  struct termios *p
);
```

STATUS CODES:

EBADF	Invalid file descriptor
ENOOTY	Terminal control function attempted for a file that is not a terminal.

DESCRIPTION:

The `tcgetattr()` gets the parameters associated with the terminal referred to by `fildes` and stores them into the `termios()` structure pointed to by `termios_p`.

NOTES:

NONE

6.4.6 tcsetattr - Set terminal attributes

CALLING SEQUENCE:

```
#include <termios.h>
#include <unistd.h>

int tcsetattr(
  int                   fildes,
  int                   options,
  const struct termios *tp
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

6.4.7 tcsendbreak - Sends a break to a terminal

CALLING SEQUENCE:

```
int tcsendbreak(
  int fd
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

This routine is not currently supported by RTEMS but could be in a future version.

6.4.8 tcdrain - Waits for all output to be transmitted to the terminal.

CALLING SEQUENCE:

```
#include <termios.h>
#include <unistd.h>

int tcdrain(
  int fildes
);
```

STATUS CODES:

EBADF	Invalid file descriptor
EINTR	Function was interrupted by a signal
ENOTTY	Terminal control function attempted for a file that is not a terminal.

DESCRIPTION:

The `tcdrain()` function waits until all output written to `fildes` has been transmitted.

NOTES:

NONE

6.4.9 tcflush - Discards terminal data

CALLING SEQUENCE:

```
int tcflush(
  int fd
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

This routine is not currently supported by RTEMS but could be in a future version.

6.4.10 tcflow - Suspends/restarts terminal output.

CALLING SEQUENCE:

```
int tcflow(
  int fd
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

This routine is not currently supported by RTEMS but could be in a future version.

6.4.11 tcgetpgrp - Gets foreground process group ID

CALLING SEQUENCE:

```
int tcgetpgrp(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

This routine is not currently supported by RTEMS but could be in a future version.

6.4.12 tcsetpgrp - Sets foreground process group ID

CALLING SEQUENCE:

```
int tcsetpgrp(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

This routine is not currently supported by RTEMS but could be in a future version.

7 Language-Specific Services for the C Programming Language Manager

7.1 Introduction

The language-specific services for the C programming language manager is ...

The directives provided by the language-specific services for the C programming language manager are:

- `setlocale` - Set the Current Locale
- `fileno` - Obtain File Descriptor Number for this File
- `fdopen` - Associate Stream with File Descriptor
- `flockfile` - Acquire Ownership of File Stream
- `ftrylockfile` - Poll to Acquire Ownership of File Stream
- `funlockfile` - Release Ownership of File Stream
- `getc_unlocked` - Get Character without Locking
- `getchar_unlocked` - Get Character from stdin without Locking
- `putc_unlocked` - Put Character without Locking
- `putchar_unlocked` - Put Character to stdin without Locking
- `setjmp` - Save Context for Non-Local Goto
- `longjmp` - Non-Local Jump to a Saved Context
- `sigsetjmp` - Save Context with Signal Status for Non-Local Goto
- `siglongjmp` - Non-Local Jump with Signal Status to a Saved Context
- `tzset` - Initialize Time Conversion Information
- `strtok_r` - Reentrant Extract Token from String
- `asctime_r` - Reentrant struct tm to ASCII Time Conversion
- `ctime_r` - Reentrant time_t to ASCII Time Conversion
- `gmtime_r` - Reentrant UTC Time Conversion
- `localtime_r` - Reentrant Local Time Conversion
- `rand_r` - Reentrant Random Number Generation

7.2 Background

There is currently no text in this section.

7.3 Operations

There is currently no text in this section.

7.4 Directives

This section details the language-specific services for the C programming language manager's directives. A subsection is dedicated to each of this manager's directives and describes the calling sequence, related constants, usage, and status codes.

7.4.1 setlocale - Set the Current Locale

CALLING SEQUENCE:

```
int setlocale(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

7.4.2 fileno - Obtain File Descriptor Number for this File

CALLING SEQUENCE:

```
int fileno(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

7.4.3 fdopen - Associate Stream with File Descriptor

CALLING SEQUENCE:

```
int fdopen(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

7.4.4 flockfile - Acquire Ownership of File Stream

CALLING SEQUENCE:

```
int flockfile(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

7.4.5 ftrylockfile - Poll to Acquire Ownership of File Stream

CALLING SEQUENCE:

```
int ftrylockfile(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

7.4.6 funlockfile - Release Ownership of File Stream

CALLING SEQUENCE:

```
int funlockfile(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

7.4.7 getc_unlocked - Get Character without Locking

CALLING SEQUENCE:

```
int getc_unlocked(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

7.4.8 getchar_unlocked - Get Character from stdin without Locking

CALLING SEQUENCE:

```
int getchar_unlocked(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

7.4.9 putc_unlocked - Put Character without Locking

CALLING SEQUENCE:

```
int putc_unlocked(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

7.4.10 putchar_unlocked - Put Character to stdin without Locking

CALLING SEQUENCE:

```
int putchar_unlocked(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

7.4.11 setjmp - Save Context for Non-Local Goto

CALLING SEQUENCE:

```
int setjmp(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

7.4.12 longjmp - Non-Local Jump to a Saved Context

CALLING SEQUENCE:

```
int longjmp(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

7.4.13 sigsetjmp - Save Context with Signal Status for Non-Local Goto

CALLING SEQUENCE:

```
int sigsetjmp(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

7.4.14 siglongjmp - Non-Local Jump with Signal Status to a Saved Context

CALLING SEQUENCE:

```
int siglongjmp(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

7.4.15 tzset - Initialize Time Conversion Information

CALLING SEQUENCE:

```
int tzset(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

7.4.16 strtok_r - Reentrant Extract Token from String

CALLING SEQUENCE:

```
int strtok_r(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

7.4.17 asctime_r - Reentrant struct tm to ASCII Time Conversion

CALLING SEQUENCE:

```
int asctime_r(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

7.4.18 ctime_r - Reentrant time_t to ASCII Time Conversion

CALLING SEQUENCE:

```
int ctime_r(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

7.4.19 gmtime_r - Reentrant UTC Time Conversion

CALLING SEQUENCE:

```
int gmtime_r(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

7.4.20 localtime_r - Reentrant Local Time Conversion

CALLING SEQUENCE:

```
int localtime_r(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

7.4.21 rand_r - Reentrant Random Number Generation

CALLING SEQUENCE:

```
int rand_r(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

8 System Databases Manager

8.1 Introduction

The system databases manager is ...

The directives provided by the system databases manager are:

- `getgrgid` - Get Group File Entry for ID
- `getgrgid_r` - Reentrant Get Group File Entry
- `getgrnam` - Get Group File Entry for Name
- `getgrnam_r` - Reentrant Get Group File Entry for Name
- `getpwuid` - Get Password File Entry for UID
- `getpwuid_r` - Reentrant Get Password File Entry for UID
- `getpwnam` - Get Password File Entry for Name
- `getpwnam_r` - Reentrant Get Password File Entry for Name

8.2 Background

There is currently no text in this section.

8.3 Operations

There is currently no text in this section.

8.4 Directives

This section details the system databases manager's directives. A subsection is dedicated to each of this manager's directives and describes the calling sequence, related constants, usage, and status codes.

8.4.1 getgrgid - Get Group File Entry for ID

CALLING SEQUENCE:

```
int getgrgid(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

8.4.2 getgrgid_r - Reentrant Get Group File Entry

CALLING SEQUENCE:

```
int getgrgid_r(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

8.4.3 getgrnam - Get Group File Entry for Name

CALLING SEQUENCE:

```
int getgrnam(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

8.4.4 getgrnam_r - Reentrant Get Group File Entry for Name

CALLING SEQUENCE:

```
int getgrnam_r(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

8.4.5 getpwuid - Get Password File Entry for UID

CALLING SEQUENCE:

```
int getpwuid(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

8.4.6 getpwuid_r - Reentrant Get Password File Entry for UID

CALLING SEQUENCE:

```
int getpwuid_r(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

8.4.7 getpwnam - Password File Entry for Name

CALLING SEQUENCE:

```
int getpwnam(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

8.4.8 getpwnam_r - Reentrant Get Password File Entry for Name

CALLING SEQUENCE:

```
int getpwnam_r(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

9 Semaphore Manager

9.1 Introduction

The semaphore manager provides functions to allocate, delete, and control semaphores. This manager is based on the POSIX 1003.1 standard.

The directives provided by the semaphore manager are:

- `sem_init` - Initialize an unnamed semaphore
- `sem_destroy` - Destroy an unnamed semaphore
- `sem_open` - Open a named semaphore
- `sem_close` - Close a named semaphore
- `sem_unlink` - Remove a named semaphore
- `sem_wait` - Lock a semaphore
- `sem_trywait` - Lock a semaphore
- `sem_timedwait` - Wait on a Semaphore for a Specified Time
- `sem_post` - Unlock a semaphore
- `sem_getvalue` - Get the value of a semeaphore

9.2 Background

9.2.1 Theory

Semaphores are used for synchronization and mutual exclusion by indicating the availability and number of resources. The task (the task which is returning resources) notifying other tasks of an event increases the number of resources held by the semaphore by one. The task (the task which will obtain resources) waiting for the event decreases the number of resources held by the semaphore by one. If the number of resources held by a semaphore is insufficient (namely 0), the task requiring resources will wait until the next time resources are returned to the semaphore. If there is more than one task waiting for a semaphore, the tasks will be placed in the queue.

9.2.2 "sem_t" Structure

The `sem_t` structure is used to represent semaphores. It is passed as an argument to the semaphore directives and is defined as follows:

```
typedef int sem_t;
```

9.2.3 Building a Semaphore Attribute Set

9.3 Operations

9.3.1 Using as a Binary Semaphore

Although POSIX supports mutexes, they are only visible between threads. To work between processes, a binary semaphore must be used.

Creating a semaphore with a limit on the count of 1 effectively restricts the semaphore to being a binary semaphore. When the binary semaphore is available, the count is 1. When the binary semaphore is unavailable, the count is 0.

Since this does not result in a true binary semaphore, advanced binary features like the Priority Inheritance and Priority Ceiling Protocols are not available.

There is currently no text in this section.

9.4 Directives

This section details the semaphore manager's directives. A subsection is dedicated to each of this manager's directives and describes the calling sequence, related constants, usage, and status codes.

9.4.1 sem_init - Initialize an unnamed semaphore

CALLING SEQUENCE:

```
int sem_init(
  sem_t        *sem,
  int           pshared,
  unsigned int  value
);
```

STATUS CODES:

EINVAL	The value argument exceeds SEM_VALUE_MAX
ENOSPC	A resource required to initialize the semaphore has been exhausted The limit on semaphores (SEM_VALUE_MAX) has been reached
ENOSYS	The function sem_init is not supported by this implementation
EPERM	The process lacks appropriate privileges to initialize the semaphore

DESCRIPTION:

The sem_init function is used to initialize the unnamed semaphore referred to by "sem". The value of the initialized semaphore is the parameter "value". The semaphore remains valid until it is destroyed.

ADD MORE HERE XXX

NOTES:

If the functions completes successfully, it shall return a value of zero. Otherwise, it shall return a value of -1 and set "errno" to specify the error that occurred.

Multiprocessing is currently not supported in this implementation.

9.4.2 sem_destroy - Destroy an unnamed semaphore

CALLING SEQUENCE:

```
int sem_destroy(
  sem_t *sem
);
```

STATUS CODES:

EINVAL	The value argument exceeds SEM_VALUE_MAX
ENOSYS	The function sem_init is not supported by this implementation
EBUSY	There are currently processes blocked on the semaphore

DESCRIPTION:

The sem_destroy function is used to destroy an unnamed semaphore refered to by "sem". sem_destroy can only be used on a semaphore that was created using sem_init.

NOTES:

If the functions completes successfully, it shall return a value of zero. Otherwise, it shall return a value of -1 and set "errno" to specify the error that occurred.

Multiprocessing is currently not supported in this implementation.

9.4.3 sem_open - Open a named semaphore

CALLING SEQUENCE:

```
int sem_open(
  const char *name,
  int         oflag
);
```

ARGUMENTS:

The following flag bit may be set in oflag:

`O_CREAT` - Creates the semaphore if it does not already exist. If O_CREAT is set and the semaphore already exists then O_CREAT has no effect. Otherwise, sem_open() creates a semaphore. The O_CREAT flag requires the third and fourth argument: mode and value of type mode_t and unsigned int, respectively.

`O_EXCL` - If O_EXCL and O_CREAT are set, all call to sem_open() shall fail if the semaphore name exists

STATUS CODES:

EACCES	Valid name specified but oflag permissions are denied, or the semaphore name specified does not exist and permission to create the named semaphore is denied.
EEXIST	O_CREAT and O_EXCL are set and the named semaphore already exists.
EINTR	The sem_open() operation was interrupted by a signal.
EINVAL	The sem_open() operation is not supported for the given name.
EMFILE	Too many semaphore descriptors or file descriptors in use by this process.
ENAMETOOLONG	The length of the name exceed PATH_MAX or name component is longer than NAME_MAX while POSIX_NO_TRUNC is in effect.
ENOENT	O_CREAT is not set and the named semaphore does not exist.
ENOSPC	There is insufficient space for the creation of a new named semaphore.
ENOSYS	The function sem_open() is not supported by this implementation.

DESCRIPTION:

The sem_open() function establishes a connection between a specified semaphore and a process. After a call to sem_open with a specified semaphore name, a process can reference

to semaphore by the associated name using the address returned by the call. The oflag arguments listed above control the state of the semaphore by determining if the semaphore is created or accessed by a call to sem_open().

NOTES:

9.4.4 sem_close - Close a named semaphore

CALLING SEQUENCE:

```
int sem_close(
  sem_t *sem_close
);
```

STATUS CODES:

EACCES	The semaphore argument is not a valid semaphore descriptor.
ENOSYS	The function sem_close is not supported by this implementation.

DESCRIPTION:

The sem_close() function is used to indicate that the calling process is finished using the named semaphore indicated by sem. The function sem_close deallocates any system resources that were previously allocated by a sem_open system call. If sem_close() completes successfully it returns a 1, otherwise a value of -1 is return and errno is set.

NOTES:

9.4.5 sem_unlink - Unlink a semaphore

CALLING SEQUENCE:

```
int sem_unlink(
  const char *name
);
```

STATUS CODES:

EACCESS	Permission is denied to unlink a semaphore.
ENAMETOOLONG	The length of the strong name exceed NAME_MAX while POSIX_NO_TRUNC is in effect.
ENOENT	The name of the semaphore does not exist.
ENOSPC	There is insufficient space for the creation of a new named semaphore.
ENOSYS	The function sem_unlink is not supported by this implementation.

DESCRIPTION:

The sem_unlink() function shall remove the semaphore name by the string name. If a process is currently accessing the name semaphore, the sem_unlink command has no effect. If one or more processes have the semaphore open when the sem_unlink function is called, the destruction of semaphores shall be postponed until all reference to semaphore are destroyed by calls to sem_close, _exit(), or exec. After all references have been destroyed, it returns immediately.

If the termination is successful, the function shall return 0. Otherwise, a -1 is returned and the errno is set.

NOTES:

9.4.6 sem_wait - Wait on a Semaphore

CALLING SEQUENCE:

```
int sem_wait(
  sem_t *sem
);
```

STATUS CODES:

EINVAL The "sem" argument does not refer to a valid semaphore

DESCRIPTION:

This function attempts to lock a semaphore specified by `sem`. If the semaphore is available, then the semaphore is locked (i.e., the semaphore value is decremented). If the semaphore is unavailable (i.e., the semaphore value is zero), then the function will block until the semaphore becomes available. It will then successfully lock the semaphore. The semaphore remains locked until released by a `sem_post()` call.

If the call is unsuccessful, then the function returns -1 and sets errno to the appropriate error code.

NOTES:

Multiprocessing is not supported in this implementation.

9.4.7 sem_trywait - Non-blocking Wait on a Semaphore

CALLING SEQUENCE:

```
int sem_trywait(
  sem_t *sem
);
```

STATUS CODES:

EAGAIN	The semaphore is not available (i.e., the semaphore value is zero), so the semaphore could not be locked.
EINVAL	The `sem` argument does not refewr to a valid semaphore

DESCRIPTION:

This function attempts to lock a semaphore specified by `sem`. If the semaphore is available, then the semaphore is locked (i.e., the semaphore value is decremented) and the function returns a value of 0. The semaphore remains locked until released by a `sem_post()` call. If the semaphore is unavailable (i.e., the semaphore value is zero), then the function will return a value of -1 immediately and set `errno` to EAGAIN.

If the call is unsuccessful, then the function returns -1 and sets `errno` to the appropriate error code.

NOTES:

Multiprocessing is not supported in this implementation.

9.4.8 sem_timedwait - Wait on a Semaphore for a Specified Time

CALLING SEQUENCE:

```
int sem_timedwait(
  sem_t                 *sem,
  const struct timespec *timeout
);
```

STATUS CODES:

EAGAIN	The semaphore is not available (i.e., the semaphore value is zero), so the semaphore could not be locked.
EINVAL	The `sem` argument does not refewr to a valid semaphore

DESCRIPTION:

This function attemtps to lock a semaphore specified by `sem`, and will wait for the semaphore for an interval specified by `timeout`. If the semaphore is available, then the semaphore is locked (i.e., the semaphore value is decremented) and the function returns a value of 0. The semaphore remains locked until released by a `sem_post()` call. If the semaphore is unavailable, then the function will wait for the semaphore to become available for the amount of time specified by `timeout`.

If the semaphore does not become available within the interval specified by `timeout`, then the function returns -1 and sets `errno` to EAGAIN. If any other error occurs, the function returns -1 and sets `errno` to the appropriate error code.

NOTES:

Multiprocessing is not supported in this implementation.

9.4.9 sem_post - Unlock a Semaphore

CALLING SEQUENCE:

```
int sem_post(
  sem_t *sem
);
```

STATUS CODES:

EINVAL The `sem` argument does not refer to a valid semaphore

DESCRIPTION:

This function attempts to release the semaphore specified by `sem`. If other tasks are waiting on the semaphore, then one of those tasks (which one depends on the scheduler being used) is allowed to lock the semaphore and return from its `sem_wait()`, `sem_trywait()`, or `sem_timedwait()` call. If there are no other tasks waiting on the semaphore, then the semaphore value is simply incremented. `sem_post()` returns 0 upon successful completion.

If an error occurs, the function returns -1 and sets `errno` to the appropriate error code.

NOTES:

Multiprocessing is not supported in this implementation.

9.4.10 sem_getvalue - Get the value of a semaphore

CALLING SEQUENCE:

```
int sem_getvalue(
  sem_t *sem,
  int   *sval
);
```

STATUS CODES:

EINVAL	The "sem" argument does not refer to a valid semaphore
ENOSYS	The function sem_getvalue is not supported by this implementation

DESCRIPTION:

The sem_getvalue functions sets the location referenced by the "sval" argument to the value of the semaphore without affecting the state of the semaphore. The updated value represents a semaphore value that occurred at some point during the call, but is not necessarily the actual value of the semaphore when it returns to the calling process.

If "sem" is locked, the value returned by sem_getvalue will be zero or a negative number whose absolute value is the number of processes waiting for the semaphore at some point during the call.

NOTES:

If the functions completes successfully, it shall return a value of zero. Otherwise, it shall return a value of -1 and set "errno" to specify the error that occurred.

10 Mutex Manager

10.1 Introduction

The mutex manager implements the functionality required of the mutex manager as defined by POSIX 1003.1b-1996. This standard requires that a compliant operating system provide the facilties to ensure that threads can operate with mutual exclusion from one another and defines the API that must be provided.

The services provided by the mutex manager are:

- `pthread_mutexattr_init` - Initialize a Mutex Attribute Set
- `pthread_mutexattr_destroy` - Destroy a Mutex Attribute Set
- `pthread_mutexattr_setprotocol` - Set the Blocking Protocol
- `pthread_mutexattr_getprotocol` - Get the Blocking Protocol
- `pthread_mutexattr_setprioceiling` - Set the Priority Ceiling
- `pthread_mutexattr_getprioceiling` - Get the Priority Ceiling
- `pthread_mutexattr_setpshared` - Set the Visibility
- `pthread_mutexattr_getpshared` - Get the Visibility
- `pthread_mutex_init` - Initialize a Mutex
- `pthread_mutex_destroy` - Destroy a Mutex
- `pthread_mutex_lock` - Lock a Mutex
- `pthread_mutex_trylock` - Poll to Lock a Mutex
- `pthread_mutex_timedlock` - Lock a Mutex with Timeout
- `pthread_mutex_unlock` - Unlock a Mutex
- `pthread_mutex_setprioceiling` - Dynamically Set the Priority Ceiling
- `pthread_mutex_getprioceiling` - Dynamically Get the Priority Ceiling

10.2 Background

10.2.1 Mutex Attributes

Mutex attributes are utilized only at mutex creation time. A mutex attribute structure may be initialized and passed as an argument to the `mutex_init` routine. Note that the priority ceiling of a mutex may be set at run-time.

blocking protcol is the XXX

priority ceiling is the XXX

pshared is the XXX

10.2.2 PTHREAD_MUTEX_INITIALIZER

This is a special value that a variable of type `pthread_mutex_t` may be statically initialized to as shown below:

```
pthread_mutex_t my_mutex = PTHREAD_MUTEX_INITIALIZER;
```

This indicates that `my_mutex` will be automatically initialized by an implicit call to `pthread_mutex_init` the first time the mutex is used.

Note that the mutex will be initialized with default attributes.

10.3 Operations

There is currently no text in this section.

10.4 Services

This section details the mutex manager's services. A subsection is dedicated to each of this manager's services and describes the calling sequence, related constants, usage, and status codes.

10.4.1 pthread_mutexattr_init - Initialize a Mutex Attribute Set

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_mutexattr_init(
  pthread_mutexattr_t *attr
);
```

STATUS CODES:

EINVAL The attribute pointer argument is invalid.

DESCRIPTION:

The `pthread_mutexattr_init` routine initializes the mutex attributes object specified by `attr` with the default value for all of the individual attributes.

NOTES:

XXX insert list of default attributes here.

10.4.2 pthread_mutexattr_destroy - Destroy a Mutex Attribute Set

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_mutexattr_destroy(
  pthread_mutexattr_t *attr
);
```

STATUS CODES:

EINVAL	The attribute pointer argument is invalid.
EINVAL	The attribute set is not initialized.

DESCRIPTION:

The `pthread_mutex_attr_destroy` routine is used to destroy a mutex attributes object. The behavior of using an attributes object after it is destroyed is implementation dependent.

NOTES:

NONE

10.4.3 pthread_mutexattr_setprotocol - Set the Blocking Protocol

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_mutexattr_setprotocol(
  pthread_mutexattr_t *attr,
  int                  protocol
);
```

STATUS CODES:

EINVAL	The attribute pointer argument is invalid.
EINVAL	The attribute set is not initialized.
EINVAL	The protocol argument is invalid.

DESCRIPTION:

The `pthread_mutexattr_setprotocol` routine is used to set value of the `protocol` attribute. This attribute controls the order in which threads waiting on this mutex will receive it.

The `protocol` can be one of the following:

`PTHREAD_PRIO_NONE` in which case blocking order is FIFO.

`PTHREAD_PRIO_INHERIT`
in which case blocking order is priority with the priority inheritance protocol in effect.

`PTHREAD_PRIO_PROTECT`
in which case blocking order is priority with the priority ceiling protocol in effect.

NOTES:

There is currently no way to get simple priority blocking ordering with POSIX mutexes even though this could easily by supported by RTEMS.

10.4.4 pthread_mutexattr_getprotocol - Get the Blocking Protocol

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_mutexattr_getprotocol(
  pthread_mutexattr_t *attr,
  int                 *protocol
);
```

STATUS CODES:

EINVAL	The attribute pointer argument is invalid.
EINVAL	The attribute set is not initialized.
EINVAL	The protocol pointer argument is invalid.

DESCRIPTION:

The `pthread_mutexattr_getprotocol` routine is used to obtain the value of the `protocol` attribute. This attribute controls the order in which threads waiting on this mutex will receive it.

NOTES:

NONE

10.4.5 pthread_mutexattr_setprioceiling - Set the Priority Ceiling

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_mutexattr_setprioceiling(
  pthread_mutexattr_t *attr,
  int                  prioceiling
);
```

STATUS CODES:

EINVAL	The attribute pointer argument is invalid.
EINVAL	The attribute set is not initialized.
EINVAL	The prioceiling argument is invalid.

DESCRIPTION:

The `pthread_mutexattr_setprioceiling` routine is used to set value of the `prioceiling` attribute. This attribute specifies the priority that is the ceiling for threads obtaining this mutex. Any task obtaining this mutex may not be of greater priority that the ceiling. If it is of lower priority, then its priority will be elevated to `prioceiling`.

NOTES:

NONE

10.4.6 pthread_mutexattr_getprioceiling - Get the Priority Ceiling

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_mutexattr_getprioceiling(
  const pthread_mutexattr_t *attr,
  int                       *prioceiling
);
```

STATUS CODES:

EINVAL	The attribute pointer argument is invalid.
EINVAL	The attribute set is not initialized.
EINVAL	The prioceiling pointer argument is invalid.

DESCRIPTION:

The `pthread_mutexattr_getprioceiling` routine is used to obtain the value of the `prioceiling` attribute. This attribute specifies the priority ceiling for this mutex.

NOTES:

NONE

10.4.7 pthread_mutexattr_setpshared - Set the Visibility

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_mutexattr_setpshared(
  pthread_mutexattr_t *attr,
  int                  pshared
);
```

STATUS CODES:

EINVAL	The attribute pointer argument is invalid.
EINVAL	The attribute set is not initialized.
EINVAL	The pshared argument is invalid.

DESCRIPTION:

NOTES:

10.4.8 pthread_mutexattr_getpshared - Get the Visibility

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_mutexattr_getpshared(
  const pthread_mutexattr_t *attr,
  int                       *pshared
);
```

STATUS CODES:

EINVAL	The attribute pointer argument is invalid.
EINVAL	The attribute set is not initialized.
EINVAL	The pshared pointer argument is invalid.

DESCRIPTION:

NOTES:

10.4.9 pthread_mutex_init - Initialize a Mutex

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_mutex_init(
  pthread_mutex_t           *mutex,
  const pthread_mutexattr_t *attr
);
```

STATUS CODES:

EINVAL	The attribute set is not initialized.
EINVAL	The specified protocol is invalid.
EAGAIN	The system lacked the necessary resources to initialize another mutex.
ENOMEM	Insufficient memory exists to initialize the mutex.
EBUSY	Attempted to reinialize the object reference by mutex, a previously initialized, but not yet destroyed.

DESCRIPTION:

NOTES:

10.4.10 pthread_mutex_destroy - Destroy a Mutex

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_mutex_destroy(
  pthread_mutex_t *mutex
);
```

STATUS CODES:

EINVAL	The specified mutex is invalid.
EBUSY	Attempted to destroy the object reference by mutex, while it is locked or referenced by another thread.

DESCRIPTION:

NOTES:

10.4.11 pthread_mutex_lock - Lock a Mutex

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_mutex_lock(
  pthread_mutex_t *mutex
);
```

STATUS CODES:

EINVAL	The specified mutex is invalid.
EINVAL	The mutex has the protocol attribute of PTHREAD_PRIO_PROTECT and the priority of the calling thread is higher than the current priority ceiling.
EDEADLK	The current thread already owns the mutex.

DESCRIPTION:

NOTES:

10.4.12 pthread_mutex_trylock - Poll to Lock a Mutex

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_mutex_trylock(
  pthread_mutex_t *mutex
);
```

STATUS CODES:

EINVAL	The specified mutex is invalid.
EINVAL	The mutex has the protocol attribute of PTHREAD_PRIO_PROTECT and the priority of the calling thread is higher than the current priority ceiling.
EDEADLK	The current thread already owns the mutex.

DESCRIPTION:

NOTES:

10.4.13 pthread_mutex_timedlock - Lock a Mutex with Timeout

CALLING SEQUENCE:

```
#include <pthread.h>
#include <time.h>

int pthread_mutex_timedlock(
  pthread_mutex_t       *mutex,
  const struct timespec *timeout
);
```

STATUS CODES:

EINVAL	The specified mutex is invalid.
EINVAL	The nanoseconds field of timeout is invalid.
EINVAL	The mutex has the protocol attribute of PTHREAD_PRIO_PROTECT and the priority of the calling thread is higher than the current priority ceiling.
EDEADLK	The current thread already owns the mutex.

DESCRIPTION:

NOTES:

10.4.14 pthread_mutex_unlock - Unlock a Mutex

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_mutex_unlock(
  pthread_mutex_t *mutex
);
```

STATUS CODES:

EINVAL The specified mutex is invalid.

DESCRIPTION:

NOTES:

10.4.15 pthread_mutex_setprioceiling - Dynamically Set the Priority Ceiling

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_mutex_setprioceiling(
  pthread_mutex_t *mutex,
  int              prioceiling,
  int             *oldceiling
);
```

STATUS CODES:

EINVAL	The oldceiling pointer parameter is invalid.
EINVAL	The prioceiling parameter is an invalid priority.
EINVAL	The specified mutex is invalid.

DESCRIPTION:

NOTES:

10.4.16 pthread_mutex_getprioceiling - Get the Current Priority Ceiling

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_mutex_getprioceiling(
  pthread_mutex_t *mutex,
  int             *prioceiling
);
```

STATUS CODES:

EINVAL	The prioceiling pointer parameter is invalid.
EINVAL	The specified mutex is invalid.

DESCRIPTION:

NOTES:

11 Condition Variable Manager

11.1 Introduction

The condition variable manager ...

The directives provided by the condition variable manager are:

- `pthread_condattr_init` - Initialize a Condition Variable Attribute Set
- `pthread_condattr_destroy` - Destroy a Condition Variable Attribute Set
- `pthread_condattr_setpshared` - Set Process Shared Attribute
- `pthread_condattr_getpshared` - Get Process Shared Attribute
- `pthread_cond_init` - Initialize a Condition Variable
- `pthread_cond_destroy` - Destroy a Condition Variable
- `pthread_cond_signal` - Signal a Condition Variable
- `pthread_cond_broadcast` - Broadcast a Condition Variable
- `pthread_cond_wait` - Wait on a Condition Variable
- `pthread_cond_timedwait` - With with Timeout a Condition Variable

11.2 Background

There is currently no text in this section.

11.3 Operations

There is currently no text in this section.

11.4 Directives

This section details the condition variable manager's directives. A subsection is dedicated to each of this manager's directives and describes the calling sequence, related constants, usage, and status codes.

11.4.1 pthread_condattr_init - Initialize a Condition Variable Attribute Set

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_condattr_init(
  pthread_condattr_t *attr
);
```

STATUS CODES:

ENOMEM Insufficient memory is available to initialize the condition variable attributes object.

DESCRIPTION:

NOTES:

11.4.2 pthread_condattr_destroy - Destroy a Condition Variable Attribute Set

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_condattr_destroy(
  pthread_condattr_t *attr
);
```

STATUS CODES:

EINVAL The attribute object specified is invalid.

DESCRIPTION:

NOTES:

11.4.3 pthread_condattr_setpshared - Set Process Shared Attribute

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_condattr_setpshared(
  pthread_condattr_t *attr,
  int                 pshared
);
```

STATUS CODES:

EINVAL Invalid argument passed.

DESCRIPTION:

NOTES:

11.4.4 pthread_condattr_getpshared - Get Process Shared Attribute

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_condattr_getpshared(
  const pthread_condattr_t *attr,
  int                      *pshared
);
```

STATUS CODES:

EINVAL Invalid argument passed.

DESCRIPTION:

NOTES:

11.4.5 pthread_cond_init - Initialize a Condition Variable

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_cond_init(
  pthread_cond_t           *cond,
  const pthread_condattr_t *attr
);
```

STATUS CODES:

EAGAIN	The system lacked a resource other than memory necessary to create the initialize the condition variable object.
ENOMEM	Insufficient memory is available to initialize the condition variable object.
EBUSY	The specified condition variable has already been initialized.
EINVAL	The specified attribute value is invalid.

DESCRIPTION:

NOTES:

11.4.6 pthread_cond_destroy - Destroy a Condition Variable

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_cond_destroy(
  pthread_cond_t *cond
);
```

STATUS CODES:

EINVAL	The specified condition variable is invalid.
EBUSY	The specified condition variable is currently in use.

DESCRIPTION:

NOTES:

11.4.7 pthread_cond_signal - Signal a Condition Variable

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_cond_signal(
  pthread_cond_t *cond
);
```

STATUS CODES:

EINVAL The specified condition variable is not valid.

DESCRIPTION:

NOTES:

This routine should not be invoked from a handler from an asynchronous signal handler or an interrupt service routine.

11.4.8 pthread_cond_broadcast - Broadcast a Condition Variable

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_cond_broadcast(
  pthread_cond_t *cond
);
```

STATUS CODES:

EINVAL The specified condition variable is not valid.

DESCRIPTION:

NOTES:

This routine should not be invoked from a handler from an asynchronous signal handler or an interrupt service routine.

11.4.9 pthread_cond_wait - Wait on a Condition Variable

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_cond_wait(
  pthread_cond_t *cond,
  pthread_mutex_t *mutex
);
```

STATUS CODES:

EINVAL The specified condition variable or mutex is not initialized OR different mutexes were specified for concurrent pthread_cond_wait() and pthread_cond_timedwait() operations on the same condition variable OR the mutex was not owned by the current thread at the time of the call.

DESCRIPTION:

NOTES:

11.4.10 pthread_cond_timedwait - Wait with Timeout a Condition Variable

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_cond_timedwait(
  pthread_cond_t        *cond,
  pthread_mutex_t       *mutex,
  const struct timespec *abstime
);
```

STATUS CODES:

EINVAL The specified condition variable or mutex is not initialized OR different mutexes were specified for concurrent pthread_cond_wait() and pthread_cond_timedwait() operations on the same condition variable OR the mutex was not owned by the current thread at the time of the call.

ETIMEDOUT The specified time has elapsed without the condition variable being satisfied.

DESCRIPTION:

NOTES:

12 Memory Management Manager

12.1 Introduction

The memory management manager is ...

The directives provided by the memory management manager are:

- `mlockall` - Lock the Address Space of a Process
- `munlockall` - Unlock the Address Space of a Process
- `mlock` - Lock a Range of the Process Address Space
- `munlock` - Unlock a Range of the Process Address Space
- `mmap` - Map Process Addresses to a Memory Object
- `munmap` - Unmap Previously Mapped Addresses
- `mprotect` - Change Memory Protection
- `msync` - Memory Object Synchronization
- `shm_open` - Open a Shared Memory Object
- `shm_unlink` - Remove a Shared Memory Object

12.2 Background

There is currently no text in this section.

12.3 Operations

There is currently no text in this section.

12.4 Directives

This section details the memory management manager's directives. A subsection is dedicated to each of this manager's directives and describes the calling sequence, related constants, usage, and status codes.

12.4.1 mlockall - Lock the Address Space of a Process

CALLING SEQUENCE:

```
int mlockall(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

12.4.2 munlockall - Unlock the Address Space of a Process

CALLING SEQUENCE:

```
int munlockall(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

12.4.3 mlock - Lock a Range of the Process Address Space

CALLING SEQUENCE:

```
int mlock(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

12.4.4 munlock - Unlock a Range of the Process Address Space

CALLING SEQUENCE:

```
int munlock(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

12.4.5 mmap - Map Process Addresses to a Memory Object

CALLING SEQUENCE:

```
int mmap(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

12.4.6 munmap - Unmap Previously Mapped Addresses

CALLING SEQUENCE:

```
int munmap(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

12.4.7 mprotect - Change Memory Protection

CALLING SEQUENCE:

```
int mprotect(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

12.4.8 msync - Memory Object Synchronization

CALLING SEQUENCE:

```
int msync(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

12.4.9 shm_open - Open a Shared Memory Object

CALLING SEQUENCE:

```
int shm_open(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

12.4.10 shm_unlink - Remove a Shared Memory Object

CALLING SEQUENCE:

```
int shm_unlink(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

13 Scheduler Manager

13.1 Introduction

The scheduler manager ...

The directives provided by the scheduler manager are:

- `sched_get_priority_min` - Get Minimum Priority Value
- `sched_get_priority_max` - Get Maximum Priority Value
- `sched_rr_get_interval` - Get Timeslicing Quantum
- `sched_yield` - Yield the Processor

13.2 Background

13.2.1 Priority

In the RTEMS implementation of the POSIX API, the priorities range from the low priority of `sched_get_priority_min()` to the highest priority of `sched_get_priority_max()`. Numerically higher values represent higher priorities.

13.2.2 Scheduling Policies

The following scheduling policies are available:

SCHED_FIFO Priority-based, preemptive scheduling with no timeslicing. This is equivalent to what is called "manual round-robin" scheduling.

SCHED_RR Priority-based, preemptive scheduling with timeslicing. Time quantums are maintained on a per-thread basis and are not reset at each context switch. Thus, a thread which is preempted and subsequently resumes execution will attempt to complete the unused portion of its time quantum.

SCHED_OTHER Priority-based, preemptive scheduling with timeslicing. Time quantums are maintained on a per-thread basis and are reset at each context switch.

SCHED_SPORADIC Priority-based, preemptive scheduling utilizing three additional parameters: budget, replenishment period, and low priority. Under this policy, the thread is allowed to execute for "budget" amount of time before its priority is lowered to "low priority". At the end of each replenishment period, the thread resumes its initial priority and has its budget replenished.

13.3 Operations

There is currently no text in this section.

13.4 Directives

This section details the scheduler manager's directives. A subsection is dedicated to each of this manager's directives and describes the calling sequence, related constants, usage, and status codes.

13.4.1 sched_get_priority_min - Get Minimum Priority Value

CALLING SEQUENCE:

```
#include <sched.h>

int sched_get_priority_min(
  int policy
);
```

STATUS CODES:

On error, this routine returns -1 and sets errno to one of the following:

EINVAL The indicated policy is invalid.

DESCRIPTION:

This routine return the minimum (numerically and logically lowest) priority for the specified `policy`.

NOTES:

NONE

13.4.2 sched_get_priority_max - Get Maximum Priority Value

CALLING SEQUENCE:

```
#include <sched.h>

int sched_get_priority_max(
  int policy
);
```

STATUS CODES:

On error, this routine returns -1 and sets errno to one of the following:

EINVAL The indicated policy is invalid.

DESCRIPTION:

This routine return the maximum (numerically and logically highest) priority for the specified `policy`.

NOTES:

NONE

13.4.3 sched_rr_get_interval - Get Timeslicing Quantum

CALLING SEQUENCE:

```
#include <sched.h>

int sched_rr_get_interval(
  pid_t            pid,
  struct timespec *interval
);
```

STATUS CODES:

On error, this routine returns -1 and sets errno to one of the following:

ESRCH	The indicated process id is invalid.
EINVAL	The specified interval pointer parameter is invalid.

DESCRIPTION:

This routine returns the length of the timeslice quantum in the `interval` parameter for the specified `pid`.

NOTES:

The `pid` argument should be 0 to indicate the calling process.

13.4.4 sched_yield - Yield the Processor

CALLING SEQUENCE:

```
#include <sched.h>

int sched_yield( void );
```

STATUS CODES:

This routine always returns zero to indicate success.

DESCRIPTION:

This call forces the calling thread to yield the processor to another thread. Normally this is used to implement voluntary round-robin task scheduling.

NOTES:

NONE

14 Clock Manager

14.1 Introduction

The clock manager ...

The directives provided by the clock manager are:

- `clock_gettime` - Obtain Time of Day
- `clock_settime` - Set Time of Day
- `clock_getres` - Get Clock Resolution
- `sleep` - Delay Process Execution
- `nanosleep` - Delay with High Resolution
- `gettimeofday` - Get the Time of Day
- `time` - Get time in seconds

14.2 Background

There is currently no text in this section.

14.3 Operations

There is currently no text in this section.

14.4 Directives

This section details the clock manager's directives. A subsection is dedicated to each of this manager's directives and describes the calling sequence, related constants, usage, and status codes.

14.4.1 clock_gettime -Obtain Time of Day

CALLING SEQUENCE:

```
#include <time.h>

int clock_gettime(
  clockid_t        clock_id,
  struct timespec *tp
);
```

STATUS CODES:

On error, this routine returns -1 and sets errno to one of the following:

EINVAL	The tp pointer parameter is invalid.
EINVAL	The clock_id specified is invalid.

DESCRIPTION:

NOTES:

NONE

14.4.2 clock_settime - Set Time of Day

CALLING SEQUENCE:

```
#include <time.h>

int clock_settime(
  clockid_t              clock_id,
  const struct timespec *tp
);
```

STATUS CODES:

On error, this routine returns -1 and sets errno to one of the following:

EINVAL	The tp pointer parameter is invalid.
EINVAL	The clock_id specified is invalid.
EINVAL	The contents of the tp structure are invalid.

DESCRIPTION:

NOTES:

NONE

14.4.3 clock_getres - Get Clock Resolution

CALLING SEQUENCE:

```
#include <time.h>

int clock_getres(
  clockid_t        clock_id,
  struct timespec *res
);
```

STATUS CODES:

On error, this routine returns -1 and sets errno to one of the following:

EINVAL	The res pointer parameter is invalid.
EINVAL	The clock_id specified is invalid.

DESCRIPTION:

NOTES:

If res is NULL, then the resolution is not returned.

14.4.4 sleep - Delay Process Execution

CALLING SEQUENCE:

```
#include <time.h>

unsigned int sleep(
  unsigned int seconds
);
```

STATUS CODES:

This routine returns the number of unslept seconds.

DESCRIPTION:

The `sleep()` function delays the calling thread by the specified number of `seconds`.

NOTES:

This call is interruptible by a signal.

14.4.5 nanosleep - Delay with High Resolution

CALLING SEQUENCE:

```
#include <time.h>

int nanosleep(
  const struct timespec *rqtp,
  struct timespec       *rmtp
);
```

STATUS CODES:

On error, this routine returns -1 and sets errno to one of the following:

EINTR	The routine was interrupted by a signal.
EAGAIN	The requested sleep period specified negative seconds or nanoseconds.
EINVAL	The requested sleep period specified an invalid number for the nanoseconds field.

DESCRIPTION:

NOTES:

This call is interruptible by a signal.

14.4.6 gettimeofday - Get the Time of Day

CALLING SEQUENCE:

```
#include <sys/time.h>
#include <unistd.h>

int gettimeofday(
  struct timeval  *tp,
  struct timezone *tzp
);
```

STATUS CODES:

On error, this routine returns -1 and sets `errno` as appropriate.

EPERM	`settimeofdat` is called by someone other than the superuser.
EINVAL	Timezone (or something else) is invalid.
EFAULT	One of `tv` or `tz` pointed outside your accessible address space

DESCRIPTION:

This routine returns the current time of day in the `tp` structure.

NOTES:

Currently, the timezone information is not supported. The `tzp` argument is ignored.

14.4.7 time - Get time in seconds

CALLING SEQUENCE:

```
#include <time.h>

int time(
  time_t *tloc
);
```

STATUS CODES:

This routine returns the number of seconds since the Epoch.

DESCRIPTION:

`time` returns the time since 00:00:00 GMT, January 1, 1970, measured in seconds

If `tloc` in non null, the return value is also stored in the memory pointed to by `t`.

NOTES:

NONE

15 Timer Manager

15.1 Introduction

The timer manager is ...

The services provided by the timer manager are:

- `timer_create` - Create a Per-Process Timer
- `timer_delete` - Delete a Per-Process Timer
- `timer_settime` - Set Next Timer Expiration
- `timer_gettime` - Get Time Remaining on Timer
- `timer_getoverrun` - Get Timer Overrun Count

15.2 Background

15.3 Operations

15.4 System Calls

This section details the timer manager's services. A subsection is dedicated to each of this manager's services and describes the calling sequence, related constants, usage, and status codes.

15.4.1 timer_create - Create a Per-Process Timer

CALLING SEQUENCE:

```
#include <time.h>
#include <signal.h>

int timer_create(
  clockid_t        clock_id,
  struct sigevent *evp,
  timer_t         *timerid
);
```

STATUS CODES:

EXXX -

DESCRIPTION:

NOTES:

15.4.2 timer_delete - Delete a Per-Process Timer

CALLING SEQUENCE:

```
#include <time.h>

int timer_delete(
  timer_t timerid
);
```

STATUS CODES:

EXXX -

DESCRIPTION:

NOTES:

15.4.3 timer_settime - Set Next Timer Expiration

CALLING SEQUENCE:

```
#include <time.h>

int timer_settime(
  timer_t                  timerid,
  int                      flags,
  const struct itimerspec *value,
  struct itimerspec       *ovalue
);
```

STATUS CODES:

EXXX -

DESCRIPTION:

NOTES:

15.4.4 timer_gettime - Get Time Remaining on Timer

CALLING SEQUENCE:

```
#include <time.h>

int timer_gettime(
  timer_t            timerid,
  struct itimerspec *value
);
```

STATUS CODES:

EXXX -

DESCRIPTION:

NOTES:

15.4.5 timer_getoverrun - Get Timer Overrun Count

CALLING SEQUENCE:

```
#include <time.h>

int timer_getoverrun(
  timer_t   timerid
);
```

STATUS CODES:

EXXX -

DESCRIPTION:

NOTES:

16 Message Passing Manager

16.1 Introduction

The message passing manager is the means to provide communication and synchronization capabilities using POSIX message queues.

The directives provided by the message passing manager are:

- `mq_open` - Open a Message Queue
- `mq_close` - Close a Message Queue
- `mq_unlink` - Remove a Message Queue
- `mq_send` - Send a Message to a Message Queue
- `mq_receive` - Receive a Message from a Message Queue
- `mq_notify` - Notify Process that a Message is Available
- `mq_setattr` - Set Message Queue Attributes
- `mq_getattr` - Get Message Queue Attributes

16.2 Background

16.2.1 Theory

Message queues are named objects that operate with readers and writers. In addition, a message queue is a priority queue of discrete messages. POSIX message queues offer a certain, basic amount of application access to, and control over, the message queue geometry that can be changed.

16.2.2 Messages

A message is a variable length buffer where information can be stored to support communication. The length of the message and the information stored in that message are user-defined and can be actual data, pointer(s), or empty. There is a maximum acceptable length for a message that is associated with each message queue.

16.2.3 Message Queues

Message queues are named objects similar to the pipes of POSIX. They are a means of communicating data between multiple processes and for passing messages among tasks and ISRs. Message queues can contain a variable number of messages from 0 to an upper limit that is user defined. The maximum length of the message can be set on a per message queue basis. Normally messages are sent and received from the message queue in FIFO

order. However, messages can also be prioritized and a priority queue established for the passing of messages. Synchronization is needed when a task waits for a message to arrive at a queue. Also, a task may poll a queue for the arrival of a message.

The message queue descriptor `mqd_t` represents the message queue. It is passed as an argument to all of the message queue functions.

16.2.4 Building a Message Queue Attribute Set

The mq_attr structure is used to define the characteristics of the message queue.

```
typedef struct mq_attr{
  long mq_flags;
  long mq_maxmsg;
  long mq_msgsize;
  long mq_curmsgs;
};
```

All of these attributes are set when the message queue is created using mq_open. The mq_flags field is not used in the creation of a message queue, it is only used by mq_setattr and mq_getattr. The structure mq_attr is passed as an argument to mq_setattr and mq_getattr.

The mq_flags contain information affecting the behavior of the message queue. The O_NONBLOCK mq_flag is the only flag that is defined. In mq_setattr, the mq_flag can be set to dynamically change the blocking and non-blocking behavior of the message queue. If the non-block flag is set then the message queue is non-blocking, and requests to send and receive messages do not block waiting for resources. For a blocking message queue, a request to send might have to wait for an empty message queue, and a request to receive might have to wait for a message to arrive on the queue. Both mq_maxmsg and mq_msgsize affect the sizing of the message queue. mq_maxmsg specifies how many messages the queue can hold at any one time. mq_msgsize specifies the size of any one message on the queue. If either of these limits is exceeded, an error message results.

Upon return from mq_getattr, the mq_curmsgs is set according to the current state of the message queue. This specifies the number of messages currently on the queue.

16.2.5 Notification of a Message on the Queue

Every message queue has the ability to notify one (and only one) process whenever the queue's state changes from empty (0 messages) to nonempty. This means that the process does not have to block or constantly poll while it waits for a message. By calling mq_notify, you can attach a notification request to a message queue. When a message is received by an empty queue, if there are no processes blocked and waiting for the message, then the queue notifies the requesting process of a message arrival. There is only one signal sent by the message queue, after that the notification request is de-registered and another process can attach its notification request. After receipt of a notification, a process must re-register if it wishes to be notified again.

If there is a process blocked and waiting for the message, that process gets the message, and notification is not sent. It is also possible for another process to receive the message after the notification is sent but before the notified process has sent its receive request.

Only one process can have a notification request attached to a message queue at any one time. If another process attempts to register a notification request, it fails. You can de-register for a message queue by passing a NULL to mq_notify, this removes any notification request attached to the queue. Whenever the message queue is closed, all notification attachments are removed.

16.2.6 POSIX Interpretation Issues

There is one significant point of interpretation related to the RTEMS implementation of POSIX message queues:

What happens to threads already blocked on a message queue when the mode of that same message queue is changed from blocking to non-blocking?

The RTEMS POSIX implementation decided to unblock all waiting tasks with an `EAGAIN` status just as if a non-blocking version of the same operation had returned unsatisfied. This case is not discussed in the POSIX standard and other implementations may have chosen alternative behaviors.

16.3 Operations

16.3.1 Opening or Creating a Message Queue

If the message queue already exists, mq_open() opens it, if the message queue does not exist, mq_open() creates it. When a message queue is created, the geometry of the message queue is contained in the attribute structure that is passed in as an argument. This includes mq_msgsize that dictates the maximum size of a single message, and the mq_maxmsg that dictates the maximum number of messages the queue can hold at one time. The blocking or non-blocking behavior of the queue can also specified.

16.3.2 Closing a Message Queue

The mq_close() function is used to close the connection made to a message queue that was made during mq_open. The message queue itself and the messages on the queue are persistent and remain after the queue is closed.

16.3.3 Removing a Message Queue

The mq_unlink() function removes the named message queue. If the message queue is not open when mq_unlink is called, then the queue is immediately eliminated. Any messages

that were on the queue are lost, and the queue can not be opened again. If processes have the queue open when mq_unlink is called, the removal of the queue is delayed until the last process using the queue has finished. However, the name of the message queue is removed so that no other process can open it.

16.3.4 Sending a Message to a Message Queue

The mq_send() function adds the message in priority order to the message queue. Each message has an assigned a priority. The highest priority message is be at the front of the queue.

The maximum number of messages that a message queue may accept is specified at creation by the mq_maxmsg field of the attribute structure. If this amount is exceeded, the behavior of the process is determined according to what oflag was used when the message queue was opened. If the queue was opened with O_NONBLOCK flag set, the process does not block, and an error is returned. If the O_NONBLOCK flag was not set, the process does block and wait for space on the queue.

16.3.5 Receiving a Message from a Message Queue

The mq_receive() function is used to receive the oldest of the highest priority message(s) from the message queue specified by mqdes. The messages are received in FIFO order within the priorities. The received message's priority is stored in the location referenced by the msg_prio. If the msg_prio is a NULL, the priority is discarded. The message is removed and stored in an area pointed to by msg_ptr whose length is of msg_len. The msg_len must be at least equal to the mq_msgsize attribute of the message queue.

The blocking behavior of the message queue is set by O_NONBLOCK at mq_open or by setting O_NONBLOCK in mq_flags in a call to mq_setattr. If this is a blocking queue, the process does block and wait on an empty queue. If this a non-blocking queue, the process does not block. Upon successful completion, mq_receive returns the length of the selected message in bytes and the message is removed from the queue.

16.3.6 Notification of Receipt of a Message on an Empty Queue

The mq_notify() function registers the calling process to be notified of message arrival at an empty message queue. Every message queue has the ability to notify one (and only one) process whenever the queue's state changes from empty (0 messages) to nonempty. This means that the process does not have to block or constantly poll while it waits for a message. By calling mq_notify, a notification request is attached to a message queue. When a message is received by an empty queue, if there are no processes blocked and waiting for the message, then the queue notifies the requesting process of a message arrival. There is only one signal sent by the message queue, after that the notification request is de-registered and another process can attach its notification request. After receipt of a notification, a process must re-register if it wishes to be notified again.

If there is a process blocked and waiting for the message, that process gets the message, and notification is not sent. Only one process can have a notification request attached to a message queue at any one time. If another process attempts to register a notification request, it fails. You can de-register for a message queue by passing a NULL to mq_notify, this removes any notification request attached to the queue. Whenever the message queue is closed, all notification attachments are removed.

16.3.7 Setting the Attributes of a Message Queue

The mq_setattr() function is used to set attributes associated with the open message queue description referenced by the message queue descriptor specified by mqdes. The *omqstat represents the old or previous attributes. If omqstat is non-NULL, the function mq_setattr() stores, in the location referenced by omqstat, the previous message queue attributes and the current queue status. These values are the same as would be returned by a call to mq_getattr() at that point.

There is only one mq_attr.mq_flag that can be altered by this call. This is the flag that deals with the blocking and non-blocking behavior of the message queue. If the flag is set then the message queue is non-blocking, and requests to send or receive do not block while waiting for resources. If the flag is not set, then message send and receive may involve waiting for an empty queue or waiting for a message to arrive.

16.3.8 Getting the Attributes of a Message Queue

The mq_getattr() function is used to get status information and attributes of the message queue associated with the message queue descriptor. The results are returned in the mq_attr structure referenced by the mqstat argument. All of these attributes are set at create time, except the blocking/non-blocking behavior of the message queue which can be dynamically set by using mq_setattr. The attribute mq_curmsg is set to reflect the number of messages on the queue at the time that mq_getattr was called.

16.4 Directives

This section details the message passing manager's directives. A subsection is dedicated to each of this manager's directives and describes the calling sequence, related constants, usage, and status codes.

16.4.1 mq_open - Open a Message Queue

CALLING SEQUENCE:

```
#include <mqueue.h>

mqd_t mq_open(
  const char     *name,
  int             oflag,
  mode_t          mode,
  struct mq_attr *attr
);
```

STATUS CODES:

EACCES - Either the message queue exists and the permissions requested in oflags were denied, or the message does not exist and permission to create one is denied.

EEXIST - You tried to create a message queue that already exists.

EINVAL - An inappropriate name was given for the message queue, or the values of mq-maxmsg or mq_msgsize were less than 0.

ENOENT - The message queue does not exist, and you did not specify to create it.

EINTR - The call to mq_open was interrupted by a signal.

EMFILE - The process has too many files or message queues open. This is a process limit error.

ENFILE - The system has run out of resources to support more open message queues. This is a system error.

ENAMETOOLONG - mq_name is too long.

DESCRIPTION:

The mq_open () function establishes the connection between a process and a message queue with a message queue descriptor. If the message queue already exists, mq_open opens it, if the message queue does not exist, mq_open creates it. Message queues can have multiple senders and receivers. If mq_open is successful, the function returns a message queue descriptor. Otherwise, the function returns a -1 and sets 'errno' to indicate the error.

The name of the message queue is used as an argument. For the best of portability, the name of the message queue should begin with a "/" and no other "/" should be in the name. Different systems interpret the name in different ways.

The oflags contain information on how the message is opened if the queue already exists. This may be O_RDONLY for read only, O_WRONLY for write only, of O_RDWR, for read and write.

In addition, the oflags contain information needed in the creation of a message queue. `O_NONBLOCK` - If the non-block flag is set then the message queue is non-blocking, and requests to send and receive messages do not block waiting for resources. If the flag is not set then the message queue is blocking, and a request to send might have to wait for an empty message queue. Similarly, a request to receive might have to wait for a message to arrive on the queue. `O_CREAT` - This call specifies that the call the mq_open is to create a new message queue. In this case the mode and attribute arguments of the function call are utilized. The message queue is created with a mode similar to the creation of a file, read and write permission creator, group, and others.

The geometry of the message queue is contained in the attribute structure. This includes mq_msgsize that dictates the maximum size of a single message, and the mq_maxmsg that dictates the maximum number of messages the queue can hold at one time. If a NULL is used in the mq_attr argument, then the message queue is created with implementation defined defaults. `O_EXCL` - is always set if O_CREAT flag is set. If the message queue already exists, O_EXCL causes an error message to be returned, otherwise, the new message queue fails and appends to the existing one.

NOTES:

The mq_open () function does not add or remove messages from the queue. When a new message queue is being created, the mq_flag field of the attribute structure is not used.

16.4.2 mq_close - Close a Message Queue

CALLING SEQUENCE:

```
#include <mqueue.h>

int mq_close(
  mqd_t mqdes
);
```

STATUS CODES:

`EINVAL` - The descriptor does not represent a valid open message queue

DESCRIPTION:

The mq_close function removes the association between the message queue descriptor, mqdes, and its message queue. If mq_close() is successfully completed, the function returns a value of zero; otherwise, the function returns a value of -1 and sets errno to indicate the error.

NOTES:

If the process had successfully attached a notification request to the message queue via mq_notify, this attachment is removed, and the message queue is available for another process to attach for notification. mq_close has no effect on the contents of the message queue, all the messages that were in the queue remain in the queue.

16.4.3 mq_unlink - Remove a Message Queue

CALLING SEQUENCE:

```
#include <mqueue.h>

int mq_unlink(
  const char *name
);
```

STATUS CODES:

`EINVAL` - The descriptor does not represent a valid message queue

DESCRIPTION:

The mq_unlink() function removes the named message queue. If the message queue is not open when mq_unlink is called, then the queue is immediately eliminated. Any messages that were on the queue are lost, and the queue can not be opened again. If processes have the queue open when mq_unlink is called, the removal of the queue is delayed until the last process using the queue has finished. However, the name of the message queue is removed so that no other process can open it. Upon successful completion, the function returns a value of zero. Otherwise, the named message queue is not changed by this function call, and the function returns a value of -1 and sets errno to indicate the error.

NOTES:

Calls to mq_open() to re-create the message queue may fail until the message queue is actually removed. However, the mq_unlink() call need not block until all references have been closed; it may return immediately.

16.4.4 mq_send - Send a Message to a Message Queue

CALLING SEQUENCE:

```
#include<mqueue.h>
int mq_send(
  mqd_t        mqdes,
  const char  *msg_ptr,
  size_t       msg_len,
  unsigned int msg_prio
);
```

STATUS CODES:

`EBADF` - The descriptor does not represent a valid message queue, or the queue was opened for read only O_RDONLY `EINVAL` - The value of msg_prio was greater than the MQ_PRIO_MAX. `EMSGSIZE` - The msg_len is greater than the mq_msgsize attribute of the message queue `EAGAIN` - The message queue is non-blocking, and there is no room on the queue for another message as specified by the mq_maxmsg. `EINTR` - The message queue is blocking. While the process was waiting for free space on the queue, a signal arrived that interrupted the wait.

DESCRIPTION:

The mq_send() function adds the message pointed to by the argument msg_ptr to the message queue specified by mqdes. Each message is assigned a priority , from 0 to MQ_PRIO_MAX. MQ_PRIO_MAX is defined in <limits.h> and must be at least 32. Messages are added to the queue in order of their priority. The highest priority message is at the front of the queue.

The maximum number of messages that a message queue may accept is specified at creation by the mq_maxmsg field of the attribute structure. If this amount is exceeded, the behavior of the process is determined according to what oflag was used when the message queue was opened. If the queue was opened with O_NONBLOCK flag set, then the EAGAIN error is returned. If the O_NONBLOCK flag was not set, the process blocks and waits for space on the queue, unless it is interrupted by a signal.

Upon successful completion, the mq_send () function returns a value of zero. Otherwise, no message is enqueued, the function returns -1, and errno is set to indicate the error.

NOTES:

If the specified message queue is not full, mq_send inserts the message at the position indicated by the msg_prio argument.

16.4.5 mq_receive - Receive a Message from a Message Queue

CALLING SEQUENCE:

```
#include <mqueue.h>

size_t mq_receive(
  mqd_t         mqdes,
  char         *msg_ptr,
  size_t        msg_len,
  unsigned int *msg_prio
);
```

STATUS CODES:

`EBADF` - The descriptor does not represent a valid message queue, or the queue was opened for write only O_WRONLY `EMSGSIZE` - The msg_len is less than the mq_msgsize attribute of the message queue `EAGAIN` - The message queue is non-blocking, and the queue is empty `EINTR` - The message queue is blocking. While the process was waiting for a message to arrive on the queue, a signal arrived that interrupted the wait.

DESCRIPTION:

The mq_receive function is used to receive the oldest of the highest priority message(s) from the message queue specified by mqdes. The messages are received in FIFO order within the priorities. The received message's priority is stored in the location referenced by the msg_prio. If the msg_prio is a NULL, the priority is discarded. The message is removed and stored in an area pointed to by msg_ptr whose length is of msg_len. The msg_len must be at least equal to the mq_msgsize attribute of the message queue.

The blocking behavior of the message queue is set by O_NONBLOCK at mq_open or by setting O_NONBLOCK in mq_flags in a call to mq_setattr. If this is a blocking queue, the process blocks and waits on an empty queue. If this a non-blocking queue, the process does not block.

Upon successful completion, mq_receive returns the length of the selected message in bytes and the message is removed from the queue. Otherwise, no message is removed from the queue, the function returns a value of -1, and sets errno to indicate the error.

NOTES:

If the size of the buffer in bytes, specified by the msg_len argument, is less than the mq_msgsize attribute of the message queue, the function fails and returns an error

16.4.6 mq_notify - Notify Process that a Message is Available

CALLING SEQUENCE:

```
#include <mqueue.h>

int mq_notify(
  mqd_t                    mqdes,
  const struct sigevent *notification
);
```

STATUS CODES:

`EBADF` - The descriptor does not refer to a valid message queue `EBUSY` - A notification request is already attached to the queue

DESCRIPTION:

If the argument notification is not NULL, this function registers the calling process to be notified of message arrival at an empty message queue associated with the specified message queue descriptor, mqdes.

Every message queue has the ability to notify one (and only one) process whenever the queue's state changes from empty (0 messages) to nonempty. This means that the process does not have to block or constantly poll while it waits for a message. By calling mq_notify, a notification request is attached to a message queue. When a message is received by an empty queue, if there are no processes blocked and waiting for the message, then the queue notifies the requesting process of a message arrival. There is only one signal sent by the message queue, after that the notification request is de-registered and another process can attach its notification request. After receipt of a notification, a process must re-register if it wishes to be notified again.

If there is a process blocked and waiting for the message, that process gets the message, and notification is not be sent. Only one process can have a notification request attached to a message queue at any one time. If another process attempts to register a notification request, it fails. You can de-register for a message queue by passing a NULL to mq_notify; this removes any notification request attached to the queue. Whenever the message queue is closed, all notification attachments are removed.

Upon successful completion, mq_notify returns a value of zero; otherwise, the function returns a value of -1 and sets errno to indicate the error.

NOTES:

It is possible for another process to receive the message after the notification is sent but before the notified process has sent its receive request.

16.4.7 mq_setattr - Set Message Queue Attributes

CALLING SEQUENCE:

```
#include <mqueue.h>

int mq_setattr(
  mqd_t                 mqdes,
  const struct mq_attr *mqstat,
  struct mq_attr       *omqstat
);
```

STATUS CODES:

`EBADF` - The message queue descriptor does not refer to a valid, open queue. `EINVAL` - The mq_flag value is invalid.

DESCRIPTION:

The mq_setattr function is used to set attributes associated with the open message queue description referenced by the message queue descriptor specified by mqdes. The *omqstat represents the old or previous attributes. If omqstat is non-NULL, the function mq_setattr() stores, in the location referenced by omqstat, the previous message queue attributes and the current queue status. These values are the same as would be returned by a call to mq_getattr() at that point.

There is only one mq_attr.mq_flag which can be altered by this call. This is the flag that deals with the blocking and non-blocking behavior of the message queue. If the flag is set then the message queue is non-blocking, and requests to send or receive do not block while waiting for resources. If the flag is not set, then message send and receive may involve waiting for an empty queue or waiting for a message to arrive.

Upon successful completion, the function returns a value of zero and the attributes of the message queue have been changed as specified. Otherwise, the message queue attributes is unchanged, and the function returns a value of -1 and sets errno to indicate the error.

NOTES:

All other fields in the mq_attr are ignored by this call.

16.4.8 mq_getattr - Get Message Queue Attributes

CALLING SEQUENCE:

```
#include <mqueue.h>
int mq_getattr(
  mqd_t mqdes,
  struct mq_attr *mqstat
);
```

STATUS CODES:

`EBADF` - The message queue descriptor does not refer to a valid, open message queue.

DESCRIPTION:

The mqdes argument specifies a message queue descriptor. The mq_getattr function is used to get status information and attributes of the message queue associated with the message queue descriptor. The results are returned in the mq_attr structure referenced by the mqstat argument. All of these attributes are set at create time, except the blocking/non-blocking behavior of the message queue which can be dynamically set by using mq_setattr. The attribute mq_curmsg is set to reflect the number of messages on the queue at the time that mq_getattr was called.

Upon successful completion, the mq_getattr function returns zero. Otherwise, the function returns -1 and sets errno to indicate the error.

NOTES:

17 Thread Manager

17.1 Introduction

The thread manager implements the functionality required of the thread manager as defined by POSIX 1003.1b-1996. This standard requires that a compliant operating system provide the facilties to manage multiple threads of control and defines the API that must be provided.

The services provided by the thread manager are:

- `pthread_attr_init` - Initialize a Thread Attribute Set
- `pthread_attr_destroy` - Destroy a Thread Attribute Set
- `pthread_attr_setdetachstate` - Set Detach State
- `pthread_attr_getdetachstate` - Get Detach State
- `pthread_attr_setstacksize` - Set Thread Stack Size
- `pthread_attr_getstacksize` - Get Thread Stack Size
- `pthread_attr_setstackaddr` - Set Thread Stack Address
- `pthread_attr_getstackaddr` - Get Thread Stack Address
- `pthread_attr_setscope` - Set Thread Scheduling Scope
- `pthread_attr_getscope` - Get Thread Scheduling Scope
- `pthread_attr_setinheritsched` - Set Inherit Scheduler Flag
- `pthread_attr_getinheritsched` - Get Inherit Scheduler Flag
- `pthread_attr_setschedpolicy` - Set Scheduling Policy
- `pthread_attr_getschedpolicy` - Get Scheduling Policy
- `pthread_attr_setschedparam` - Set Scheduling Parameters
- `pthread_attr_getschedparam` - Get Scheduling Parameters
- `pthread_create` - Create a Thread
- `pthread_exit` - Terminate the Current Thread
- `pthread_detach` - Detach a Thread
- `pthread_join` - Wait for Thread Termination
- `pthread_self` - Get Thread ID
- `pthread_equal` - Compare Thread IDs
- `pthread_once` - Dynamic Package Initialization
- `pthread_setschedparam` - Set Thread Scheduling Parameters
- `pthread_getschedparam` - Get Thread Scheduling Parameters

17.2 Background

17.2.1 Thread Attributes

Thread attributes are utilized only at thread creation time. A thread attribute structure may be initialized and passed as an argument to the `pthread_create` routine.

stack address is the address of the optionally user specified stack area for this thread. If this value is NULL, then RTEMS allocates the memory for the thread stack from the RTEMS Workspace Area. Otherwise, this is the user specified address for the memory to be used for the thread's stack. Each thread must have a distinct stack area. Each processor family has different alignment rules which should be followed.

stack size is the minimum desired size for this thread's stack area. If the size of this area as specified by the stack size attribute is smaller than the minimum for this processor family and the stack is not user specified, then RTEMS will automatically allocate a stack of the minimum size for this processor family.

contention scope specifies the scheduling contention scope. RTEMS only supports the PTHREAD_SCOPE_PROCESS scheduling contention scope.

scheduling inheritance
specifies whether a user specified or the scheduling policy and parameters of the currently executing thread are to be used. When this is PTHREAD_INHERIT_SCHED, then the scheduling policy and parameters of the currently executing thread are inherited by the newly created thread.

scheduling policy and parameters
specify the manner in which the thread will contend for the processor. The scheduling parameters are interpreted based on the specified policy. All policies utilize the thread priority parameter.

17.3 Operations

There is currently no text in this section.

17.4 Services

This section details the thread manager's services. A subsection is dedicated to each of this manager's services and describes the calling sequence, related constants, usage, and status codes.

17.4.1 pthread_attr_init - Initialize a Thread Attribute Set

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_attr_init(
  pthread_attr_t *attr
);
```

STATUS CODES:

EINVAL The attribute pointer argument is invalid.

DESCRIPTION:

The `pthread_attr_init` routine initializes the thread attributes object specified by `attr` with the default value for all of the individual attributes.

NOTES:

The settings in the default attributes are implementation defined. For RTEMS, the default attributes are as follows:

- stackadr is not set to indicate that RTEMS is to allocate the stack memory.
- stacksize is set to `PTHREAD_MINIMUM_STACK_SIZE`.
- contentionscope is set to `PTHREAD_SCOPE_PROCESS`.
- inheritsched is set to `PTHREAD_INHERIT_SCHED` to indicate that the created thread inherits its scheduling attributes from its parent.
- detachstate is set to `PTHREAD_CREATE_JOINABLE`.

17.4.2 pthread_attr_destroy - Destroy a Thread Attribute Set

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_attr_destroy(
  pthread_attr_t *attr
);
```

STATUS CODES:

EINVAL	The attribute pointer argument is invalid.
EINVAL	The attribute set is not initialized.

DESCRIPTION:

The `pthread_attr_destroy` routine is used to destroy a thread attributes object. The behavior of using an attributes object after it is destroyed is implementation dependent.

NOTES:

NONE

17.4.3 pthread_attr_setdetachstate - Set Detach State

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_attr_setdetachstate(
  pthread_attr_t *attr,
  int             detachstate
);
```

STATUS CODES:

EINVAL	The attribute pointer argument is invalid.
EINVAL	The attribute set is not initialized.
EINVAL	The detachstate argument is invalid.

DESCRIPTION:

The `pthread_attr_setdetachstate` routine is used to value of the `detachstate` attribute. This attribute controls whether the thread is created in a detached state.

The `detachstate` can be either `PTHREAD_CREATE_DETACHED` or `PTHREAD_CREATE_JOINABLE`. The default value for all threads is `PTHREAD_CREATE_JOINABLE`.

NOTES:

If a thread is in a detached state, then the use of the ID with the `pthread_detach` or `pthread_join` routines is an error.

17.4.4 pthread_attr_getdetachstate - Get Detach State

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_attr_getdetachstate(
  const pthread_attr_t *attr,
  int                  *detachstate
);
```

STATUS CODES:

EINVAL	The attribute pointer argument is invalid.
EINVAL	The attribute set is not initialized.
EINVAL	The detatchstate pointer argument is invalid.

DESCRIPTION:

The `pthread_attr_getdetachstate` routine is used to obtain the current value of the `detachstate` attribute as specified by the `attr` thread attribute object.

NOTES:

NONE

17.4.5 pthread_attr_setstacksize - Set Thread Stack Size

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_attr_setstacksize(
  pthread_attr_t *attr,
  size_t          stacksize
);
```

STATUS CODES:

EINVAL	The attribute pointer argument is invalid.
EINVAL	The attribute set is not initialized.

DESCRIPTION:

The `pthread_attr_setstacksize` routine is used to set the `stacksize` attribute in the `attr` thread attribute object.

NOTES:

As required by POSIX, RTEMS defines the feature symbol `_POSIX_THREAD_ATTR_STACKSIZE` to indicate that this routine is supported.

If the specified stacksize is below the minimum required for this CPU (`PTHREAD_STACK_MIN`, then the stacksize will be set to the minimum for this CPU.

17.4.6 pthread_attr_getstacksize - Get Thread Stack Size

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_attr_getstacksize(
  const pthread_attr_t *attr,
  size_t               *stacksize
);
```

STATUS CODES:

EINVAL	The attribute pointer argument is invalid.
EINVAL	The attribute set is not initialized.
EINVAL	The stacksize pointer argument is invalid.

DESCRIPTION:

The `pthread_attr_getstacksize` routine is used to obtain the `stacksize` attribute in the `attr` thread attribute object.

NOTES:

As required by POSIX, RTEMS defines the feature symbol `_POSIX_THREAD_ATTR_STACKSIZE` to indicate that this routine is supported.

17.4.7 pthread_attr_setstackaddr - Set Thread Stack Address

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_attr_setstackaddr(
  pthread_attr_t *attr,
  void           *stackaddr
);
```

STATUS CODES:

EINVAL	The attribute pointer argument is invalid.
EINVAL	The attribute set is not initialized.

DESCRIPTION:

The `pthread_attr_setstackaddr` routine is used to set the `stackaddr` attribute in the `attr` thread attribute object.

NOTES:

As required by POSIX, RTEMS defines the feature symbol `_POSIX_THREAD_ATTR_STACKADDR` to indicate that this routine is supported.

It is imperative to the proper operation of the system that each thread have sufficient stack space.

17.4.8 pthread_attr_getstackaddr - Get Thread Stack Address

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_attr_getstackaddr(
  const pthread_attr_t  *attr,
  void                 **stackaddr
);
```

STATUS CODES:

EINVAL	The attribute pointer argument is invalid.
EINVAL	The attribute set is not initialized.
EINVAL	The stackaddr pointer argument is invalid.

DESCRIPTION:

The `pthread_attr_getstackaddr` routine is used to obtain the `stackaddr` attribute in the `attr` thread attribute object.

NOTES:

As required by POSIX, RTEMS defines the feature symbol `_POSIX_THREAD_ATTR_STACKADDR` to indicate that this routine is supported.

17.4.9 pthread_attr_setscope - Set Thread Scheduling Scope

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_attr_setscope(
  pthread_attr_t *attr,
  int             contentionscope
);
```

STATUS CODES:

EINVAL	The attribute pointer argument is invalid.
EINVAL	The attribute set is not initialized.
EINVAL	The contention scope specified is not valid.
ENOTSUP	The contention scope specified (PTHREAD_SCOPE_SYSTEM) is not supported.

DESCRIPTION:

The `pthread_attr_setscope` routine is used to set the contention scope field in the thread attribute object `attr` to the value specified by `contentionscope`.

The `contentionscope` must be either `PTHREAD_SCOPE_SYSTEM` to indicate that the thread is to be within system scheduling contention or `PTHREAD_SCOPE_PROCESS` indicating that the thread is to be within the process scheduling contention scope.

NOTES:

As required by POSIX, RTEMS defines the feature symbol `_POSIX_THREAD_PRIORITY_SCHEDULING` to indicate that the family of routines to which this routine belongs is supported.

17.4.10 pthread_attr_getscope - Get Thread Scheduling Scope

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_attr_getscope(
  const pthread_attr_t *attr,
  int                  *contentionscope
);
```

STATUS CODES:

EINVAL	The attribute pointer argument is invalid.
EINVAL	The attribute set is not initialized.
EINVAL	The contentionscope pointer argument is invalid.

DESCRIPTION:

The `pthread_attr_getscope` routine is used to obtain the value of the contention scope field in the thread attributes object `attr`. The current value is returned in `contentionscope`.

NOTES:

As required by POSIX, RTEMS defines the feature symbol `_POSIX_THREAD_PRIORITY_SCHEDULING` to indicate that the family of routines to which this routine belongs is supported.

17.4.11 pthread_attr_setinheritsched - Set Inherit Scheduler Flag

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_attr_setinheritsched(
  pthread_attr_t *attr,
  int             inheritsched
);
```

STATUS CODES:

EINVAL	The attribute pointer argument is invalid.
EINVAL	The attribute set is not initialized.
EINVAL	The specified scheduler inheritance argument is invalid.

DESCRIPTION:

The `pthread_attr_setinheritsched` routine is used to set the inherit scheduler field in the thread attribute object `attr` to the value specified by `inheritsched`.

The `contentionscope` must be either `PTHREAD_INHERIT_SCHED` to indicate that the thread is to inherit the scheduling policy and parameters fromthe creating thread, or `PTHREAD_EXPLICIT_SCHED` to indicate that the scheduling policy and parameters for this thread are to be set from the corresponding values in the attributes object. If `contentionscope` is `PTHREAD_INHERIT_SCHED`, then the scheduling attributes in the `attr` structure will be ignored at thread creation time.

NOTES:

As required by POSIX, RTEMS defines the feature symbol `_POSIX_THREAD_PRIORITY_SCHEDULING` to indicate that the family of routines to which this routine belongs is supported.

17.4.12 pthread_attr_getinheritsched - Get Inherit Scheduler Flag

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_attr_getinheritsched(
  const pthread_attr_t *attr,
  int                  *inheritsched
);
```

STATUS CODES:

EINVAL	The attribute pointer argument is invalid.
EINVAL	The attribute set is not initialized.
EINVAL	The inheritsched pointer argument is invalid.

DESCRIPTION:

The `pthread_attr_getinheritsched` routine is used to object the current value of the inherit scheduler field in the thread attribute object `attr`.

NOTES:

As required by POSIX, RTEMS defines the feature symbol `_POSIX_THREAD_PRIORITY_SCHEDULING` to indicate that the family of routines to which this routine belongs is supported.

17.4.13 pthread_attr_setschedpolicy - Set Scheduling Policy

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_attr_setschedpolicy(
  pthread_attr_t *attr,
  int             policy
);
```

STATUS CODES:

EINVAL	The attribute pointer argument is invalid.
EINVAL	The attribute set is not initialized.
ENOTSUP	The specified scheduler policy argument is invalid.

DESCRIPTION:

The `pthread_attr_setschedpolicy` routine is used to set the scheduler policy field in the thread attribute object `attr` to the value specified by `policy`.

Scheduling policies may be one of the following:

- `SCHED_DEFAULT`
- `SCHED_FIFO`
- `SCHED_RR`
- `SCHED_SPORADIC`
- `SCHED_OTHER`

The precise meaning of each of these is discussed elsewhere in this manual.

NOTES:

As required by POSIX, RTEMS defines the feature symbol `_POSIX_THREAD_PRIORITY_SCHEDULING` to indicate that the family of routines to which this routine belongs is supported.

17.4.14 pthread_attr_getschedpolicy - Get Scheduling Policy

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_attr_getschedpolicy(
  const pthread_attr_t *attr,
  int                  *policy
);
```

STATUS CODES:

EINVAL	The attribute pointer argument is invalid.
EINVAL	The attribute set is not initialized.
EINVAL	The specified scheduler policy argument pointer is invalid.

DESCRIPTION:

The `pthread_attr_getschedpolicy` routine is used to obtain the scheduler policy field from the thread attribute object `attr`. The value of this field is returned in `policy`.

NOTES:

As required by POSIX, RTEMS defines the feature symbol `_POSIX_THREAD_PRIORITY_SCHEDULING` to indicate that the family of routines to which this routine belongs is supported.

17.4.15 pthread_attr_setschedparam - Set Scheduling Parameters

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_attr_setschedparam(
  pthread_attr_t           *attr,
  const struct sched_param  param
);
```

STATUS CODES:

EINVAL	The attribute pointer argument is invalid.
EINVAL	The attribute set is not initialized.
EINVAL	The specified scheduler parameter argument is invalid.

DESCRIPTION:

The `pthread_attr_setschedparam` routine is used to set the scheduler parameters field in the thread attribute object `attr` to the value specified by `param`.

NOTES:

As required by POSIX, RTEMS defines the feature symbol `_POSIX_THREAD_PRIORITY_SCHEDULING` to indicate that the family of routines to which this routine belongs is supported.

17.4.16 pthread_attr_getschedparam - Get Scheduling Parameters

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_attr_getschedparam(
  const pthread_attr_t *attr,
  struct sched_param   *param
);
```

STATUS CODES:

EINVAL	The attribute pointer argument is invalid.
EINVAL	The attribute set is not initialized.
EINVAL	The specified scheduler parameter argument pointer is invalid.

DESCRIPTION:

The `pthread_attr_getschedparam` routine is used to obtain the scheduler parameters field from the thread attribute object `attr`. The value of this field is returned in `param`.

NOTES:

As required by POSIX, RTEMS defines the feature symbol `_POSIX_THREAD_PRIORITY_SCHEDULING` to indicate that the family of routines to which this routine belongs is supported.

17.4.17 pthread_create - Create a Thread

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_create(
  pthread_t             *thread,
  const pthread_attr_t  *attr,
  void                 (*start_routine)( void *),
  void                  *arg
);
```

STATUS CODES:

EINVAL	The attribute set is not initialized.
EINVAL	The user specified a stack address and the size of the area was not large enough to meet this processor's minimum stack requirements.
EINVAL	The specified scheduler inheritance policy was invalid.
ENOTSUP	The specified contention scope was PTHREAD_SCOPE_PROCESS.
EINVAL	The specified thread priority was invalid.
EINVAL	The specified scheduling policy was invalid.
EINVAL	The scheduling policy was SCHED_SPORADIC and the specified replenishment period is less than the initial budget.
EINVAL	The scheduling policy was SCHED_SPORADIC and the specified low priority is invalid.
EAGAIN	The system lacked the necessary resources to create another thread, or the self imposed limit on the total number of threads in a process PTHREAD_THREAD_MAX would be exceeded.
EINVAL	Invalid argument passed.

DESCRIPTION:

The `pthread_create` routine is used to create a new thread with the attributes specified by `attr`. If the `attr` argument is `NULL`, then the default attribute set will be used. Modification of the contents of `attr` after this thread is created does not have an impact on this thread.

The thread begins execution at the address specified by `start_routine` with `arg` as its only argument. If `start_routine` returns, then it is functionally equivalent to the thread executing the `pthread_exit` service.

Upon successful completion, the ID of the created thread is returned in the `thread` argument.

NOTES:

There is no concept of a single main thread in RTEMS as there is in a tradition UNIX system. POSIX requires that the implicit return of the main thread results in the same effects as if there were a call to `exit`. This does not occur in RTEMS.

The signal mask of the newly created thread is inherited from its creator and the set of pending signals for this thread is empty.

17.4.18 pthread_exit - Terminate the Current Thread

CALLING SEQUENCE:

```
#include <pthread.h>

void pthread_exit(
  void *status
);
```

STATUS CODES:

NONE

DESCRIPTION:

The `pthread_exit` routine is used to temrinate the calling thread. The `status` is made available to any successful join with the terminating thread.

When a thread returns from its start routine, it results in an implicit call to the `pthread_exit` routine with the return value of the function serving as the argument to `pthread_exit`.

NOTES:

Any cancellation cleanup handlers that hace been pushed and not yet popped shall be popped in reverse of the order that they were pushed. After all cancellation cleanup handlers have been executed, if the thread has any thread-specific data, destructors for that data will be invoked.

Thread termination does not release or free any application visible resources including byt not limited to mutexes, file descriptors, allocated memory, etc.. Similarly, exitting a thread does not result in any process-oriented cleanup activity.

There is no concept of a single main thread in RTEMS as there is in a tradition UNIX system. POSIX requires that the implicit return of the main thread results in the same effects as if there were a call to `exit`. This does not occur in RTEMS.

All access to any automatic variables allocated by the threads is lost when the thread exits. Thus references (i.e. pointers) to local variables of a thread should not be used in a global manner without care. As a specific example, a pointer to a local variable should NOT be used as the return value.

17.4.19 pthread_detach - Detach a Thread

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_detach(
  pthread_t thread
);
```

STATUS CODES:

ESRCH	The thread specified is invalid.
EINVAL	The thread specified is not a joinable thread.

DESCRIPTION:

The `pthread_detach` routine is used to to indicate that storage for `thread` can be reclaimed when the thread terminates without another thread joinging with it.

NOTES:

If any threads have previously joined with the specified thread, then they will remain joined with that thread. Any subsequent calls to `pthread_join` on the specified thread will fail.

17.4.20 pthread_join - Wait for Thread Termination

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_join(
  pthread_t    thread,
  void       **value_ptr
);
```

STATUS CODES:

ESRCH	The thread specified is invalid.
EINVAL	The thread specified is not a joinable thread.
EDEADLK	A deadlock was detected or thread is the calling thread.

DESCRIPTION:

The `pthread_join` routine suspends execution of the calling thread until `thread` terminates. If `thread` has already terminated, then this routine returns immediately. The value returned by `thread` (i.e. passed to `pthread_exit` is returned in `value_ptr`.

When this routine returns, then `thread` has been temrinated.

NOTES:

The results of multiple simultaneous joins on the same thread is undefined.

If any threads have previously joined with the specified thread, then they will remain joined with that thread. Any subsequent calls to `pthread_join` on the specified thread will fail.

If value_ptr is NULL, then no value is returned.

17.4.21 pthread_self - Get Thread ID

CALLING SEQUENCE:

```
#include <pthread.h>

pthread_t pthread_self( void );
```

STATUS CODES:

The value returned is the ID of the calling thread.

DESCRIPTION:

This routine returns the ID of the calling thread.

NOTES:

NONE

17.4.22 pthread_equal - Compare Thread IDs

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_equal(
   pthread_t t1,
   pthread_t t2
);
```

STATUS CODES:

zero	The thread ids are not equal.
non-zero	The thread ids are equal.

DESCRIPTION:

The `pthread_equal` routine is used to compare two thread IDs and determine if they are equal.

NOTES:

The behavior is undefined if the thread IDs are not valid.

17.4.23 pthread_once - Dynamic Package Initialization

CALLING SEQUENCE:

```
#include <pthread.h>

pthread_once_t once_control = PTHREAD_ONCE_INIT;

int pthread_once(
   pthread_once_t   *once_control,
   void            (*init_routine)(void)
);
```

STATUS CODES:

NONE

DESCRIPTION:

The `pthread_once` routine is used to provide controlled initialization of variables. The first call to `pthread_once` by any thread with the same `once_control` will result in the `init_routine` being invoked with no arguments. Subsequent calls to `pthread_once` with the same `once_control` will have no effect.

The `init_routine` is guaranteed to have run to completion when this routine returns to the caller.

NOTES:

The behavior of `pthread_once` is undefined if `once_control` is automatic storage (i.e. on a task stack) or is not initialized using `PTHREAD_ONCE_INIT`.

17.4.24 pthread_setschedparam - Set Thread Scheduling Parameters

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_setschedparam(
  pthread_t           thread,
  int                 policy,
  struct sched_param *param
);
```

STATUS CODES:

EINVAL	The scheduling parameters indicated by the parameter param is invalid.
EINVAL	The value specified by policy is invalid.
EINVAL	The scheduling policy was SCHED_SPORADIC and the specified replenishment period is less than the initial budget.
EINVAL	The scheduling policy was SCHED_SPORADIC and the specified low priority is invalid.
ESRCH	The thread indicated was invalid.

DESCRIPTION:

The `pthread_setschedparam` routine is used to set the scheduler parameters currently associated with the thread specified by `thread` to the policy specified by `policy`. The contents of `param` are interpreted based upon the `policy` argument.

NOTES:

As required by POSIX, RTEMS defines the feature symbol `_POSIX_THREAD_PRIORITY_SCHEDULING` to indicate that the family of routines to which this routine belongs is supported.

17.4.25 pthread_getschedparam - Get Thread Scheduling Parameters

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_getschedparam(
  pthread_t            thread,
  int                 *policy,
  struct sched_param *param
);
```

STATUS CODES:

EINVAL	The policy pointer argument is invalid.
EINVAL	The scheduling parameters pointer argument is invalid.
ESRCH	The thread indicated by the parameter thread is invalid.

DESCRIPTION:

The `pthread_getschedparam` routine is used to obtain the scheduler policy and parameters associated with `thread`. The current policy and associated parameters values returned in `policy` and `param`, respectively.

NOTES:

As required by POSIX, RTEMS defines the feature symbol `_POSIX_THREAD_PRIORITY_SCHEDULING` to indicate that the family of routines to which this routine belongs is supported.

18 Key Manager

18.1 Introduction

The key manager ...

The directives provided by the key manager are:

- `pthread_key_create` - Create Thread Specific Data Key
- `pthread_key_delete` - Delete Thread Specific Data Key
- `pthread_setspecific` - Set Thread Specific Key Value
- `pthread_getspecific` - Get Thread Specific Key Value

18.2 Background

There is currently no text in this section.

18.3 Operations

There is currently no text in this section.

18.4 Directives

This section details the key manager's directives. A subsection is dedicated to each of this manager's directives and describes the calling sequence, related constants, usage, and status codes.

18.4.1 pthread_key_create - Create Thread Specific Data Key

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_key_create(
  pthread_key_t *key,
  void (*destructor)( void )
);
```

STATUS CODES:

EAGAIN	There were not enough resources available to create another key.
ENOMEM	Insufficient memory exists to create the key.

18.4.2 pthread_key_delete - Delete Thread Specific Data Key

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_key_delete(
pthread_key_t key,
);
```

STATUS CODES:

EINVAL The key was invalid

DESCRIPTION:

NOTES:

18.4.3 pthread_setspecific - Set Thread Specific Key Value

CALLING SEQUENCE:

```
#include <pthread.h>

int pthread_setspecific(
pthread_key_t key,
const void *value
);
```

STATUS CODES:

EINVAL The specified key is invalid.

DESCRIPTION:

NOTES:

18.4.4 pthread_getspecific - Get Thread Specific Key Value

CALLING SEQUENCE:

```
#include <pthread.h>

void *pthread_getspecific(
pthread_key_t key
);
```

STATUS CODES:

NULL	There is no thread-specific data associated with the specified key.
non-NULL	The data associated with the specified key.

DESCRIPTION:

NOTES:

19 Thread Cancellation Manager

19.1 Introduction

The thread cancellation manager is ...

The directives provided by the thread cancellation manager are:

- `pthread_cancel` - Cancel Execution of a Thread
- `pthread_setcancelstate` - Set Cancelability State
- `pthread_setcanceltype` - Set Cancelability Type
- `pthread_testcancel` - Create Cancellation Point
- `pthread_cleanup_push` - Establish Cancellation Handler
- `pthread_cleanup_pop` - Remove Cancellation Handler

19.2 Background

There is currently no text in this section.

19.3 Operations

There is currently no text in this section.

19.4 Directives

This section details the thread cancellation manager's directives. A subsection is dedicated to each of this manager's directives and describes the calling sequence, related constants, usage, and status codes.

19.4.1 pthread_cancel - Cancel Execution of a Thread

CALLING SEQUENCE:

```
int pthread_cancel(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

19.4.2 pthread_setcancelstate - Set Cancelability State

CALLING SEQUENCE:

```
int pthread_setcancelstate(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

19.4.3 pthread_setcanceltype - Set Cancelability Type

CALLING SEQUENCE:

```
int pthread_setcanceltype(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

19.4.4 pthread_testcancel - Create Cancellation Point

CALLING SEQUENCE:

```
int pthread_testcancel(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

19.4.5 pthread_cleanup_push - Establish Cancellation Handler

CALLING SEQUENCE:

```
int pthread_cleanup_push(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

19.4.6 pthread_cleanup_pop - Remove Cancellation Handler

CALLING SEQUENCE:

```
int pthread_cleanup_push(
);
```

STATUS CODES:

E The

DESCRIPTION:

NOTES:

20 Services Provided by C Library (libc)

20.1 Introduction

This section lists the routines that provided by the Newlib C Library.

20.2 Standard Utility Functions (stdlib.h)

- `abort` - Abnormal termination of a program
- `abs` - Integer absolute value (magnitude)
- `assert` - Macro for Debugging Diagnostics
- `atexit` - Request execution of functions at program exit
- `atof` - String to double or float
- `atoi` - String to integer
- `bsearch` - Binary search
- `calloc` - Allocate space for arrays
- `div` - Divide two integers
- `ecvtbuf` - Double or float to string of digits
- `ecvt` - Double or float to string of digits (malloc result)
- `__env_lock` - Lock environment list for getenv and setenv
- `gvcvt` - Format double or float as string
- `exit` - End program execution
- `getenv` - Look up environment variable
- `labs` - Long integer absolute value (magnitude)
- `ldiv` - Divide two long integers
- `malloc` - Allocate memory
- `realloc` - Reallocate memory
- `free` - Free previously allocated memory
- `mallinfo` - Get information about allocated memory
- `__malloc_lock` - Lock memory pool for malloc and free
- `mbstowcs` - Minimal multibyte string to wide string converter
- `mblen` - Minimal multibyte length
- `mbtowc` - Minimal multibyte to wide character converter
- `qsort` - Sort an array
- `rand` - Pseudo-random numbers
- `strtod` - String to double or float
- `strtol` - String to long
- `strtoul` - String to unsigned long

- `system` - Execute command string
- `wcstombs` - Minimal wide string to multibyte string converter
- `wctomb` - Minimal wide character to multibyte converter

20.3 Character Type Macros and Functions (ctype.h)

- `isalnum` - Alphanumeric character predicate
- `isalpha` - Alphabetic character predicate
- `isascii` - ASCII character predicate
- `iscntrl` - Control character predicate
- `isdigit` - Decimal digit predicate
- `islower` - Lower-case character predicate
- `isprint` - Printable character predicates (isprint, isgraph)
- `ispunct` - Punctuation character predicate
- `isspace` - Whitespace character predicate
- `isupper` - Uppercase character predicate
- `isxdigit` - Hexadecimal digit predicate
- `toascii` - Force integers to ASCII range
- `tolower` - Translate characters to lower case
- `toupper` - Translate characters to upper case

20.4 Input and Output (stdio.h)

- `clearerr` - Clear file or stream error indicator
- `fclose` - Close a file
- `feof` - Test for end of file
- `ferror` - Test whether read/write error has occurred
- `fflush` - Flush buffered file output
- `fgetc` - Get a character from a file or stream
- `fgetpos` - Record position in a stream or file
- `fgets` - Get character string from a file or stream
- `fiprintf` - Write formatted output to file (integer only)
- `fopen` - Open a file
- `fdopen` - Turn an open file into a stream
- `fputc` - Write a character on a stream or file
- `fputs` - Write a character string in a file or stream
- `fread` - Read array elements from a file
- `freopen` - Open a file using an existing file descriptor
- `fseek` - Set file position

- `fsetpos` - Restore position of a stream or file
- `ftell` - Return position in a stream or file
- `fwrite` - Write array elements from memory to a file or stream
- `getc` - Get a character from a file or stream (macro)
- `getchar` - Get a character from standard input (macro)
- `gets` - Get character string from standard input (obsolete)
- `iprintf` - Write formatted output (integer only)
- `mktemp` - Generate unused file name
- `perror` - Print an error message on standard error
- `putc` - Write a character on a stream or file (macro)
- `putchar` - Write a character on standard output (macro)
- `puts` - Write a character string on standard output
- `remove` - Delete a file's name
- `rename` - Rename a file
- `rewind` - Reinitialize a file or stream
- `setbuf` - Specify full buffering for a file or stream
- `setvbuf` - Specify buffering for a file or stream
- `siprintf` - Write formatted output (integer only)
- `printf` - Write formatted output
- `scanf` - Scan and format input
- `tmpfile` - Create a temporary file
- `tmpnam` - Generate name for a temporary file
- `vprintf` - Format variable argument list

20.5 Strings and Memory (string.h)

- `bcmp` - Compare two memory areas
- `bcopy` - Copy memory regions
- `bzero` - Initialize memory to zero
- `index` - Search for character in string
- `memchr` - Find character in memory
- `memcmp` - Compare two memory areas
- `memcpy` - Copy memory regions
- `memmove` - Move possibly overlapping memory
- `memset` - Set an area of memory
- `rindex` - Reverse search for character in string
- `strcasecmp` - Compare strings ignoring case
- `strcat` - Concatenate strings
- `strchr` - Search for character in string

- `strcmp` - Character string compare
- `strcoll` - Locale specific character string compare
- `strcpy` - Copy string
- `strcspn` - Count chars not in string
- `strerror` - Convert error number to string
- `strlen` - Character string length
- `strlwr` - Convert string to lower case
- `strncasecmp` - Compare strings ignoring case
- `strncat` - Concatenate strings
- `strncmp` - Character string compare
- `strncpy` - Counted copy string
- `strpbrk` - Find chars in string
- `strrchr` - Reverse search for character in string
- `strspn` - Find initial match
- `strstr` - Find string segment
- `strtok` - Get next token from a string
- `strupr` - Convert string to upper case
- `strxfrm` - Transform string

20.6 Signal Handling (signal.h)

- `raise` - Send a signal
- `signal` - Specify handler subroutine for a signal

20.7 Time Functions (time.h)

- `asctime` - Format time as string
- `clock` - Cumulative processor time
- `ctime` - Convert time to local and format as string
- `difftime` - Subtract two times
- `gmtime` - Convert time to UTC (GMT) traditional representation
- `localtime` - Convert time to local representation
- `mktime` - Convert time to arithmetic representation
- `strftime` - Flexible calendar time formatter
- `time` - Get current calendar time (as single number)

20.8 Locale (locale.h)

- `setlocale` - Select or query locale

20.9 Reentrant Versions of Functions

- Equivalent for errno variable:
    - `errno_r` - XXX
- Locale functions:
    - `localeconv_r` - XXX
    - `setlocale_r` - XXX
- Equivalents for stdio variables:
    - `stdin_r` - XXX
    - `stdout_r` - XXX
    - `stderr_r` - XXX
- Stdio functions:
    - `fdopen_r` - XXX
    - `perror_r` - XXX
    - `tempnam_r` - XXX
    - `fopen_r` - XXX
    - `putchar_r` - XXX
    - `tmpnam_r` - XXX
    - `getchar_r` - XXX
    - `puts_r` - XXX
    - `tmpfile_r` - XXX
    - `gets_r` - XXX
    - `remove_r` - XXX
    - `vfprintf_r` - XXX
    - `iprintf_r` - XXX
    - `rename_r` - XXX
    - `vsnprintf_r` - XXX
    - `mkstemp_r` - XXX
    - `snprintf_r` - XXX
    - `vsprintf_r` - XXX
    - `mktemp_t` - XXX
    - `sprintf_r` - XXX
- Signal functions:
    - `init_signal_r` - XXX
    - `signal_r` - XXX
    - `kill_r` - XXX
    - `_sigtramp_r` - XXX
    - `raise_r` - XXX
- Stdlib functions:

        - calloc_r - XXX
        - mblen_r - XXX
        - srand_r - XXX
        - dtoa_r - XXX
        - mbstowcs_r - XXX
        - strtod_r - XXX
        - free_r - XXX
        - mbtowc_r - XXX
        - strtol_r - XXX
        - getenv_r - XXX
        - memalign_r - XXX
        - strtoul_r - XXX
        - mallinfo_r - XXX
        - mstats_r - XXX
        - system_r - XXX
        - malloc_r - XXX
        - rand_r - XXX
        - wcstombs_r - XXX
        - malloc_r - XXX
        - realloc_r - XXX
        - wctomb_r - XXX
        - malloc_stats_r - XXX
        - setenv_r - XXX
    - String functions:
        - strtok_r - XXX
    - System functions:
        - close_r - XXX
        - link_r - XXX
        - unlink_r - XXX
        - execve_r - XXX
        - lseek_r - XXX
        - wait_r - XXX
        - fcntl_r - XXX
        - open_r - XXX
        - write_r - XXX
        - fork_r - XXX
        - read_r - XXX
        - fstat_r - XXX
        - sbrk_r - XXX

    - `gettimeofday_r` - XXX
    - `stat_r` - XXX
    - `getpid_r` - XXX
    - `times_r` - XXX
- Time function:
    - `asctime_r` - XXX

20.10 Miscellaneous Macros and Functions

- `unctrl` - Return printable representation of a character

20.11 Variable Argument Lists

- Stdarg (stdarg.h):
    - `va_start` - XXX
    - `va_arg` - XXX
    - `va_end` - XXX
- Vararg (varargs.h):
    - `va_alist` - XXX
    - `va_start-trad` - XXX
    - `va_arg-trad` - XXX
    - `va_end-trad` - XXX

20.12 Reentrant System Calls

- `open_r` - XXX
- `close_r` - XXX
- `lseek_r` - XXX
- `read_r` - XXX
- `write_r` - XXX
- `fork_r` - XXX
- `wait_r` - XXX
- `stat_r` - XXX
- `fstat_r` - XXX
- `link_r` - XXX
- `unlink_r` - XXX
- `sbrk_r` - XXX

21 Services Provided by the Math Library (libm)

21.1 Introduction

This section lists the routines that provided by the Newlib Math Library (libm).

21.2 Standard Math Functions (math.h)

- `acos` - Arccosine
- `acosh` - Inverse hyperbolic cosine
- `asin` - Arcsine
- `asinh` - Inverse hyperbolic sine
- `atan` - Arctangent
- `atan2` - Arctangent of y/x
- `atanh` - Inverse hyperbolic tangent
- `jN` - Bessel functions (jN and yN)
- `cbrt` - Cube root
- `copysign` - Sign of Y and magnitude of X
- `cosh` - Hyperbolic cosine
- `erf` - Error function (erf and erfc)
- `exp` - Exponential
- `expm1` - Exponential of x and - 1
- `fabs` - Absolute value (magnitude)
- `floor` - Floor and ceiling (floor and ceil)
- `fmod` - Floating-point remainder (modulo)
- `frexp` - Split floating-point number
- `gamma` - Logarithmic gamma function
- `hypot` - Distance from origin
- `ilogb` - Get exponent
- `infinity` - Floating infinity
- `isnan` - Check type of number
- `ldexp` - Load exponent
- `log` - Natural logarithms
- `log10` - Base 10 logarithms
- `log1p` - Log of 1 + X
- `matherr` - Modifiable math error handler
- `modf` - Split fractional and integer parts
- `nan` - Floating Not a Number

- `nextafter` - Get next representable number
- `pow` - X to the power Y
- `remainder` - remainder of X divided by Y
- `scalbn` - scalbn
- `sin` - Sine or cosine (sin and cos)
- `sinh` - Hyperbolic sine
- `sqrt` - Positive square root
- `tan` - Tangent
- `tanh` - Hyperbolic tangent

22 Status of Implementation

This chapter provides an overview of the status of the implementation of the POSIX API for RTEMS. The *POSIX 1003.1b Compliance Guide* provides more detailed information regarding the implementation of each of the numerous functions, constants, and macros specified by the POSIX 1003.1b standard.

RTEMS supports many of the process and user/group oriented services in a "single user/single process" manner. This means that although these services may be of limited usefulness or functionality, they are provided and do work in a coherent manner. This is significant when porting existing code from UNIX to RTEMS.

- Implementation
    - The current implementation of `dup()` is insufficient.
    - FIFOs `mkfifo()` are not currently implemented.
    - Asynchronous IO is not implemented.
    - The `flockfile()` family is not implemented
    - getc/putc unlocked family is not implemented
    - Shared Memory is not implemented
    - Mapped Memory is not implemented
    - NOTES:
        - For Shared Memory and Mapped Memory services, it is unclear what level of support is appropriate and possible for RTEMS.
- Functional Testing
    - Tests for unimplemented services
- Performance Testing
    - There are no POSIX Performance Tests.
- Documentation
    - Many of the service description pages are not complete in this manual. These need to be completed and information added to the background and operations sections.
    - Example programs (not just tests) would be very nice.

Command and Variable Index

_

_exit 14

A

access 92
aio_cancel 128
aio_error 126
aio_fsync 130
aio_read 123
aio_return 127
aio_suspend 129
aio_write 124
alarm 35
asctime_r 163

C

cfgetispeed 132
cfgetospeed 133
cfsetispeed 134
cfsetospeed 135
chdir 71
chmod 93
chown 96
clock_getres 244
clock_gettime 241
clock_settime 243
close 112
closedir 70
creat 76
ctermid 58
ctime_r 164

D

dup 110
dup2 111

E

execl 5
execle 7
execlp 9
execv 6
execve 8
execvp 10

F

fchdir 72
fchmod 94
fcntl 116
fdatasync 120
fdopen 149
fileno 148
flockfile 150
fork 4
fpathconf 102
fstat 90
fsync 119
ftruncate 98
ftrylockfile 151
funlockfile 152

G

getc_unlocked 153
getchar_unlocked 154
getcwd 73
getdents 95
getegid 45
getenv 56
geteuid 43
getgid 44
getgrgid 170
getgrgid_r 171
getgrnam 172
getgrnam_r 173
getgroups 48
getlogin 49
getlogin_r 50
getpgrp 51
getpid 40
getppid 41
getpwnam 176
getpwnam_r 177
getpwuid 174
getpwuid_r 175
gettimeofday 247
getuid 42
gmtime_r 165

I

isatty 61

K

kill 27

L

link 79
lio_listio 125
localtime_r 166
longjmp 158
lseek 118
lstat 91

M

mkdir 82
mkfifo 83
mknod 104
mlock 226
mlockall 224
mmap 228
mount 121
mprotect 230
mq_attr 256
mq_close 262
mq_getattr 269
mq_notify 266
mq_open 260
mq_receive 265
mq_send 264
mq_setattr 268
mq_unlink 263
mqd_t 256
msync 231
munlock 227
munlockall 225
munmap 229

N

nanosleep 246

O

open 74
opendir 65

P

pathconf 100
pause 30
pipe 109
pthread_atfork 11
pthread_attr_destroy 274
pthread_attr_getdetachstate 276
pthread_attr_getinheritsched 284
pthread_attr_getschedparam 288
pthread_attr_getschedpolicy 286
pthread_attr_getscope 282
pthread_attr_getstackaddr 280
pthread_attr_getstacksize 278
pthread_attr_init 273
pthread_attr_setdetachstate 275
pthread_attr_setinheritsched 283
pthread_attr_setschedparam 287
pthread_attr_setschedpolicy 285
pthread_attr_setscope 281
pthread_attr_setstackaddr 279
pthread_attr_setstacksize 277
pthread_cancel 306
pthread_cleanup_pop 311
pthread_cleanup_push 310
pthread_cond_broadcast 219
pthread_cond_destroy 217
pthread_cond_init 216
pthread_cond_signal 218
pthread_cond_timedwait 221
pthread_cond_wait 220
pthread_condattr_destroy 213
pthread_condattr_getpshared 215
pthread_condattr_init 212
pthread_condattr_setpshared 214
pthread_create 289
pthread_detach 292
pthread_equal 295
pthread_exit 291
pthread_getschedparam 298
pthread_join 293
pthread_kill 24
pthread_mutex_destroy 204
pthread_mutex_getprioceiling 210
pthread_mutex_init 203
pthread_mutex_lock 205
pthread_mutex_setprioceiling 209
pthread_mutex_timedlock 207
pthread_mutex_trylock 206
pthread_mutex_unlock 208
pthread_mutexattr_destroy 196
pthread_mutexattr_getprioceiling 200
pthread_mutexattr_getprotocol 198
pthread_mutexattr_getpshared 202
pthread_mutexattr_init 195
pthread_mutexattr_setprioceiling 199
pthread_mutexattr_setprotocol 197
pthread_mutexattr_setpshared 201
pthread_once 296
pthread_self 294
pthread_setcancelstate 307
pthread_setcanceltype 308
pthread_setschedparam 297
pthread_sigmask 26
pthread_testcancel 309
putc_unlocked 155
putchar_unlocked 156

R

rand_r ... 167
read ... 113
readdir ... 66
readlink ... 81
rename ... 87
rewinddir ... 67
rmdir ... 85

S

scandir ... 68
sched_get_priority_max ... 238
sched_get_priority_min ... 237
sched_rr_get_interval ... 239
sched_yield ... 240
sem_close ... 185
sem_destroy ... 182
sem_getvalue ... 191
sem_init ... 181
sem_open ... 183
sem_post ... 190
sem_t ... 179
sem_timedwait ... 189
sem_trywait ... 188
sem_unlink ... 186
sem_wait ... 187
setenv ... 57
setgid ... 47
setjmp ... 157
setlocale ... 147
setpgid ... 53
setsid ... 52
setuid ... 46
shm_open ... 232
shm_unlink ... 233
sigaction ... 23
sigaddset ... 18
sigdelset ... 19
sigemptyset ... 22
sigfillset ... 20
sigismember ... 21
siglongjmp ... 160
sigpending ... 28
sigprocmask ... 25
sigqueue ... 34
sigsetjmp ... 159
sigsuspend ... 29
sigtimedwait ... 33
sigwait ... 31
sigwaitinfo ... 32
sleep ... 245
stat ... 89
strtok_r ... 162
symlink ... 80
sysconf ... 62

T

tcdrain ... 139
tcflow ... 141
tcflush ... 140
tcgetattr ... 136
tcgetpgrp ... 142
tcsendbreak ... 138
tcsetattr ... 137
tcsetpgrp ... 143
telldir ... 69
time ... 248
times ... 55
truncate ... 99
ttyname ... 59
ttyname_r ... 60
tzset ... 161

U

umask ... 78
uname ... 54
unlink ... 84
unmount ... 122
utime ... 97

W

wait ... 12
waitpid ... 13
write ... 115

Concept Index

A

acquire ownership of file stream 150
add a signal to a signal set 18
associate stream with file descriptor 149
asynchronous file synchronization 130
asynchronous read 123
asynchronous write 124

B

broadcast a condition variable 219

C

cancel asynchronous i/o request 128
cancel execution of a thread 306
change access and/or modification times of an inode 97
change memory protection 230
changes file mode. 93
changes permissions of a file 94
changes the current working directory 71, 72
changes the owner and/or group of a file. 96
check permissions for a file 92
close a message queue 262
close a named semaphore 185
closes a file. 112
compare thread ids 295
create a directory 104
create a new file or rewrite an existing one 76
create a process 4
create a thread 289
create an inter 109
create cancellation point 309
create session and set process group id 52
creates a link to a file 79
creates a symbolic link to a file 80

D

delay process execution 245
delay with high resolution 246
delete a directory 85
delete a signal from a signal set 19
destroy a condition variable 217
destroy a condition variable attribute set 213
destroy a mutex 204
destroy a mutex attribute set 196
destroy a thread attribute set 274
destroy an unnamed semaphore 182
detach a thread 292
determine if file descriptor is terminal 61
determine terminal device name 59
discards terminal data 140
duplicates an open file descriptor 110, 111
dynamic package initialization 296
dynamically set the priority ceiling 209

E

empty a signal set 22
ends directory read operation 70
establish cancellation handler 310
examine and change process blocked signals 25
examine and change signal action 23
examine and change thread blocked signals 26
examine pending signals 28
execute a file 5, 6, 7, 8, 9, 10

F

fill a signal set 20

G

generate terminal pathname 58
get character from stdin without locking 154
get character without locking 153
get clock resolution 244
get configurable system variables 62
get detach state 276
get directory entries 95
get effective group id 45
get effective user id 43
get environment variables 56
get group file entry for id 170
get group file entry for name 172
get inherit scheduler flag 284
get maximum priority value 238
get message queue attributes 269
get minimum priority value 237
get parent process id 41
get password file entry for uid 174
get process group id 51
get process id 40
get process shared attribute 215
get process times 55
get real group id 44
get scheduling parameters 288
get scheduling policy 286
get supplementary group ids 48
get system name 54
get the blocking protocol 198
get the current priority ceiling 210
get the priority ceiling 200
get the time of day 247
get the value of a semaphore 191
get the visibility 202

get thread id 294
get thread scheduling parameters 298
get thread scheduling scope 282
get thread stack address 280
get thread stack size 278
get time in seconds 248
get timeslicing quantum 239
get user id 42
get user name 49
get user name, reentrant 50
gets configuration values for files 100, 102
gets current working directory 73
gets file status 90, 91
gets foreground process group id 142
gets information about a file 89
gets terminal attributes 136

I

initialize a condition variable 216
initialize a condition variable attribute set 212
initialize a mutex 203
initialize a mutex attribute set 195
initialize a thread attribute set 273
initialize an unnamed semaphore 181
initialize time conversion information 161
is signal a member of a signal set 21

L

list directed i/o 125
lock a mutex 205
lock a mutex with timeout 207
lock a range of the process address space 226
lock the address space of a process 224

M

makes a directory 82
makes a fifo special file 83
manipulates an open file descriptor 116
map process addresses to a memory object 228
memory object synchronization 231
mount a file system 121

N

non 158, 160, 188
notify process that a message is available 266

O

obtain file descriptor number for this file 148
obtain the name of a symbolic link destination .. 81
obtain time of day 241
open a directory 65
open a message queue 260
open a named semaphore 183
open a shared memory object 232
opens a file 74

P

password file entry for name 176
poll to acquire ownership of file stream 151
poll to lock a mutex 206
put character to stdin without locking 156
put character without locking 155

Q

queue a signal to a process 34

R

reads a directory 66
reads from a file 113
reads terminal input baud rate 132
reads terminal output baud rate 133
receive a message from a message queue 265
reentrant determine terminal device name 60
reentrant extract token from string 162
reentrant get group file entry 171
reentrant get group file entry for name 173
reentrant get password file entry for name 177
reentrant get password file entry for uid 175
reentrant get user name 50
reentrant local time conversion 166
reentrant random number generation 167
reentrant struct tm to ascii time conversion ... 163
reentrant time_t to ascii time conversion 164
reentrant utc time conversion 165
register fork handlers 11
release ownership of file stream 152
remove a message queue 263
remove a shared memory object 233
remove cancellation handler 311
removes a directory entry 84
renames a file 87
reposition read/write file offset 118
resets the readdir() pointer 67
retrieve error status of asynchronous i/o operation 126
retrieve return status asynchronous i/o operation 127
return current location in directory stream 69

S

save context for non 157
save context with signal status for non 159
scan a directory for matching entries 68
schedule alarm 35
send a message to a message queue 264
send a signal to a process 27
send a signal to a thread 24
sends a break to a terminal 138
set cancelability state 307
set cancelability type 308
set detach state 275
set environment variables 57
set group id 47
set inherit scheduler flag 283
set message queue attributes 268
set process group id for job control 53
set process shared attribute 214
set scheduling parameters 287
set scheduling policy 285
set terminal attributes 137
set the blocking protocol 197
set the current locale 147
set the priority ceiling 199
set the visibility 201
set thread scheduling parameters 297
set thread scheduling scope 281
set thread stack address 279
set thread stack size 277
set time of day 243
set user id 46
sets a file creation mask. 78
sets foreground process group id 143
sets terminal input baud rate 134
sets terminal output baud rate 135
signal a condition variable 218
suspend process execution 30
suspends/restarts terminal output 141
synchronize file complete in 119
synchronize file in 120
synchronously accept a signal 31, 32
synchronously accept a signal with timeout 33

T

terminate a process 14
terminate the current thread 291
truncate a file to a specified length 98, 99

U

unlink a semaphore 186
unlock a mutex 208
unlock a range of the process address space ... 227
unlock a semaphore 190
unlock the address space of a process 225
unmap previously mapped addresses 229
unmount file systems 122

W

wait for a signal 29
wait for asynchronous i/o request 129
wait for process termination 12, 13
wait for thread termination 293
wait on a condition variable 220
wait on a semaphore 187
wait on a semaphore for a specified time 189
wait with timeout a condition variable 221
waits for all output to be transmitted to the terminal. 139
writes to a file 115

Y

yield the processor 240